



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
		DNU					E29				
		DNU					F29				
		RREF TL					F30				
GXB L1		GXB_TX_L8n					G27				
GXB L1		GXB_TX_L8p					G28				
GXB L1		GXB_RX_L8p,GXB_REFCLK_L8p					H30				
GXB L1		GXB_RX_L8n,GXB_REFCLK_L8n					H29				
GXB L1		GXB_TX_L7n					J27				
GXB L1		GXB_TX_L7p					J28				
GXB L1		GXB_RX_L7p,GXB_REFCLK_L7p					K30				
GXB L1		GXB_RX_L7n,GXB_REFCLK_L7n					K29				
GXB L1		GXB_TX_L6n					L27				
GXB L1		GXB_TX_L6p					L28				
GXB L1		GXB_RX_L6p,GXB_REFCLK_L6p					M30				
GXB L1		GXB_RX_L6n,GXB_REFCLK_L6n					M29				
GXB L1		REFCLK2Ln					R23				
GXB L1		REFCLK2Lp					R22				
GXB L0		REFCLK1Ln					U23				
GXB L0		REFCLK1Lp					U22				
GXB L0		GXB_TX_L5n					N27				
GXB L0		GXB_TX_L5p					N28				
GXB L0		GXB_RX_L5p,GXB_REFCLK_L5p					P30				
GXB L0		GXB_RX_L5n,GXB_REFCLK_L5n					P29				
GXB L0		GXB_TX_L4n					R27				
GXB L0		GXB_TX_L4p					R28				
GXB L0		GXB_RX_L4p,GXB_REFCLK_L4p					T30				
GXB L0		GXB_RX_L4n,GXB_REFCLK_L4n					T29				
GXB L0		GXB_TX_L3n					U27				
GXB L0		GXB_TX_L3p					U28				
GXB L0		GXB_RX_L3p,GXB_REFCLK_L3p					V30				
GXB L0		GXB_RX_L3n,GXB_REFCLK_L3n					V29				
GXB L0		GXB_TX_L2n					W27				
GXB L0		GXB_TX_L2p					W28				
GXB L0		GXB_RX_L2p,GXB_REFCLK_L2p					Y30				
GXB L0		GXB_RX_L2n,GXB_REFCLK_L2n					Y29				
GXB L0		GXB_TX_L1n					AA27				
GXB L0		GXB_TX_L1p					AA28				
GXB L0		GXB_RX_L1p,GXB_REFCLK_L1p					AB30				
GXB L0		GXB_RX_L1n,GXB_REFCLK_L1n					AB29				
GXB L0		GXB_TX_L0n					AC27				
GXB L0		GXB_TX_L0p					AC28				
GXB L0		GXB_RX_L0p,GXB_REFCLK_L0p					AD30				
GXB L0		GXB_RX_L0n,GXB_REFCLK_L0n					AD29				
GXB L0		REFCLK0Ln					W23				
GXB L0		REFCLK0Lp					W22				
		DNU					AB26				
3A		TDO		TDO			AF30				
3A		TMS		TMS			AG30				
3A		TCK		TCK			AG29				
3A		TDI		TDI			AF29				
3A		DCCLK		DCCLK			AJ29				
3A		rCSO		DATA4			AA25				
3A		AS_DATA3		DATA3			AH30				
3A		AS_DATA2		DATA2			AJ30				
3A		AS_DATA1		DATA1			AK29				
3A		AS_DATA0,ASDO		DATA0			AK28				
3A	VREFB3AN0	IO	RZQ_0		DIFFIO_TX_B1n	DIFFOUT_B1n	AF28				
3A	VREFB3AN0	IO			DIFFIO_TX_B1p	DIFFOUT_B1p	AG28	DO1B			
3A	VREFB3AN0	IO	CLK0n		DIFFIO_RX_B2n	DIFFOUT_B2n	AF27	DO1B			
3A	VREFB3AN0	IO	CLK0p		DIFFIO_RX_B2p	DIFFOUT_B2p	AG27	DO1B			
3A	VREFB3AN0	IO			DIFFIO_TX_B3n	DIFFOUT_B3n	AE27				
3A	VREFB3AN0	IO			DIFFIO_TX_B3p	DIFFOUT_B3p	AE26	DO1B			
3A	VREFB3AN0	IO	CLK1n		DIFFIO_RX_B4n	DIFFOUT_B4n	AH28	DO3n1B/QK1B			
3A	VREFB3AN0	IO	CLK1p		DIFFIO_RX_B4p	DIFFOUT_B4p	AJ28	DO3n1B/CQ1B/CQn1B/QKn1B			
3A	VREFB3AN0	IO	FPLL_B1_CLKOUT1,FPLL_B1_CLKOUTn		DIFFIO_TX_B5n	DIFFOUT_B5n	AJ27				
3A	VREFB3AN0	IO	FPLL_B1_CLKOUT0,FPLL_B1_CLKOUTp,FPLL_B1_FB0		DIFFIO_TX_B5p	DIFFOUT_B5p	AK27	DO1B			
3A	VREFB3AN0	IO	FPLL_B1_CLKOUT3,FPLL_B1_FBn		DIFFIO_RX_B6n	DIFFOUT_B6n	AB25	DO1B			
3A	VREFB3AN0	IO	FPLL_B1_CLKOUT2,FPLL_B1_FBp,FPLL_B1_FB1		DIFFIO_RX_B6p	DIFFOUT_B6p	AC25	DO1B			
3A	VREFB3AN0	IO	VREFB3AN0				AD25				
3A	VREFB3AN0	IO					AE25	DO1B			
3A	VREFB3AN0	IO	CLK2n		DIFFIO_RX_B7n	DIFFOUT_B7n	AG26	DO1B			
3A	VREFB3AN0	IO	CLK2p		DIFFIO_RX_B7p	DIFFOUT_B7p	AH25	DO1B			
3A	VREFB3AN0	IO			DIFFIO_TX_B8n	DIFFOUT_B8n	AK26				
3A	VREFB3AN0	IO			DIFFIO_TX_B8p	DIFFOUT_B8p	AK25	DO2B			
3A	VREFB3AN0	IO	CLK3n		DIFFIO_RX_B9n	DIFFOUT_B9n	AF25	DO2B			
3A	VREFB3AN0	IO	CLK3p		DIFFIO_RX_B9p	DIFFOUT_B9p	AG25	DO2B			
3A	VREFB3AN0	IO			DIFFIO_TX_B10n	DIFFOUT_B10n	AB23				
3A	VREFB3AN0	IO			DIFFIO_TX_B10p	DIFFOUT_B10p	AB24	DO2B			
3A	VREFB3AN0	IO			DIFFIO_RX_B11n	DIFFOUT_B11n	AJ25	DO3n2B/QK2B			
3A	VREFB3AN0	IO			DIFFIO_RX_B11p	DIFFOUT_B11p	AJ25	DO3n2B/CQ2B/CQn2B/QKn2B			
3A	VREFB3AN0	IO			DIFFIO_TX_B12n	DIFFOUT_B12n	AC24				
3A	VREFB3AN0	IO			DIFFIO_TX_B12p	DIFFOUT_B12p	AD24	DO2B			
3A	VREFB3AN0	IO			DIFFIO_RX_B13n	DIFFOUT_B13n	AF24	DO2B			
3A	VREFB3AN0	IO			DIFFIO_RX_B13p	DIFFOUT_B13p	AG24	DO2B			
3A	VREFB3AN0	IO			DIFFIO_TX_B14n	DIFFOUT_B14n	AD23				
3A	VREFB3AN0	IO			DIFFIO_TX_B14p	DIFFOUT_B14p	AE23	DO2B			
3A	VREFB3AN0	IO			DIFFIO_RX_B15n	DIFFOUT_B15n	AJ24	DO2B			
3A	VREFB3AN0	IO			DIFFIO_RX_B15p	DIFFOUT_B15p	AK24	DO2B			
3D	VREFB3DN0	IO			DIFFIO_TX_B70n	DIFFOUT_B70n	AC22				
3D	VREFB3DN0	IO			DIFFIO_TX_B70p	DIFFOUT_B70p	AD22	DO3B	DO1B		
3D	VREFB3DN0	IO			DIFFIO_RX_B71n	DIFFOUT_B71n	AA22	DO3B	DO1B		
3D	VREFB3DN0	IO			DIFFIO_RX_B71p	DIFFOUT_B71p	AB22	DO3B	DO1B		



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
3D	VREFB3DN0	IO			DIFFIO_TX_B72n	DIFFOUT_B72n	AB21				
3D	VREFB3DN0	IO			DIFFIO_TX_B72p	DIFFOUT_B72p	AC21	DO3B	DO1B		
3D	VREFB3DN0	IO			DIFFIO_RX_B73n	DIFFOUT_B73n	AG23	DO3n3B/OK3B	DO1B		
3D	VREFB3DN0	IO			DIFFIO_RX_B73p	DIFFOUT_B73p	AH23	DO33B/CQ3B/CQn3B/OKn3B	DO1B		
3D	VREFB3DN0	IO			DIFFIO_TX_B74n	DIFFOUT_B74n	AD21				
3D	VREFB3DN0	IO			DIFFIO_TX_B74p	DIFFOUT_B74p	AE22	DO3B	DO1B		
3D	VREFB3DN0	IO			DIFFIO_RX_B75n	DIFFOUT_B75n	AF22	DO3B	DO1B		
3D	VREFB3DN0	IO			DIFFIO_RX_B75p	DIFFOUT_B75p	AG22	DO3B	DO1B		
3D	VREFB3DN0	IO	VREFB3DN0				AA21				
3D	VREFB3DN0	IO					Y20	DO3B	DO1B		
3D	VREFB3DN0	IO	CLK4n		DIFFIO_RX_B76n	DIFFOUT_B76n	AH22	DO3B	DO1B		
3D	VREFB3DN0	IO	CLK4p		DIFFIO_RX_B76p	DIFFOUT_B76p	AJ22	DO3B	DO1B		
3D	VREFB3DN0	IO			DIFFIO_TX_B77n	DIFFOUT_B77n	AD20				
3D	VREFB3DN0	IO			DIFFIO_TX_B77p	DIFFOUT_B77p	AE20	DO4B	DO1B		
3D	VREFB3DN0	IO			DIFFIO_RX_B78n	DIFFOUT_B78n	AF21	DO4B	DO1B		
3D	VREFB3DN0	IO			DIFFIO_RX_B78p	DIFFOUT_B78p	AG21	DO4B	DO1B		
3D	VREFB3DN0	IO			DIFFIO_TX_B79n	DIFFOUT_B79n	AA19				
3D	VREFB3DN0	IO	FPLL_BC_CLKOUT1,FPLL_BC_CLKOUTn		DIFFIO_TX_B79p	DIFFOUT_B79p	AH19	DO4B	DO1B		
3D	VREFB3DN0	IO	FPLL_BC_CLKOUT0,FPLL_BC_CLKOUTp,FPLL_BC_FB0		DIFFIO_RX_B79n	DIFFOUT_B79n	AG20	DO3nB/OK4B	DO3nB/OK1B		
3D	VREFB3DN0	IO			DIFFIO_RX_B80n	DIFFOUT_B80n	AD20	DO34B/CQ4B/CQn4B/OKn4B	DO31B/CQ1B/CQn1B/OKn1B		
3D	VREFB3DN0	IO	FPLL_BC_CLKOUT2,FPLL_BC_FBp,FPLL_BC_FB1		DIFFIO_RX_B80p	DIFFOUT_B80p	AH20				
3D	VREFB3DN0	IO			DIFFIO_TX_B81n	DIFFOUT_B81n	AA20	DO4B	DO1B		
3D	VREFB3DN0	IO			DIFFIO_TX_B81p	DIFFOUT_B81p	AB20	DO4B	DO1B		
3D	VREFB3DN0	IO	CLK6n		DIFFIO_RX_B82n	DIFFOUT_B82n	AJ21	DO4B	DO1B		
3D	VREFB3DN0	IO	CLK6p		DIFFIO_RX_B82p	DIFFOUT_B82p	AK22	DO4B	DO1B		
3D	VREFB3DN0	IO			DIFFIO_TX_B83n	DIFFOUT_B83n	AC19				
3D	VREFB3DN0	IO			DIFFIO_TX_B83p	DIFFOUT_B83p	AD19	DO4B	DO1B		
3D	VREFB3DN0	IO	CLK7n		DIFFIO_RX_B84n	DIFFOUT_B84n	AK20	DO4B	DO1B		
3D	VREFB3DN0	IO	CLK7p		DIFFIO_RX_B84p	DIFFOUT_B84p	AK21	DO4B	DO1B		
		VCCD_FPLL					W15				
		VCCA_FPLL					W16				
		DNU					Y16				
4D	VREFB4DN0	IO			DIFFIO_TX_B93n	DIFFOUT_B93n	AJ19				CS# 4D 1
4D	VREFB4DN0	IO			DIFFIO_TX_B93p	DIFFOUT_B93p	AK19	DO5B	DO2B		CS# 4D 0
4D	VREFB4DN0	IO			DIFFIO_RX_B94n	DIFFOUT_B94n	AD19	DO5B	DO2B		
4D	VREFB4DN0	IO			DIFFIO_RX_B94p	DIFFOUT_B94p	AG19	DO5B	DO2B		A 4D 15
4D	VREFB4DN0	IO			DIFFIO_TX_B95n	DIFFOUT_B95n	AC18				ODT 4D 1
4D	VREFB4DN0	IO			DIFFIO_TX_B95p	DIFFOUT_B95p	AD18	DO5B	DO2B		ODT 4D 0
4D	VREFB4DN0	IO			DIFFIO_RX_B96n	DIFFOUT_B96n	AH19	DO5nB/OK5B	DO2B		WE# 4D
4D	VREFB4DN0	IO			DIFFIO_RX_B96p	DIFFOUT_B96p	AH18	DO55B/CQ5B/CQn5B/OKn5B	DO2B		CAS# 4D
4D	VREFB4DN0	IO			DIFFIO_TX_B97n	DIFFOUT_B97n	AA18				RAS# 4D
4D	VREFB4DN0	IO			DIFFIO_TX_B97p	DIFFOUT_B97p	AB18	DO5B	DO2B		BA 4D 2
4D	VREFB4DN0	IO			DIFFIO_RX_B98n	DIFFOUT_B98n	AE18	DO5B	DO2B		A 4D 10
4D	VREFB4DN0	IO			DIFFIO_RX_B98p	DIFFOUT_B98p	AF18	DO5B	DO2B		BA 4D 0
4D	VREFB4DN0	IO	VREFB4DN0				AD17				
4D	VREFB4DN0	IO					AE17	DO5B	DO2B		A 4D 14
4D	VREFB4DN0	IO			DIFFIO_RX_B99n	DIFFOUT_B99n	AA17	DO5B	DO2B		A 4D 13
4D	VREFB4DN0	IO			DIFFIO_RX_B99p	DIFFOUT_B99p	AB17	DO5B	DO2B		A 4D 12
4D	VREFB4DN0	IO			DIFFIO_TX_B100n	DIFFOUT_B100n	AA16				A 4D 11
4D	VREFB4DN0	IO			DIFFIO_TX_B100p	DIFFOUT_B100p	AB16	DO6B	DO2B		A 4D 9
4D	VREFB4DN0	IO			DIFFIO_RX_B101n	DIFFOUT_B101n	AG17	DO6B	DO2B		A 4D 8
4D	VREFB4DN0	IO			DIFFIO_RX_B101p	DIFFOUT_B101p	AH17	DO6B	DO2B		A 4D 7
4D	VREFB4DN0	IO			DIFFIO_TX_B102n	DIFFOUT_B102n	AC16				A 4D 6
4D	VREFB4DN0	IO			DIFFIO_TX_B102p	DIFFOUT_B102p	AD16	DO6B	DO2B		A 4D 5
4D	VREFB4DN0	IO			DIFFIO_RX_B103n	DIFFOUT_B103n	AJ18	DO5nB/OK6B	DO5n2B/OK2B		A 4D 4
4D	VREFB4DN0	IO			DIFFIO_RX_B103p	DIFFOUT_B103p	AK17	DO56B/CQ6B/CQn6B/OKn6B	DO52B/CQ2B/CQn2B/OKn2B		A 4D 3
4D	VREFB4DN0	IO			DIFFIO_TX_B104n	DIFFOUT_B104n	AG16	DO6B	DO2B		A 4D 2
4D	VREFB4DN0	IO			DIFFIO_TX_B104p	DIFFOUT_B104p	AG16	DO6B	DO2B		A 4D 1
4D	VREFB4DN0	IO			DIFFIO_RX_B105n	DIFFOUT_B105n	AA15	DO6B	DO2B		A 4D 0
4D	VREFB4DN0	IO			DIFFIO_RX_B105p	DIFFOUT_B105p	AB15	DO6B	DO2B		A 4D 0
4D	VREFB4DN0	IO			DIFFIO_TX_B106n	DIFFOUT_B106n	AC15				CKE 4D 1
4D	VREFB4DN0	IO			DIFFIO_TX_B106p	DIFFOUT_B106p	AD15	DO6B	DO2B		CKE 4D 0
4D	VREFB4DN0	IO			DIFFIO_RX_B107n	DIFFOUT_B107n	AJ16	DO6B	DO2B		CK# 4D
4D	VREFB4DN0	IO			DIFFIO_RX_B107p	DIFFOUT_B107p	AK16	DO6B	DO2B		CK 4D
4C	VREFB4CN0	IO			DIFFIO_TX_B108n	DIFFOUT_B108n	AA14				RESET# 4D
4C	VREFB4CN0	IO			DIFFIO_TX_B108p	DIFFOUT_B108p	AB14	DO7B	DO3B	DO1B	DO1 4C 8
4C	VREFB4CN0	IO			DIFFIO_RX_B109n	DIFFOUT_B109n	AG15	DO7B	DO3B	DO1B	DO1 4C 7
4C	VREFB4CN0	IO			DIFFIO_RX_B109p	DIFFOUT_B109p	AH15	DO7B	DO3B	DO1B	DO1 4C 6
4C	VREFB4CN0	IO			DIFFIO_TX_B110n	DIFFOUT_B110n	AE15				
4C	VREFB4CN0	IO			DIFFIO_TX_B110p	DIFFOUT_B110p	AF15	DO7B	DO3B	DO1B	DM1 4C
4C	VREFB4CN0	IO			DIFFIO_RX_B111n	DIFFOUT_B111n	AJ15	DO5n7B/OK7B	DO3B	DO1B	DO5#1 4C
4C	VREFB4CN0	IO			DIFFIO_RX_B111p	DIFFOUT_B111p	AK14	DO57B/CQ7B/CQn7B/OKn7B	DO3B	DO1B	DO5#1 4C
4C	VREFB4CN0	IO			DIFFIO_TX_B112n	DIFFOUT_B112n	AG14				
4C	VREFB4CN0	IO			DIFFIO_TX_B112p	DIFFOUT_B112p	AH14	DO7B	DO3B	DO1B	DO1 4C 5
4C	VREFB4CN0	IO			DIFFIO_RX_B113n	DIFFOUT_B113n	AD13	DO7B	DO3B	DO1B	DO1 4C 4
4C	VREFB4CN0	IO			DIFFIO_RX_B113p	DIFFOUT_B113p	AE13	DO7B	DO3B	DO1B	DO1 4C 3
4C	VREFB4CN0	IO	VREFB4CN0				AD14				
4C	VREFB4CN0	IO			DIFFIO_RX_B114n	DIFFOUT_B114n	AH13	DO7B	DO3B	DO1B	DO1 4C 2
4C	VREFB4CN0	IO			DIFFIO_RX_B114p	DIFFOUT_B114p	AJ13	DO7B	DO3B	DO1B	DO1 4C 1
4C	VREFB4CN0	IO			DIFFIO_TX_B115n	DIFFOUT_B115n	AC13				DO1 4C 0
4C	VREFB4CN0	IO			DIFFIO_TX_B115p	DIFFOUT_B115p	AD12	DO8B	DO3B	DO1B	DO2 4C 8
4C	VREFB4CN0	IO			DIFFIO_RX_B116n	DIFFOUT_B116n	AF12	DO8B	DO3B	DO1B	DO2 4C 7
4C	VREFB4CN0	IO			DIFFIO_RX_B116p	DIFFOUT_B116p	AF13	DO8B	DO3B	DO1B	DO2 4C 6
4C	VREFB4CN0	IO			DIFFIO_TX_B117n	DIFFOUT_B117n	AA13				
4C	VREFB4CN0	IO			DIFFIO_TX_B117p	DIFFOUT_B117p	AB13	DO8B	DO3B	DO1B	DM2 4C
4C	VREFB4CN0	IO			DIFFIO_RX_B118n	DIFFOUT_B118n	AG12	DO5n8B/OK8B	DO5n3B/OK3B	DO1B	DO5#2 4C
4C	VREFB4CN0	IO			DIFFIO_RX_B118p	DIFFOUT_B118p	AH12	DO58B/CQ8B/CQn8B/OKn8B	DO53B/CQ3B/CQn3B/OKn3B	DO1B	DO5#2 4C
4C	VREFB4CN0	IO			DIFFIO_TX_B119n	DIFFOUT_B119n	AJ12				
4C	VREFB4CN0	IO			DIFFIO_TX_B119p	DIFFOUT_B119p	AK12	DO8B	DO3B	DO1B	DO2 4C 5
4C	VREFB4CN0	IO			DIFFIO_RX_B120n	DIFFOUT_B120n	AB12	DO8B	DO3B	DO1B	DO2 4C 4
4C	VREFB4CN0	IO			DIFFIO_RX_B120p	DIFFOUT_B120p	AC12	DO8B	DO3B	DO1B	DO2 4C 3
4C	VREFB4CN0	IO			DIFFIO_TX_B121n	DIFFOUT_B121n	Y12				



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
4C	VREFB4CN0	IO			DIFFIO_TX_B121p	DIFFOUT_B121p	Y13	DO8B	DO3B	DQ1B	DO2_4C_2
4C	VREFB4CN0	IO			DIFFIO_RX_B122n	DIFFOUT_B122n	AG11	DO8B	DO3B	DQ1B	DO2_4C_1
4C	VREFB4CN0	IO			DIFFIO_RX_B122p	DIFFOUT_B122p	AH11	DO8B	DO3B	DQ1B	DO2_4C_0
4B	VREFB4BN0	IO			DIFFIO_TX_B123n	DIFFOUT_B123n	AD11	DO9B	DO4B	DQ1B	DO3_4B_8
4B	VREFB4BN0	IO			DIFFIO_RX_B124n	DIFFOUT_B124n	AA12	DO9B	DO4B	DQ1B	DO3_4B_7
4B	VREFB4BN0	IO			DIFFIO_RX_B124p	DIFFOUT_B124p	AB11	DO9B	DO4B	DQ1B	DO3_4B_6
4B	VREFB4BN0	IO			DIFFIO_TX_B125n	DIFFOUT_B125n	AA11	DO9B	DO4B	DQ1B	DO3_4B_5
4B	VREFB4BN0	IO			DIFFIO_TX_B125p	DIFFOUT_B125p	AA10	DO9B	DO4B	DQ1B	DM3_4B
4B	VREFB4BN0	IO			DIFFIO_RX_B126n	DIFFOUT_B126n	AK11	DQS9B/QK9B	DO4B	DQS1B/QK1B	DQS#3_4B
4B	VREFB4BN0	IO			DIFFIO_RX_B126p	DIFFOUT_B126p	AK10	DQS9B/CQ9B/CQn9B/QKn9B	DO4B	DQS1B/CQ1B/CQn1B	DQS3_4B
4B	VREFB4BN0	IO			DIFFIO_TX_B127n	DIFFOUT_B127n	AF10	DO9B	DO4B	DQ1B	DO3_4B_5
4B	VREFB4BN0	IO			DIFFIO_TX_B127p	DIFFOUT_B127p	AG10	DO9B	DO4B	DQ1B	DO3_4B_4
4B	VREFB4BN0	IO			DIFFIO_RX_B128n	DIFFOUT_B128n	AB10	DO9B	DO4B	DQ1B	DO3_4B_3
4B	VREFB4BN0	IO			DIFFIO_RX_B128p	DIFFOUT_B128p	AB9	DO9B	DO4B	DQ1B	DO3_4B_2
4B	VREFB4BN0	IO			DIFFIO_TX_B129n	DIFFOUT_B129n	AC10	DO9B	DO4B	DQ1B	DO3_4B_1
4B	VREFB4BN0	IO			DIFFIO_TX_B129p	DIFFOUT_B129p	AD10	DO9B	DO4B	DQ1B	DO3_4B_0
4B	VREFB4BN0	IO			DIFFIO_RX_B130n	DIFFOUT_B130n	AH9	DO9B	DO4B	DQ1B	DO3_4B_0
4B	VREFB4BN0	IO			DIFFIO_RX_B130p	DIFFOUT_B130p	AJ10	DO9B	DO4B	DQ1B	DO3_4B_0
4B	VREFB4BN0	IO			DIFFIO_TX_B131n	DIFFOUT_B131n	AE9	DO10B	DO4B	DQ1B	DO4_4B_8
4B	VREFB4BN0	IO			DIFFIO_TX_B131p	DIFFOUT_B131p	AF9	DO10B	DO4B	DQ1B	DO4_4B_7
4B	VREFB4BN0	IO			DIFFIO_RX_B132n	DIFFOUT_B132n	AJ9	DO10B	DO4B	DQ1B	DO4_4B_6
4B	VREFB4BN0	IO			DIFFIO_RX_B132p	DIFFOUT_B132p	AK8	DO10B	DO4B	DQ1B	DO4_4B_5
4B	VREFB4BN0	IO			DIFFIO_TX_B133n	DIFFOUT_B133n	AC9	DO10B	DO4B	DQ1B	DO4_4B_4
4B	VREFB4BN0	IO			DIFFIO_TX_B133p	DIFFOUT_B133p	AD9	DO10B	DO4B	DQ1B	DO4_4B_3
4B	VREFB4BN0	IO			DIFFIO_RX_B134n	DIFFOUT_B134n	AB8	DQS10B/QK10B	DO4B	DQS#4_4B	DO3#4_4B
4B	VREFB4BN0	IO			DIFFIO_RX_B134p	DIFFOUT_B134p	AB8	DQS10B/CQ10B/CQn10B/QKn10B	DO4B	DQS#4_4B	DO3#4_4B
4B	VREFB4BN0	IO			DIFFIO_TX_B135n	DIFFOUT_B135n	AG8	DO10B	DO4B	DQ1B	DO4_4B_5
4B	VREFB4BN0	IO			DIFFIO_TX_B135p	DIFFOUT_B135p	AH8	DO10B	DO4B	DQ1B	DO4_4B_4
4B	VREFB4BN0	IO			DIFFIO_RX_B136n	DIFFOUT_B136n	AJ7	DO10B	DO4B	DQ1B	DO4_4B_3
4B	VREFB4BN0	IO			DIFFIO_RX_B136p	DIFFOUT_B136p	AK7	DO10B	DO4B	DQ1B	DO4_4B_2
4B	VREFB4BN0	IO	VREFB4BN0				AD8	DO10B	DO4B	DQ1B	DO4_4B_1
4B	VREFB4BN0	IO					AE8	DO10B	DO4B	DQ1B	DO4_4B_0
4B	VREFB4BN0	IO			DIFFIO_RX_B137n	DIFFOUT_B137n	AC7	DO10B	DO4B	DQ1B	DO4_4B_0
4B	VREFB4BN0	IO			DIFFIO_RX_B137p	DIFFOUT_B137p	AH7	DO10B	DO4B	DQ1B	DO4_4B_0
4A	VREFB4AN0	IO		DATA10	DIFFIO_TX_B154n	DIFFOUT_B154n	AF7	DO11B	DO5B		
4A	VREFB4AN0	IO		DATA11	DIFFIO_TX_B154p	DIFFOUT_B154p	AG6	DO11B	DO5B		
4A	VREFB4AN0	IO		DATA5	DIFFIO_RX_B155n	DIFFOUT_B155n	AJ6	DO11B	DO5B		
4A	VREFB4AN0	IO		DATA6	DIFFIO_RX_B155p	DIFFOUT_B155p	AK6	DO11B	DO5B		
4A	VREFB4AN0	IO		DATA12	DIFFIO_TX_B156n	DIFFOUT_B156n	AH8	DO11B	DO5B		
4A	VREFB4AN0	IO		DATA13	DIFFIO_TX_B156p	DIFFOUT_B156p	AE7	DO11B	DO5B		
4A	VREFB4AN0	IO		DATA7	DIFFIO_RX_B157n	DIFFOUT_B157n	AK5	DQS11B/QK11B	DO5B		
4A	VREFB4AN0	IO		DATA8	DIFFIO_RX_B157p	DIFFOUT_B157p	AK4	DQS11B/CQ11B/CQn11B/QKn11B	DO5B		
4A	VREFB4AN0	IO		DATA14	DIFFIO_TX_B158n	DIFFOUT_B158n	AD7	DO11B	DO5B		
4A	VREFB4AN0	IO		DATA15	DIFFIO_TX_B158p	DIFFOUT_B158p	AE7	DO11B	DO5B		
4A	VREFB4AN0	IO		DATA9	DIFFIO_RX_B159n	DIFFOUT_B159n	AA6	DO11B	DO5B		
4A	VREFB4AN0	IO		CLKUSR	DIFFIO_RX_B159p	DIFFOUT_B159p	AB6	DO11B	DO5B		
4A	VREFB4AN0	IO	VREFB4AN0				AC6	DO11B	DO5B		
4A	VREFB4AN0	IO					AC7	DO11B	DO5B		
4A	VREFB4AN0	IO	CLK11n		DIFFIO_RX_B160n	DIFFOUT_B160n	AE6	DO11B	DO5B		
4A	VREFB4AN0	IO	CLK11p		DIFFIO_RX_B160p	DIFFOUT_B160p	AF6	DO11B	DO5B		
4A	VREFB4AN0	IO	FPLL_BR_CLKOUT1,FPLL_BR_CLKOUTn		DIFFIO_TX_B161n	DIFFOUT_B161n	AG5	DO12B	DO5B		
4A	VREFB4AN0	IO	FPLL_BR_CLKOUT0,FPLL_BR_CLKOUTp,FPLL_BR_FB0		DIFFIO_TX_B161p	DIFFOUT_B161p	AH5	DO12B	DO5B		
4A	VREFB4AN0	IO	FPLL_BR_CLKOUT3,FPLL_BR_FBn		DIFFIO_RX_B162n	DIFFOUT_B162n	AH4	DO12B	DO5B		
4A	VREFB4AN0	IO	FPLL_BR_CLKOUT2,FPLL_BR_FBp,FPLL_BR_FB1		DIFFIO_RX_B162p	DIFFOUT_B162p	AJ4	DO12B	DO5B		
4A	VREFB4AN0	IO			DIFFIO_TX_B163n	DIFFOUT_B163n	AD6	DO12B	DO5B		
4A	VREFB4AN0	IO			DIFFIO_TX_B163p	DIFFOUT_B163p	AE5	DO12B	DO5B		
4A	VREFB4AN0	IO	CLK10n		DIFFIO_RX_B164n	DIFFOUT_B164n	AJ3	DQS12B/QK12B	DQS#5B/QK5B		
4A	VREFB4AN0	IO	CLK10p		DIFFIO_RX_B164p	DIFFOUT_B164p	AK3	DQS12B/CQ12B/CQn12B/QKn12B	DQS#5B/CQ5B/CQn5B/QKn5B		
4A	VREFB4AN0	IO			DIFFIO_TX_B165n	DIFFOUT_B165n	AG4	DO12B	DO5B		
4A	VREFB4AN0	IO			DIFFIO_TX_B165p	DIFFOUT_B165p	AG3	DO12B	DO5B		
4A	VREFB4AN0	IO	CLK9n		DIFFIO_RX_B166n	DIFFOUT_B166n	AJ1	DO12B	DO5B		
4A	VREFB4AN0	IO	CLK9p		DIFFIO_RX_B166p	DIFFOUT_B166p	AK2	DO12B	DO5B		
4A	VREFB4AN0	IO			DIFFIO_TX_B167n	DIFFOUT_B167n	AE4	DO12B	DO5B		
4A	VREFB4AN0	IO	RZQ_1		DIFFIO_TX_B167p	DIFFOUT_B167p	AF4	DO12B	DO5B		
4A	VREFB4AN0	IO	CLK8n		DIFFIO_RX_B168n	DIFFOUT_B168n	AH2	DO12B	DO5B		
4A	VREFB4AN0	IO	CLK8p		DIFFIO_RX_B168p	DIFFOUT_B168p	AH1	DO12B	DO5B		
		RREF_BR					AF1				
		DNU					AF2				
		DNU					AG2				
GXB_R0		REFCLK0Rp					W9				
GXB_R0		REFCLK0Rn					W8				
GXB_R0		GXB_RX_R0n,GXB_REFCLK_R0n					AD2				
GXB_R0		GXB_RX_R0p,GXB_REFCLK_R0p					AD1				
GXB_R0		GXB_TX_R0p					AC3				
GXB_R0		GXB_TX_R0n					AC4				
GXB_R0		GXB_RX_R1n,GXB_REFCLK_R1n					AB2				
GXB_R0		GXB_RX_R1p,GXB_REFCLK_R1p					AB1				
GXB_R0		GXB_TX_R1p					AA3				
GXB_R0		GXB_TX_R1n					AA4				
GXB_R0		GXB_RX_R2n,GXB_REFCLK_R2n					Y2				
GXB_R0		GXB_RX_R2p,GXB_REFCLK_R2p					Y1				
GXB_R0		GXB_TX_R2p					W3				
GXB_R0		GXB_TX_R2n					W4				
GXB_R1		REFCLK2Rp					U9				
GXB_R1		REFCLK2Rn					U8				
GXB_R1		GXB_RX_R6n,GXB_REFCLK_R6n					V2				
GXB_R1		GXB_RX_R6p,GXB_REFCLK_R6p					V1				
GXB_R1		GXB_TX_R6p					U3				
GXB_R1		GXB_TX_R6n					U4				
GXB_R1		GXB_RX_R7n,GXB_REFCLK_R7n					T2				
GXB_R1		GXB_RX_R7p,GXB_REFCLK_R7p					T1				



Pin Information for the Arria® V 5AGXMB3 Device
Version 1.7
Note (1)

Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)	
GXB_R1		GXB_TX_R7p					R3					
GXB_R1		GXB_TX_R7n					R4					
GXB_R1		GXB_RX_R8n,GXB_REFCLK_R8n					F2					
GXB_R1		GXB_RX_R8p,GXB_REFCLK_R8p					P1					
GXB_R1		GXB_TX_R8n					N3					
GXB_R1		GXB_TX_R8n					N4					
GXB_R1		GXB_RX_R9n,GXB_REFCLK_R9n					M2					
GXB_R1		GXB_RX_R9p,GXB_REFCLK_R9p					M1					
GXB_R1		GXB_TX_R9p					L3					
GXB_R1		GXB_TX_R9n					L4					
GXB_R1		GXB_RX_R10n,GXB_REFCLK_R10n					K2					
GXB_R1		GXB_RX_R10p,GXB_REFCLK_R10p					J3					
GXB_R1		GXB_TX_R10p					J3					
GXB_R1		GXB_TX_R10n					J4					
GXB_R1		GXB_RX_R11n,GXB_REFCLK_R11n					H2					
GXB_R1		GXB_RX_R11p,GXB_REFCLK_R11p					H1					
GXB_R1		GXB_TX_R11p					G3					
GXB_R1		GXB_TX_R11n					G4					
GXB_R1		REFCLK3Rp					R9					
GXB_R1		REFCLK3Rn					R8					
7A		DNU					H5					
7A		GND					F5					
7A	VREFB7A0	IO	CLK12p		DIFFIO_RX_T1p	DIFFOUT_T1p	E1	DO1T		DO1T		
7A	VREFB7A0	IO	CLK12n		DIFFIO_RX_T1n	DIFFOUT_T1n	F1	DO1T		DO1T		
7A	VREFB7A0	IO	RZQ_5		DIFFIO_TX_T2p	DIFFOUT_T2p	E4	DO1T		DO1T		
7A	VREFB7A0	IO			DIFFIO_TX_T2n	DIFFOUT_T2n	E3					
7A	VREFB7A0	IO	CLK13p		DIFFIO_RX_T3p	DIFFOUT_T3p	D2	DO1T		DO1T		
7A	VREFB7A0	IO	CLK13n		DIFFIO_RX_T3n	DIFFOUT_T3n	D1	DO1T		DO1T		
7A	VREFB7A0	IO			DIFFIO_TX_T4p	DIFFOUT_T4p	D4	DO1T		DO1T		
7A	VREFB7A0	IO			DIFFIO_TX_T4n	DIFFOUT_T4n	D3					
7A	VREFB7A0	IO	CLK14p		DIFFIO_RX_T5p	DIFFOUT_T5p	A2	DQS1T/CQ1T/CQn1T/QKn1T		DQS1T/CQ1T/CQn1T/QKn1T		
7A	VREFB7A0	IO	CLK14n		DIFFIO_RX_T5n	DIFFOUT_T5n	B1	DQS1T/QK1T		DQS1T/QK1T		
7A	VREFB7A0	IO			DIFFIO_TX_T6p	DIFFOUT_T6p	C2	DO1T		DO1T		
7A	VREFB7A0	IO			DIFFIO_TX_T6n	DIFFOUT_T6n	C1					
7A	VREFB7A0	IO	FPLL_TR_CLKOUT2,FPLL_TR_FBp,FPLL_TR_FBn		DIFFIO_RX_T7p	DIFFOUT_T7p	A3	DO1T		DO1T		
7A	VREFB7A0	IO	FPLL_TR_CLKOUT3,FPLL_TR_FBn		DIFFIO_RX_T7n	DIFFOUT_T7n	B3	DO1T		DO1T		
7A	VREFB7A0	IO	FPLL_TR_CLKOUT,FPLL_TR_CLKOUTp,FPLL_TR_FB0		DIFFIO_TX_T8p	DIFFOUT_T8p	B4	DO1T		DO1T		
7A	VREFB7A0	IO	FPLL_TR_CLKOUT1,FPLL_TR_CLKOUTn		DIFFIO_TX_T8n	DIFFOUT_T8n	C4					
7A	VREFB7A0	IO	CLK15p		DIFFIO_RX_T9p	DIFFOUT_T9p	C5	DO2T		DO1T		
7A	VREFB7A0	IO	CLK15n		DIFFIO_RX_T9n	DIFFOUT_T9n	D5	DO2T		DO1T		
7A	VREFB7A0	IO					J6	DO2T		DO1T		
7A	VREFB7A0	IO	VREFB7A0				K6					
7A	VREFB7A0	IO	DEV_OE	DEV_OE	DIFFIO_RX_T10p	DIFFOUT_T10p	A5	DO2T		DO1T		
7A	VREFB7A0	IO	DEV_CLRn	DEV_CLRn	DIFFIO_RX_T10n	DIFFOUT_T10n	A4	DO2T		DO1T		
7A	VREFB7A0	IO			DIFFIO_TX_T11p	DIFFOUT_T11p	J7	DO2T		DO1T		
7A	VREFB7A0	IO			DIFFIO_TX_T11n	DIFFOUT_T11n	K7					
7A	VREFB7A0	IO	nPERSTLO		DIFFIO_RX_T12p	DIFFOUT_T12p	D6	DQS2T/CQ2T/CQn2T/QKn2T		DO1T		
7A	VREFB7A0	IO	CvP_CONFDONE		DIFFIO_RX_T12n	DIFFOUT_T12n	E6	DQS2T/QK2T		DO1T		
7A	VREFB7A0	IO	CRC_ERROR		DIFFIO_TX_T13p	DIFFOUT_T13p	G6	DO2T		DO1T		
7A	VREFB7A0	IO	PR_DONE		DIFFIO_TX_T13n	DIFFOUT_T13n	H6					
7A	VREFB7A0	IO	PR_REQUEST		DIFFIO_TX_T13n	DIFFOUT_T13n	H6					
7A	VREFB7A0	IO	INIT_DONE		DIFFIO_RX_T14p	DIFFOUT_T14p	A6	DO2T		DO1T		
7A	VREFB7A0	IO	nCEO		DIFFIO_RX_T14n	DIFFOUT_T14n	B6	DO2T		DO1T		
7A	VREFB7A0	IO	PR_ERROR		DIFFIO_TX_T15p	DIFFOUT_T15p	G7	DO2T		DO1T		
7A	VREFB7A0	IO	PR_READY		DIFFIO_TX_T15n	DIFFOUT_T15n	H7					
7B	VREFB7B0	IO			DIFFIO_RX_T32p	DIFFOUT_T32p	F8	DO3T		DO2T	DO4_7B_0	
7B	VREFB7B0	IO			DIFFIO_RX_T32n	DIFFOUT_T32n	G8	DO3T		DO2T	DO4_7B_1	
7B	VREFB7B0	IO					J8	DO3T		DO1T	DO4_7B_2	
7B	VREFB7B0	IO	VREFB7B0				K8					
7B	VREFB7B0	IO			DIFFIO_RX_T33p	DIFFOUT_T33p	E7	DO3T		DO2T	DO4_7B_3	
7B	VREFB7B0	IO			DIFFIO_RX_T33n	DIFFOUT_T33n	F7	DO3T		DO2T	DO4_7B_4	
7B	VREFB7B0	IO			DIFFIO_TX_T34p	DIFFOUT_T34p	G9	DO3T		DO2T	DO4_7B_5	
7B	VREFB7B0	IO			DIFFIO_TX_T34n	DIFFOUT_T34n	H9					
7B	VREFB7B0	IO			DIFFIO_RX_T35p	DIFFOUT_T35p	A7	DQS3T/CQ3T/CQn3T/QKn3T		DQS2T/CQ2T/CQn2T/QKn2T	DO1T	DO34_7B
7B	VREFB7B0	IO			DIFFIO_RX_T35n	DIFFOUT_T35n	A8	DQS3T/QK3T		DQS2T/QK2T	DO1T	DO34_7B
7B	VREFB7B0	IO			DIFFIO_TX_T36p	DIFFOUT_T36p	B7	DO3T		DO2T	DO1T	DM4_7B
7B	VREFB7B0	IO			DIFFIO_TX_T36n	DIFFOUT_T36n	C7					
7B	VREFB7B0	IO			DIFFIO_RX_T37p	DIFFOUT_T37p	C8	DO3T		DO2T	DO1T	DO4_7B_6
7B	VREFB7B0	IO			DIFFIO_RX_T37n	DIFFOUT_T37n	D8	DO3T		DO2T	DO1T	DO4_7B_7
7B	VREFB7B0	IO			DIFFIO_TX_T38p	DIFFOUT_T38p	J9	DO3T		DO2T	DO1T	DO4_7B_8
7B	VREFB7B0	IO			DIFFIO_TX_T38n	DIFFOUT_T38n	K9					
7B	VREFB7B0	IO			DIFFIO_RX_T39p	DIFFOUT_T39p	D9	DO4T		DO2T	DO1T	DO3_7B_0
7B	VREFB7B0	IO			DIFFIO_RX_T39n	DIFFOUT_T39n	E9	DO4T		DO2T	DO1T	DO3_7B_1
7B	VREFB7B0	IO			DIFFIO_TX_T40p	DIFFOUT_T40p	B10	DO4T		DO2T	DO1T	DO3_7B_2
7B	VREFB7B0	IO			DIFFIO_TX_T40n	DIFFOUT_T40n	B9					
7B	VREFB7B0	IO			DIFFIO_RX_T41p	DIFFOUT_T41p	A11	DO4T		DO2T	DO1T	DO3_7B_3
7B	VREFB7B0	IO			DIFFIO_RX_T41n	DIFFOUT_T41n	A10	DO4T		DO2T	DO1T	DO3_7B_4
7B	VREFB7B0	IO			DIFFIO_TX_T42p	DIFFOUT_T42p	J10	DO4T		DO2T	DO1T	DO3_7B_5
7B	VREFB7B0	IO			DIFFIO_TX_T42n	DIFFOUT_T42n	K10					
7B	VREFB7B0	IO			DIFFIO_RX_T43p	DIFFOUT_T43p	C10	DQS4T/CQ4T/CQn4T/QKn4T		DO2T	DQS1T/CQ1T/CQn1T	DO34_7B
7B	VREFB7B0	IO			DIFFIO_RX_T43n	DIFFOUT_T43n	D10	DQS4T/QK4T		DO2T	DQS1T/QK1T	DO34_7B
7B	VREFB7B0	IO			DIFFIO_TX_T44p	DIFFOUT_T44p	E10	DO4T		DO2T	DO1T	DM3_7B
7B	VREFB7B0	IO			DIFFIO_TX_T44n	DIFFOUT_T44n	F10					
7B	VREFB7B0	IO			DIFFIO_RX_T45p	DIFFOUT_T45p	C11	DO4T		DO2T	DO1T	DO3_7B_6
7B	VREFB7B0	IO			DIFFIO_RX_T45n	DIFFOUT_T45n	D11	DO4T		DO2T	DO1T	DO3_7B_7
7B	VREFB7B0	IO			DIFFIO_TX_T46p	DIFFOUT_T46p	G10	DO4T		DO2T	DO1T	DO3_7B_8
7B	VREFB7B0	IO			DIFFIO_TX_T46n	DIFFOUT_T46n	H10					
7C	VREFB7C0	IO			DIFFIO_RX_T47p	DIFFOUT_T47p	L11	DO5T		DO3T	DO1T	DO2_7C_0
7C	VREFB7C0	IO			DIFFIO_RX_T47n	DIFFOUT_T47n	K11	DO5T		DO3T	DO1T	DO2_7C_1
7C	VREFB7C0	IO			DIFFIO_TX_T48p	DIFFOUT_T48p	F11	DO5T		DO3T	DO1T	DO2_7C_2
7C	VREFB7C0	IO			DIFFIO_TX_T48n	DIFFOUT_T48n	G11					
7C	VREFB7C0	IO			DIFFIO_RX_T49p	DIFFOUT_T49p	B13	DO5T		DO3T	DO1T	DO2_7C_3
7C	VREFB7C0	IO			DIFFIO_RX_T49n	DIFFOUT_T49n	B12	DO5T		DO3T	DO1T	DO2_7C_4



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
7C	VREFB7CNO	IO			DIFFIO_TX_T50p	DIFFOOUT_T50p	D12	DO5T	DO3T	DO1T	DO2_7C_5
7C	VREFB7CNO	IO			DIFFIO_RX_T50n	DIFFOOUT_T50n	E12				
7C	VREFB7CNO	IO			DIFFIO_RX_T51p	DIFFOOUT_T51p	J12	DQS8T/CQ8T/CQn8T/QKn8T	DQS3T/CQ3T/CQn3T/QKn3T	DO1T	DO52_7C
7C	VREFB7CNO	IO			DIFFIO_RX_T51n	DIFFOOUT_T51n	K12	DQS8T/CQ8T/CQn8T/QKn8T	DQS3T/CQ3T/CQn3T/QKn3T	DO1T	DO52_7C
7C	VREFB7CNO	IO			DIFFIO_TX_T52p	DIFFOOUT_T52p	G12	DO5T	DO3T	DO1T	DM2_7C
7C	VREFB7CNO	IO			DIFFIO_TX_T52n	DIFFOOUT_T52n	H12				
7C	VREFB7CNO	IO			DIFFIO_RX_T53p	DIFFOOUT_T53p	C13	DO5T	DO3T	DO1T	DO2_7C_6
7C	VREFB7CNO	IO			DIFFIO_RX_T53n	DIFFOOUT_T53n	D13	DO5T	DO3T	DO1T	DO2_7C_7
7C	VREFB7CNO	IO			DIFFIO_TX_T54p	DIFFOOUT_T54p	E13	DO5T	DO3T	DO1T	DO2_7C_8
7C	VREFB7CNO	IO			DIFFIO_TX_T54n	DIFFOOUT_T54n	F13				
7C	VREFB7CNO	IO			DIFFIO_RX_T55p	DIFFOOUT_T55p	J14	DO6T	DO3T	DO1T	DO1_7C_0
7C	VREFB7CNO	IO			DIFFIO_RX_T55n	DIFFOOUT_T55n	K14	DO6T	DO3T	DO1T	DO1_7C_1
7C	VREFB7CNO	IO	VREFB7CNO				J13	DO6T	DO3T	DO1T	DO1_7C_2
7C	VREFB7CNO	IO					K13				
7C	VREFB7CNO	IO			DIFFIO_RX_T56p	DIFFOOUT_T56p	A14	DO6T	DO3T	DO1T	DO1_7C_3
7C	VREFB7CNO	IO			DIFFIO_RX_T56n	DIFFOOUT_T56n	A13	DO6T	DO3T	DO1T	DO1_7C_4
7C	VREFB7CNO	IO			DIFFIO_TX_T57p	DIFFOOUT_T57p	F14	DO6T	DO3T	DO1T	DO1_7C_5
7C	VREFB7CNO	IO			DIFFIO_TX_T57n	DIFFOOUT_T57n	G14				
7C	VREFB7CNO	IO			DIFFIO_RX_T58p	DIFFOOUT_T58p	C14	DQS8T/CQ8T/CQn8T/QKn8T	DO3T	DO1T	DO51_7C
7C	VREFB7CNO	IO			DIFFIO_RX_T58n	DIFFOOUT_T58n	D14	DQS8T/CQ8T/CQn8T/QKn8T	DO3T	DO1T	DO51_7C
7C	VREFB7CNO	IO			DIFFIO_TX_T59p	DIFFOOUT_T59p	G13	DO6T	DO3T	DO1T	DM1_7C
7C	VREFB7CNO	IO			DIFFIO_TX_T59n	DIFFOOUT_T59n	H13				
7C	VREFB7CNO	IO			DIFFIO_RX_T60p	DIFFOOUT_T60p	A15	DO6T	DO3T	DO1T	DO1_7C_6
7C	VREFB7CNO	IO			DIFFIO_RX_T60n	DIFFOOUT_T60n	B15	DO6T	DO3T	DO1T	DO1_7C_7
7C	VREFB7CNO	IO			DIFFIO_TX_T61p	DIFFOOUT_T61p	D15	DO6T	DO3T	DO1T	DO1_7C_8
7C	VREFB7CNO	IO			DIFFIO_TX_T61n	DIFFOOUT_T61n	E15				RESET#_7D
7D	VREFB7DNO	IO			DIFFIO_RX_T62p	DIFFOOUT_T62p	F15	DO7T	DO4T		CK#_7D
7D	VREFB7DNO	IO			DIFFIO_RX_T62n	DIFFOOUT_T62n	G15	DO7T	DO4T		CK#_7D
7D	VREFB7DNO	IO			DIFFIO_TX_T63p	DIFFOOUT_T63p	J16	DO7T	DO4T		CKE_7D_0
7D	VREFB7DNO	IO			DIFFIO_TX_T63n	DIFFOOUT_T63n	K16				CKE_7D_1
7D	VREFB7DNO	IO			DIFFIO_RX_T64p	DIFFOOUT_T64p	H15	DO7T	DO4T		A_7D_0
7D	VREFB7DNO	IO			DIFFIO_RX_T64n	DIFFOOUT_T64n	J15	DO7T	DO4T		A_7D_1
7D	VREFB7DNO	IO			DIFFIO_TX_T65p	DIFFOOUT_T65p	D16	DO7T	DO4T		A_7D_2
7D	VREFB7DNO	IO			DIFFIO_TX_T65n	DIFFOOUT_T65n	E16				A_7D_3
7D	VREFB7DNO	IO			DIFFIO_RX_T66p	DIFFOOUT_T66p	B16	DQS7T/CQ7T/CQn7T/QKn7T	DQS4T/CQ4T/CQn4T/QKn4T		A_7D_4
7D	VREFB7DNO	IO			DIFFIO_RX_T66n	DIFFOOUT_T66n	C16	DQS7T/CQ7T/CQn7T/QKn7T	DQS4T/CQ4T/CQn4T/QKn4T		A_7D_5
7D	VREFB7DNO	IO			DIFFIO_TX_T67p	DIFFOOUT_T67p	G16	DO7T	DO4T		A_7D_6
7D	VREFB7DNO	IO			DIFFIO_TX_T67n	DIFFOOUT_T67n	H16				A_7D_7
7D	VREFB7DNO	IO			DIFFIO_RX_T68p	DIFFOOUT_T68p	A17	DO7T	DO4T		A_7D_8
7D	VREFB7DNO	IO			DIFFIO_RX_T68n	DIFFOOUT_T68n	A16	DO7T	DO4T		A_7D_9
7D	VREFB7DNO	IO			DIFFIO_TX_T69p	DIFFOOUT_T69p	G17	DO7T	DO4T		A_7D_10
7D	VREFB7DNO	IO			DIFFIO_TX_T69n	DIFFOOUT_T69n	D17				A_7D_11
7D	VREFB7DNO	IO			DIFFIO_RX_T70p	DIFFOOUT_T70p	J17	DO8T	DO4T		A_7D_12
7D	VREFB7DNO	IO			DIFFIO_RX_T70n	DIFFOOUT_T70n	K17	DO8T	DO4T		A_7D_13
7D	VREFB7DNO	IO					J18	DO8T	DO4T		A_7D_14
7D	VREFB7DNO	IO	VREFB7DNO				K18				
7D	VREFB7DNO	IO			DIFFIO_RX_T71p	DIFFOOUT_T71p	D18	DO8T	DO4T		BA_7D_0
7D	VREFB7DNO	IO			DIFFIO_RX_T71n	DIFFOOUT_T71n	E18	DO8T	DO4T		BA_7D_1
7D	VREFB7DNO	IO			DIFFIO_TX_T72p	DIFFOOUT_T72p	F17	DO8T	DO4T		BA_7D_2
7D	VREFB7DNO	IO			DIFFIO_TX_T72n	DIFFOOUT_T72n	G17				RAS#_7D
7D	VREFB7DNO	IO			DIFFIO_RX_T73p	DIFFOOUT_T73p	B18	DQS8T/CQ8T/CQn8T/QKn8T	DO4T		CAS#_7D
7D	VREFB7DNO	IO			DIFFIO_RX_T73n	DIFFOOUT_T73n	C19	DQS8T/CQ8T/CQn8T/QKn8T	DO4T		WE#_7D
7D	VREFB7DNO	IO			DIFFIO_TX_T74p	DIFFOOUT_T74p	G18	DO8T	DO4T		ODT_7D_0
7D	VREFB7DNO	IO			DIFFIO_TX_T74n	DIFFOOUT_T74n	H18				ODT_7D_1
7D	VREFB7DNO	IO			DIFFIO_RX_T75p	DIFFOOUT_T75p	A19	DO8T	DO4T		A_7D_15
7D	VREFB7DNO	IO			DIFFIO_RX_T75n	DIFFOOUT_T75n	B19	DO8T	DO4T		
7D	VREFB7DNO	IO			DIFFIO_TX_T76p	DIFFOOUT_T76p	E19	DO8T	DO4T		CS#_7D_0
7D	VREFB7DNO	IO			DIFFIO_TX_T76n	DIFFOOUT_T76n	E19				CS#_7D_1
		VCCA_FPLL					M16				
		VCCD_FPLL					M15				
		DNU					K15				
8D	VREFB8DNO	IO	CLK19p		DIFFIO_RX_T85p	DIFFOOUT_T85p	F19	DO9T	DO5T		
8D	VREFB8DNO	IO	CLK19n		DIFFIO_RX_T85n	DIFFOOUT_T85n	G20	DO9T	DO5T		
8D	VREFB8DNO	IO			DIFFIO_TX_T86p	DIFFOOUT_T86p	H19	DO9T	DO5T		
8D	VREFB8DNO	IO			DIFFIO_TX_T86n	DIFFOOUT_T86n	K19				
8D	VREFB8DNO	IO	CLK18p		DIFFIO_RX_T87p	DIFFOOUT_T87p	J20	DO9T	DO5T		
8D	VREFB8DNO	IO	CLK18n		DIFFIO_RX_T87n	DIFFOOUT_T87n	K20	DO9T	DO5T		
8D	VREFB8DNO	IO			DIFFIO_TX_T88p	DIFFOOUT_T88p	F20	DO9T	DO5T		
8D	VREFB8DNO	IO			DIFFIO_TX_T88n	DIFFOOUT_T88n	F21				
8D	VREFB8DNO	IO	FPLL_TC_CLKOUT2_FPLL_TC_FBp_FPLL_TC_FB1		DIFFIO_RX_T89p	DIFFOOUT_T89p	C20	DQS9T/CQ9T/CQn9T/QKn9T	DQS5T/CQ5T/CQn5T/QKn5T		
8D	VREFB8DNO	IO	FPLL_TC_CLKOUT3_FPLL_TC_FBn		DIFFIO_RX_T89n	DIFFOOUT_T89n	D20	DQS9T/CQ9T/CQn9T/QKn9T	DQS5T/CQ5T/CQn5T/QKn5T		
8D	VREFB8DNO	IO	FPLL_TC_CLKOUT0_FPLL_TC_CLKOUTp_FPLL_TC_FB0		DIFFIO_TX_T90p	DIFFOOUT_T90p	E20	DO9T	DO5T		
8D	VREFB8DNO	IO	FPLL_TC_CLKOUT1_FPLL_TC_CLKOUTn		DIFFIO_TX_T90n	DIFFOOUT_T90n	H19				
8D	VREFB8DNO	IO	CLK17p		DIFFIO_RX_T91p	DIFFOOUT_T91p	A21	DO9T	DO5T		
8D	VREFB8DNO	IO	CLK17n		DIFFIO_RX_T91n	DIFFOOUT_T91n	B21	DO9T	DO5T		
8D	VREFB8DNO	IO			DIFFIO_TX_T92p	DIFFOOUT_T92p	D21	DO9T	DO5T		
8D	VREFB8DNO	IO			DIFFIO_TX_T92n	DIFFOOUT_T92n	E21				
8D	VREFB8DNO	IO	CLK16p		DIFFIO_RX_T93p	DIFFOOUT_T93p	D22	DO10T	DO5T		
8D	VREFB8DNO	IO	CLK16n		DIFFIO_RX_T93n	DIFFOOUT_T93n	E22	DO10T	DO5T		
8D	VREFB8DNO	IO			DIFFIO_TX_T94p	DIFFOOUT_T94p	J21	DO10T	DO5T		
8D	VREFB8DNO	IO	VREFB8DNO				K21				
8D	VREFB8DNO	IO			DIFFIO_RX_T94p	DIFFOOUT_T94p	J22	DO10T	DO5T		
8D	VREFB8DNO	IO			DIFFIO_RX_T94n	DIFFOOUT_T94n	K22	DO10T	DO5T		
8D	VREFB8DNO	IO			DIFFIO_TX_T95p	DIFFOOUT_T95p	G22	DO10T	DO5T		
8D	VREFB8DNO	IO			DIFFIO_TX_T95n	DIFFOOUT_T95n	H22				
8D	VREFB8DNO	IO			DIFFIO_RX_T96p	DIFFOOUT_T96p	B22	DQS10T/CQ10T/CQn10T/QKn10T	DO6T		
8D	VREFB8DNO	IO			DIFFIO_RX_T96n	DIFFOOUT_T96n	C22	DQS10T/CQ10T/CQn10T/QKn10T	DO6T		
8D	VREFB8DNO	IO			DIFFIO_TX_T97p	DIFFOOUT_T97p	G21	DO10T	DO5T		
8D	VREFB8DNO	IO			DIFFIO_TX_T97n	DIFFOOUT_T97n	H21				
8D	VREFB8DNO	IO			DIFFIO_RX_T98p	DIFFOOUT_T98p	F23	DO10T	DO5T		
8D	VREFB8DNO	IO			DIFFIO_RX_T98n	DIFFOOUT_T98n	G23	DO10T	DO5T		
8D	VREFB8DNO	IO			DIFFIO_TX_T99p	DIFFOOUT_T99p	C23	DO10T	DO5T		



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
8D	VREFB8D0	IO			DIFFIO_TX_T199n	DIFFOUT_T199n	D23				
8A	VREFB8A0	IO			DIFFIO_RX_T154p	DIFFOUT_T154p	A23	DO11T			
8A	VREFB8A0	IO			DIFFIO_RX_T154n	DIFFOUT_T154n	A24	DO11T			
8A	VREFB8A0	IO			DIFFIO_TX_T155p	DIFFOUT_T155p	L22	DO11T			
8A	VREFB8A0	IO			DIFFIO_TX_T155n	DIFFOUT_T155n	K23				
8A	VREFB8A0	IO			DIFFIO_RX_T156p	DIFFOUT_T156p	D24	DO11T			
8A	VREFB8A0	IO			DIFFIO_RX_T156n	DIFFOUT_T156n	E24	DO11T			
8A	VREFB8A0	IO			DIFFIO_TX_T157p	DIFFOUT_T157p	B24	DO11T			
8A	VREFB8A0	IO			DIFFIO_TX_T157n	DIFFOUT_T157n	B25				
8A	VREFB8A0	IO			DIFFIO_RX_T158p	DIFFOUT_T158p	A26	DQS11T/CQ11T/CQn11T/QKn11T			
8A	VREFB8A0	IO			DIFFIO_RX_T158n	DIFFOUT_T158n	A27	DQS11T/CQK11T			
8A	VREFB8A0	IO			DIFFIO_TX_T159p	DIFFOUT_T159p	K24	DO11T			
8A	VREFB8A0	IO			DIFFIO_TX_T159n	DIFFOUT_T159n	J23				
8A	VREFB8A0	IO	CLK23p		DIFFIO_RX_T160p	DIFFOUT_T160p	C25	DO11T			
8A	VREFB8A0	IO	CLK23n		DIFFIO_RX_T160n	DIFFOUT_T160n	D25	DO11T			
8A	VREFB8A0	IO			DIFFIO_TX_T161p	DIFFOUT_T161p	J25	DO11T			
8A	VREFB8A0	IO			DIFFIO_TX_T161n	DIFFOUT_T161n	K25				
8A	VREFB8A0	IO	CLK22p		DIFFIO_RX_T162p	DIFFOUT_T162p	D26	DO12T			
8A	VREFB8A0	IO	CLK22n		DIFFIO_RX_T162n	DIFFOUT_T162n	E25	DO12T			
8A	VREFB8A0	IO			DIFFIO_TX_T162n	DIFFOUT_T162n	G24	DO12T			
8A	VREFB8A0	IO	VREFB8A0				H25				
8A	VREFB8A0	IO	FPLL_TL_CLKOUT2.FPLL_TL_FBp.FPLL_TL_FB1		DIFFIO_RX_T163p	DIFFOUT_T163p	C27	DO12T			
8A	VREFB8A0	IO	FPLL_TL_CLKOUT3.FPLL_TL_FBn		DIFFIO_RX_T163n	DIFFOUT_T163n	C26	DO12T			
8A	VREFB8A0	IO	FPLL_TL_CLKOUT0.FPLL_TL_CLKOUTp.FPLL_TL_FB0		DIFFIO_TX_T164p	DIFFOUT_T164p	A28	DO12T			
8A	VREFB8A0	IO	FPLL_TL_CLKOUT1.FPLL_TL_CLKOUTn		DIFFIO_TX_T164n	DIFFOUT_T164n	B27				
8A	VREFB8A0	IO	CLK21p		DIFFIO_RX_T165p	DIFFOUT_T165p	A29	DQS12T/CQ12T/CQn12T/QKn12T			
8A	VREFB8A0	IO	CLK21n		DIFFIO_RX_T165n	DIFFOUT_T165n	B28	DQS12T/CQK12T			
8A	VREFB8A0	IO			DIFFIO_TX_T166p	DIFFOUT_T166p	H24	DO12T			
8A	VREFB8A0	IO			DIFFIO_TX_T166n	DIFFOUT_T166n	J24				
8A	VREFB8A0	IO	CLK20p		DIFFIO_RX_T167p	DIFFOUT_T167p	C28	DO12T			
8A	VREFB8A0	IO	CLK20n		DIFFIO_RX_T167n	DIFFOUT_T167n	D27	DO12T			
8A	VREFB8A0	IO			DIFFIO_TX_T168p	DIFFOUT_T168p	F25	DO12T			
8A	VREFB8A0	IO	RZQ_6		DIFFIO_TX_T168n	DIFFOUT_T168n	G25				
8A		MSEL0		MSEL0			C30				
8A		MSEL1		MSEL1			D30				
8A		MSEL2		MSEL2			C29				
8A		MSEL3		MSEL3			D29				
8A		MSEL4		MSEL4			F26				
8A		CONF_DONE		CONF_DONE			B30				
8A		nSTATUS		nSTATUS			D28				
8A		nCE		nCE			E28				
8A		nCONFIG		nCONFIG			E27				
8A		GND					H26				
		GND					AA26				
		GND					AA29				
		GND					AA30				
		GND					AB27				
		GND					AB28				
		GND					AC28				
		GND					AC29				
		GND					AC30				
		GND					AD27				
		GND					AD28				
		GND					AE28				
		GND					AE29				
		GND					AE30				
		GND					E30				
		GND					F27				
		GND					F28				
		GND					G26				
		GND					G29				
		GND					G30				
		GND					H27				
		GND					H28				
		GND					J26				
		GND					J29				
		GND					J30				
		GND					K27				
		GND					K28				
		GND					L25				
		GND					L26				
		GND					L29				
		GND					L30				
		GND					M24				
		GND					M27				
		GND					M28				
		GND					N23				
		GND					N24				
		GND					N26				
		GND					N29				
		GND					N30				
		GND					P23				
		GND					P25				
		GND					P27				
		GND					P28				
		GND					R24				
		GND					R29				
		GND					R30				
		GND					T23				
		GND					T27				
		GND					T28				
		GND					U24				



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
		GND					U26				
		GND					U29				
		GND					U30				
		GND					V23				
		GND					V25				
		GND					V27				
		GND					V28				
		GND					W24				
		GND					W29				
		GND					W30				
		GND					Y22				
		GND					Y23				
		GND					Y24				
		GND					Y25				
		GND					Y26				
		GND					Y27				
		GND					Y28				
		GND					AA1				
		GND					AA2				
		GND					AA5				
		GND					AB3				
		GND					AB4				
		GND					AC1				
		GND					AC2				
		GND					AC5				
		GND					AD3				
		GND					AD4				
		GND					AE1				
		GND					AE2				
		GND					AE3				
		GND					AG1				
		GND					F3				
		GND					F4				
		GND					G1				
		GND					G2				
		GND					G5				
		GND					H3				
		GND					H4				
		GND					J1				
		GND					J2				
		GND					J5				
		GND					K3				
		GND					K4				
		GND					L1				
		GND					L2				
		GND					L5				
		GND					L6				
		GND					M3				
		GND					M4				
		GND					M7				
		GND					N1				
		GND					N2				
		GND					N5				
		GND					N8				
		GND					N9				
		GND					P3				
		GND					P4				
		GND					P6				
		GND					P8				
		GND					R1				
		GND					R2				
		GND					R5				
		GND					R7				
		GND					T3				
		GND					T4				
		GND					T8				
		GND					U1				
		GND					U2				
		GND					U5				
		GND					U7				
		GND					V3				
		GND					V4				
		GND					V6				
		GND					V8				
		GND					W1				
		GND					W2				
		GND					W7				
		GND					Y3				
		GND					Y4				
		GND					Y5				
		GND					Y6				
		GND					Y7				
		GND					Y8				
		GND					Y9				
		VCCP					L11				
		VCCP					L15				
		VCCP					L19				
		VCCP					L20				
		VCCP					L9				
		VCCP					W11				
		VCCP					W13				
		VCCP					W17				



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
		VCCP					W19				
		VCCP					W21				
		VCCA_FPLL					T22				
		VCCA_FPLL					T9				
		VCCA_FPLL					P22				
		VCCA_FPLL					P9				
		VCCBAT					K26				
		VCC_AUX					M12				
		VCC_AUX					M18				
		VCC_AUX					W12				
		VCC_AUX					W18				
		VCCD_FPLL					V22				
		VCCD_FPLL					V9				
		VCCD_FPLL					N22				
		VCCD_FPLL					M8				
		VCCA_GXBL0					V24				
		VCCA_GXBR0					V7				
		VCCA_GXBL1					P24				
		VCCA_GXBR1					P7				
		VCCX_GXBL0					T24				
		VCCX_GXBR0					T7				
		VCCX_GXBL1					N25				
		VCCX_GXBR1					N7				
		VCC_L_GXBL0					T25				
		VCC_L_GXBL0					T26				
		VCC_L_GXBR0					U6				
		VCC_L_GXBL1					M25				
		VCC_L_GXBR1					M6				
		VCC_L_GXBR1					N6				
		VCCR_GXBL					M26				
		VCCR_GXBL					R25				
		VCCR_GXBL					R26				
		VCCR_GXBL					W25				
		VCCR_GXBL					W26				
		VCCR_GXBR					M5				
		VCCR_GXBR					T5				
		VCCR_GXBR					T6				
		VCCR_GXBR					W5				
		VCCR_GXBR					W6				
		VCC_T_GXBL0					U25				
		VCC_T_GXBL0					V26				
		VCC_T_GXBR0					V5				
		VCC_T_GXBL1					P26				
		VCC_T_GXBR1					P5				
		VCC_T_GXBR1					R6				
		VCC					M10				
		VCC					M14				
		VCC					M20				
		VCC					N11				
		VCC					N13				
		VCC					N15				
		VCC					N17				
		VCC					N19				
		VCC					N21				
		VCC					P10				
		VCC					P12				
		VCC					P14				
		VCC					P16				
		VCC					P18				
		VCC					P20				
		VCC					R11				
		VCC					R13				
		VCC					R15				
		VCC					R17				
		VCC					R19				
		VCC					R21				
		VCC					T10				
		VCC					T12				
		VCC					T14				
		VCC					T18				
		VCC					T20				
		VCC					U11				
		VCC					U13				
		VCC					U15				
		VCC					U17				
		VCC					U19				
		VCC					U21				
		VCC					V10				
		VCC					V12				
		VCC					V14				
		VCC					V16				
		VCC					V18				
		VCC					V20				
		VCC					T16				
		VCCIO3A					AD26				
		VCCIO3A					AE26				
		VCCIO3A					AH24				
		VCCIO3A					AH27				
		VCCIO3D					AE19				
		VCCIO3D					AE21				
		VCCIO3D					AH21				
		VCCIO3D					AK23				



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
		VCCIO4A					AB5				
		VCCIO4A					AD5				
		VCCIO4A					AH3				
		VCCIO4A					AH6				
		VCCIO4B					AE10				
		VCCIO4B					AG9				
		VCCIO4B					AH10				
		VCCIO4B					AK9				
		VCCIO4C					AE12				
		VCCIO4C					AG13				
		VCCIO4C					AK13				
		VCCIO4C					AK15				
		VCCIO4D					AE16				
		VCCIO4D					AG18				
		VCCIO4D					AH16				
		VCCIO4D					AK18				
		VCCIO7A					C3				
		VCCIO7A					C6				
		VCCIO7A					F2				
		VCCIO7A					F6				
		VCCIO7B					A9				
		VCCIO7B					C9				
		VCCIO7B					D7				
		VCCIO7B					F9				
		VCCIO7C					A12				
		VCCIO7C					C12				
		VCCIO7C					C15				
		VCCIO7C					F12				
		VCCIO7D					A18				
		VCCIO7D					C18				
		VCCIO7D					F16				
		VCCIO7D					F18				
		VCCIO8A					A25				
		VCCIO8A					C24				
		VCCIO8A					F24				
		VCCIO8A					L23				
		VCCIO8D					A20				
		VCCIO8D					A22				
		VCCIO8D					C21				
		VCCIO8D					F22				
		VCCPD3					AA23				
		VCCPD3					Y21				
		VCCPD4A					AA7				
		VCCPD4BCD					Y10				
		VCCPD4BCD					Y15				
		VCCPD4BCD					Y18				
		VCCPD7A					L8				
		VCCPD7BCD					L13				
		VCCPD7BCD					L17				
		VCCPD7BCD					M9				
		VCCPD8					M22				
		VCCPD8					M23				
		VCCPGM					K5				
		VCCPGM					AA24				
		GND					AC11				
		GND					AC14				
		GND					AC17				
		GND					AC20				
		GND					AC23				
		GND					AC8				
		GND					AF11				
		GND					AF14				
		GND					AF17				
		GND					AF20				
		GND					AF23				
		GND					AF26				
		GND					AF3				
		GND					AF5				
		GND					AF8				
		GND					AH29				
		GND					AJ11				
		GND					AJ14				
		GND					AJ17				
		GND					AJ2				
		GND					AJ20				
		GND					AJ23				
		GND					AJ26				
		GND					AJ5				
		GND					AJ8				
		GND					B11				
		GND					B14				
		GND					B17				
		GND					B2				
		GND					B20				
		GND					B23				
		GND					B26				
		GND					B29				
		GND					B5				
		GND					B8				
		GND					E11				
		GND					E14				
		GND					E17				



Pin Information for the Arria® V 5AGXMB3 Device
Version 1.7
Note (1)

Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
		GND					E2				
		GND					E20				
		GND					E23				
		GND					E26				
		GND					E5				
		GND					E8				
		GND					H11				
		GND					H14				
		GND					H17				
		GND					H20				
		GND					H23				
		GND					H8				
		GND					L10				
		GND					L12				
		GND					L14				
		GND					L16				
		GND					L18				
		GND					L21				
		GND					L24				
		GND					L7				
		GND					M11				
		GND					M13				
		GND					M17				
		GND					M19				
		GND					M21				
		GND					N10				
		GND					N12				
		GND					N14				
		GND					N16				
		GND					N18				
		GND					N20				
		GND					P11				
		GND					P13				
		GND					P15				
		GND					P17				
		GND					P19				
		GND					P21				
		GND					R10				
		GND					R12				
		GND					R14				
		GND					R18				
		GND					R20				
		GND					T11				
		GND					T13				
		GND					T15				
		GND					T17				
		GND					T19				
		GND					T21				
		GND					U10				
		GND					U12				
		GND					U14				
		GND					U16				
		GND					U18				
		GND					U20				
		GND					V11				
		GND					V13				
		GND					V15				
		GND					V17				
		GND					V19				
		GND					V21				
		GND					W10				
		GND					W14				
		GND					W20				
		GND					Y11				
		GND					Y14				
		GND					Y17				
		GND					Y19				
		GND					R16				

Notes:

- (1) For more information about pin definitions and pin connection guidelines, refer to the [Arria V Device Family Pin Connection Guidelines](#).
- (2) GXB_REFCLK pin is not supported in current Quartus II version, but will be supported in future Quartus II release version.
- (3) RESET pin is only applicable for DDR3 device.



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
		DNU					E33				
		DNU					F33				
		RREF TL					F34				
		GND					R27				
		GND					R26				
		DNU					G31				
		DNU					G32				
		GND					H34				
		GND					H33				
		DNU					J31				
		DNU					J32				
		GND					K34				
		GND					K33				
		DNU					L31				
		DNU					L32				
		GND					M34				
		GND					M33				
		GXB_L1	GXB_TX_L8n				N31				
		GXB_L1	GXB_TX_L8p				N32				
		GXB_L1	GXB_RX_L8p.GXB_REFCLK_L8p				P34				
		GXB_L1	GXB_RX_L8n.GXB_REFCLK_L8n				P33				
		GXB_L1	GXB_TX_L7n				R31				
		GXB_L1	GXB_TX_L7p				R32				
		GXB_L1	GXB_RX_L7p.GXB_REFCLK_L7p				T34				
		GXB_L1	GXB_RX_L7n.GXB_REFCLK_L7n				T33				
		GXB_L1	GXB_TX_L6n				U31				
		GXB_L1	GXB_TX_L6p				U32				
		GXB_L1	GXB_RX_L6p.GXB_REFCLK_L6p				V34				
		GXB_L1	GXB_RX_L6n.GXB_REFCLK_L6n				V33				
		GXB_L1	REFCLK2Ln				W27				
		GXB_L1	REFCLK2Lp				W28				
		GXB_L0	REFCLK1Ln				W27				
		GXB_L0	REFCLK1Lp				W26				
		GXB_L0	GXB_TX_L5n				W31				
		GXB_L0	GXB_TX_L5p				W32				
		GXB_L0	GXB_RX_L5p.GXB_REFCLK_L5p				Y34				
		GXB_L0	GXB_RX_L5n.GXB_REFCLK_L5n				Y33				
		GXB_L0	GXB_TX_L4n				AA31				
		GXB_L0	GXB_TX_L4p				AA32				
		GXB_L0	GXB_RX_L4p.GXB_REFCLK_L4p				AB34				
		GXB_L0	GXB_RX_L4n.GXB_REFCLK_L4n				AB33				
		GXB_L0	GXB_TX_L3n				AC31				
		GXB_L0	GXB_TX_L3p				AC32				
		GXB_L0	GXB_RX_L3p.GXB_REFCLK_L3p				AD34				
		GXB_L0	GXB_RX_L3n.GXB_REFCLK_L3n				AD33				
		GXB_L0	GXB_TX_L2n				AE31				
		GXB_L0	GXB_TX_L2p				AE32				
		GXB_L0	GXB_RX_L2p.GXB_REFCLK_L2p				AF34				
		GXB_L0	GXB_RX_L2n.GXB_REFCLK_L2n				AF33				
		GXB_L0	GXB_TX_L1n				AG31				
		GXB_L0	GXB_TX_L1p				AG32				
		GXB_L0	GXB_RX_L1p.GXB_REFCLK_L1p				AH34				
		GXB_L0	GXB_RX_L1n.GXB_REFCLK_L1n				AH33				
		GXB_L0	GXB_TX_L0n				AJ31				
		GXB_L0	GXB_TX_L0p				AJ32				
		GXB_L0	GXB_RX_L0p.GXB_REFCLK_L0p				AK34				
		GXB_L0	GXB_RX_L0n.GXB_REFCLK_L0n				AK33				
		GXB_L0	REFCLK0Ln				AA28				
		GXB_L0	REFCLK0Lp				AA27				
		DNU					AL32				
3A		TDO		TDO			AC28				
3A		TMS		TMS			AF30				
3A		TCK		TCK			AN32				
3A		TDI		TDI			AC29				
3A		DCLK		DCLK			AM32				
3A		ncSO		DATA4			AM34				
3A		AS_DATA3		DATA3			AM33				
3A		AS_DATA2		DATA2			AP33				
3A		AS_DATA1		DATA1			AN33				
3A		AS_DATA0_ASDD		DATA0			AN34				
3A	VREFB3AN0	IO	RZQ_0		DIFFIO_TX_B1n	DIFFOUT_B1n	AL31				
3A	VREFB3AN0	IO			DIFFIO_TX_B1p	DIFFOUT_B1p	AM31				DO1B
3A	VREFB3AN0	IO	CLK0n		DIFFIO_RX_B2n	DIFFOUT_B2n	AP31				DO1B
3A	VREFB3AN0	IO	CLK0p		DIFFIO_RX_B2p	DIFFOUT_B2p	AP32				DO1B
3A	VREFB3AN0	IO			DIFFIO_TX_B3n	DIFFOUT_B3n	AD27				
3A	VREFB3AN0	IO			DIFFIO_TX_B3p	DIFFOUT_B3p	AD26				DO1B
3A	VREFB3AN0	IO	CLK1n		DIFFIO_RX_B4n	DIFFOUT_B4n	AJ29				DQSn1B/QKn1B
3A	VREFB3AN0	IO	CLK1p		DIFFIO_RX_B4p	DIFFOUT_B4p	AJ28				DQS1B/CQ1B/CQn2B/QKn2B
3A	VREFB3AN0	IO	FPLL_BL_CLKOUT1.FPLL_BL_CLKOUTn		DIFFIO_TX_B5n	DIFFOUT_B5n	AL30				
3A	VREFB3AN0	IO	FPLL_BL_CLKOUT0.FPLL_BL_CLKOUTp.FPLL_BL_FB0		DIFFIO_TX_B5p	DIFFOUT_B5p	AM30				DO1B
3A	VREFB3AN0	IO	FPLL_BL_CLKOUT3.FPLL_BL_FBn		DIFFIO_RX_B6n	DIFFOUT_B6n	AN30				DO1B
3A	VREFB3AN0	IO	FPLL_BL_CLKOUT2.FPLL_BL_FBp.FPLL_BL_FB1		DIFFIO_RX_B6p	DIFFOUT_B6p	AP30				DO1B
3A	VREFB3AN0	IO	VREFB3AN0				AE27				
3A	VREFB3AN0	IO					AF28				DO1B
3A	VREFB3AN0	IO	CLK2n		DIFFIO_RX_B7n	DIFFOUT_B7n	AH28				DO1B
3A	VREFB3AN0	IO	CLK2p		DIFFIO_RX_B7p	DIFFOUT_B7p	AJ28				DO1B
3A	VREFB3AN0	IO			DIFFIO_TX_B8n	DIFFOUT_B8n	AL29				
3A	VREFB3AN0	IO			DIFFIO_TX_B8p	DIFFOUT_B8p	AM29				DO1B
3A	VREFB3AN0	IO	CLK3n		DIFFIO_RX_B9n	DIFFOUT_B9n	AN29				DO1B
3A	VREFB3AN0	IO	CLK3p		DIFFIO_RX_B9p	DIFFOUT_B9p	AP29				DO1B
3A	VREFB3AN0	IO			DIFFIO_TX_B10n	DIFFOUT_B10n	AE29				
3A	VREFB3AN0	IO			DIFFIO_TX_B10p	DIFFOUT_B10p	AF29				DO1B
3A	VREFB3AN0	IO			DIFFIO_RX_B11n	DIFFOUT_B11n	AQ27				DO1B
3A	VREFB3AN0	IO			DIFFIO_RX_B11p	DIFFOUT_B11p	AH27				DO1B
3A	VREFB3AN0	IO			DIFFIO_TX_B12n	DIFFOUT_B12n	AL28				
3A	VREFB3AN0	IO			DIFFIO_TX_B12p	DIFFOUT_B12p	AM28				DO1B
3A	VREFB3AN0	IO			DIFFIO_RX_B13n	DIFFOUT_B13n	AP27				DO1B
3A	VREFB3AN0	IO			DIFFIO_RX_B13p	DIFFOUT_B13p	AP28				DO1B
3A	VREFB3AN0	IO			DIFFIO_TX_B14n	DIFFOUT_B14n	AG29				



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F152	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
3A	VREFB3A0	IO			DIFFIO TX B14p	DIFFOUT B14p	AH29	DO2B		DO1B	
3A	VREFB3A0	IO			DIFFIO RX B15n	DIFFOUT B15n	AK27	DO2B		DO1B	
3A	VREFB3A0	IO			DIFFIO RX B15p	DIFFOUT B15p	AL27	DO2B		DO1B	
3A	VREFB3A0	IO			DIFFIO TX B16n	DIFFOUT B16n	AG26				
3A	VREFB3A0	IO			DIFFIO TX B16p	DIFFOUT B16p	AH26			DO1B	
3A	VREFB3A0	IO			DIFFIO RX B17n	DIFFOUT B17n	AJ25	DO3B		DO1B	
3A	VREFB3A0	IO			DIFFIO RX B17p	DIFFOUT B17p	AK26	DO3B		DO1B	
3A	VREFB3A0	IO			DIFFIO TX B18n	DIFFOUT B18n	AD29				
3A	VREFB3A0	IO			DIFFIO TX B18p	DIFFOUT B18p	AE28	DO3B		DO1B	
3A	VREFB3A0	IO			DIFFIO RX B19n	DIFFOUT B19n	AL26	DQ3nB/QK3B		DQ3n1B/QK1B	
3A	VREFB3A0	IO			DIFFIO RX B19p	DIFFOUT B19p	AM26	DQ3nB/CQ3nB/CO3nB/QK3nB		DQ3n1B/CQ1nB/CO1nB/QK1nB	
3A	VREFB3A0	IO			DIFFIO TX B20n	DIFFOUT B20n	AN27				
3A	VREFB3A0	IO			DIFFIO TX B20p	DIFFOUT B20p	AN26	DO3B		DO1B	
3A	VREFB3A0	IO			DIFFIO RX B21n	DIFFOUT B21n	AP25	DO3B		DO1B	
3A	VREFB3A0	IO			DIFFIO RX B21p	DIFFOUT B21p	AP26	DO3B		DO1B	
3A	VREFB3A0	IO			DIFFIO TX B22n	DIFFOUT B22n	AC25				
3A	VREFB3A0	IO			DIFFIO TX B22p	DIFFOUT B22p	AF26	DO3B		DO1B	
3A	VREFB3A0	IO			DIFFIO RX B23n	DIFFOUT B23n	AL25	DO3B		DO1B	
3A	VREFB3A0	IO			DIFFIO RX B23p	DIFFOUT B23p	AM25	DO3B		DO1B	
3B	VREFB3B0	IO			DIFFIO TX B24n	DIFFOUT B24n	AE23				
3B	VREFB3B0	IO			DIFFIO TX B24p	DIFFOUT B24p	AE24	DO4B		DO2B	DO1B
3B	VREFB3B0	IO			DIFFIO RX B25n	DIFFOUT B25n	AC24	DO4B		DO2B	DO1B
3B	VREFB3B0	IO			DIFFIO RX B25p	DIFFOUT B25p	AC25	DO4B		DO2B	DO1B
3B	VREFB3B0	IO			DIFFIO TX B26n	DIFFOUT B26n	AA25				
3B	VREFB3B0	IO			DIFFIO TX B26p	DIFFOUT B26p	AB25	DO4B		DO2B	DO1B
3B	VREFB3B0	IO			DIFFIO RX B27n	DIFFOUT B27n	AD24	DQ4nB/QK4B		DQ2B	DO1B
3B	VREFB3B0	IO			DIFFIO RX B27p	DIFFOUT B27p	AE25	DQ4nB/CQ4nB/CO4nB/QK4nB		DQ2B	DO1B
3B	VREFB3B0	IO			DIFFIO TX B28n	DIFFOUT B28n	AF25				
3B	VREFB3B0	IO			DIFFIO TX B28p	DIFFOUT B28p	AG24	DO4B		DO2B	DO1B
3B	VREFB3B0	IO			DIFFIO RX B29n	DIFFOUT B29n	AH24	DO4B		DO2B	DO1B
3B	VREFB3B0	IO			DIFFIO RX B29p	DIFFOUT B29p	AH25	DO4B		DO2B	DO1B
3B	VREFB3B0	IO	VREFB3B0				Y23				
3B	VREFB3B0	IO					AB24	DO4B		DO2B	DO1B
3B	VREFB3B0	IO			DIFFIO RX B30n	DIFFOUT B30n	AJ25	DO4B		DO2B	DO1B
3B	VREFB3B0	IO			DIFFIO RX B30p	DIFFOUT B30p	AK24	DO4B		DO2B	DO1B
3B	VREFB3B0	IO			DIFFIO TX B31n	DIFFOUT B31n	AK23				
3B	VREFB3B0	IO			DIFFIO TX B31p	DIFFOUT B31p	AL24	DO5B		DO2B	DO1B
3B	VREFB3B0	IO			DIFFIO RX B32n	DIFFOUT B32n	AF23	DO5B		DO2B	DO1B
3B	VREFB3B0	IO			DIFFIO RX B32p	DIFFOUT B32p	AG23	DO5B		DO2B	DO1B
3B	VREFB3B0	IO			DIFFIO TX B33n	DIFFOUT B33n	AC23				
3B	VREFB3B0	IO			DIFFIO TX B33p	DIFFOUT B33p	AD23	DO5B		DO2B	DO1B
3B	VREFB3B0	IO			DIFFIO RX B34n	DIFFOUT B34n	AH23	DQ5nB/QK5B		DQ3nB/QK3B	DO1B
3B	VREFB3B0	IO			DIFFIO RX B34p	DIFFOUT B34p	AJ23	DQ5nB/CQ5nB/CO5nB/QK5nB		DQ3nB/CQ3nB/CO3nB/QK3nB	DO1B
3B	VREFB3B0	IO			DIFFIO TX B35n	DIFFOUT B35n	AL23				
3B	VREFB3B0	IO			DIFFIO TX B35p	DIFFOUT B35p	AM23	DO6B		DO2B	DO1B
3B	VREFB3B0	IO			DIFFIO RX B36n	DIFFOUT B36n	AN23	DO6B		DO2B	DO1B
3B	VREFB3B0	IO			DIFFIO RX B36p	DIFFOUT B36p	AN24	DO6B		DO2B	DO1B
3B	VREFB3B0	IO			DIFFIO TX B37n	DIFFOUT B37n	AA23				
3B	VREFB3B0	IO			DIFFIO TX B37p	DIFFOUT B37p	AB23	DO6B		DO2B	DO1B
3B	VREFB3B0	IO			DIFFIO RX B38n	DIFFOUT B38n	AP22	DO6B		DO2B	DO1B
3B	VREFB3B0	IO			DIFFIO RX B38p	DIFFOUT B38p	AP23	DO6B		DO2B	DO1B
3C	VREFB3C0	IO			DIFFIO TX B39n	DIFFOUT B39n	AE21				
3C	VREFB3C0	IO			DIFFIO TX B39p	DIFFOUT B39p	AE22	DO6B		DO3B	DO1B
3C	VREFB3C0	IO			DIFFIO RX B40n	DIFFOUT B40n	AL21	DO6B		DO3B	DO1B
3C	VREFB3C0	IO			DIFFIO RX B40p	DIFFOUT B40p	AL22	DO6B		DO3B	DO1B
3C	VREFB3C0	IO			DIFFIO TX B41n	DIFFOUT B41n	AB22				
3C	VREFB3C0	IO			DIFFIO TX B41p	DIFFOUT B41p	AC22	DO6B		DO3B	DO1B
3C	VREFB3C0	IO			DIFFIO RX B42n	DIFFOUT B42n	AH21	DQ6nB/QK6B		DQ3B	DO3nB/QK3B
3C	VREFB3C0	IO			DIFFIO RX B42p	DIFFOUT B42p	AH22	DQ6nB/CQ6nB/CO6nB/QK6nB		DQ3B	DO3nB/CQ3nB/CO3nB/QK3nB
3C	VREFB3C0	IO			DIFFIO TX B43n	DIFFOUT B43n	AF22				
3C	VREFB3C0	IO			DIFFIO TX B43p	DIFFOUT B43p	AG21	DO6B		DO3B	DO1B
3C	VREFB3C0	IO			DIFFIO RX B44n	DIFFOUT B44n	AJ22	DO6B		DO3B	DO1B
3C	VREFB3C0	IO			DIFFIO RX B44p	DIFFOUT B44p	AK21	DO6B		DO3B	DO1B
3C	VREFB3C0	IO			DIFFIO TX B45n	DIFFOUT B45n	AA21				
3C	VREFB3C0	IO			DIFFIO TX B45p	DIFFOUT B45p	AB21	DO6B		DO3B	DO1B
3C	VREFB3C0	IO			DIFFIO RX B46n	DIFFOUT B46n	AM22	DO6B		DO3B	DO1B
3C	VREFB3C0	IO			DIFFIO RX B46p	DIFFOUT B46p	AN21	DO6B		DO3B	DO1B
3C	VREFB3C0	IO			DIFFIO TX B47n	DIFFOUT B47n	AC21				
3C	VREFB3C0	IO			DIFFIO TX B47p	DIFFOUT B47p	AD21	DO7B		DO3B	DO1B
3C	VREFB3C0	IO			DIFFIO RX B48n	DIFFOUT B48n	AN20	DO7B		DO3B	DO1B
3C	VREFB3C0	IO			DIFFIO RX B48p	DIFFOUT B48p	AP20	DO7B		DO3B	DO1B
3C	VREFB3C0	IO			DIFFIO TX B49n	DIFFOUT B49n	AA20				
3C	VREFB3C0	IO			DIFFIO TX B49p	DIFFOUT B49p	AB20	DO7B		DO3B	DO1B
3C	VREFB3C0	IO			DIFFIO RX B50n	DIFFOUT B50n	AL20	DQ7nB/QK7B		DQ3nB/QK3B	DO1B
3C	VREFB3C0	IO			DIFFIO RX B50p	DIFFOUT B50p	AM20	DQ7nB/CQ7nB/CO7nB/QK7nB		DQ3nB/CQ3nB/CO3nB/QK3nB	DO1B
3C	VREFB3C0	IO			DIFFIO TX B51n	DIFFOUT B51n	AJ20				
3C	VREFB3C0	IO			DIFFIO TX B51p	DIFFOUT B51p	AK20	DO7B		DO3B	DO1B
3C	VREFB3C0	IO			DIFFIO RX B52n	DIFFOUT B52n	AH20	DO7B		DO3B	DO1B
3C	VREFB3C0	IO			DIFFIO RX B52p	DIFFOUT B52p	AH20	DO7B		DO3B	DO1B
3C	VREFB3C0	IO	VREFB3C0				AC20				
3C	VREFB3C0	IO					AD20	DO7B		DO3B	DO1B
3C	VREFB3C0	IO			DIFFIO RX B53n	DIFFOUT B53n	AE20	DO7B		DO3B	DO1B
3C	VREFB3C0	IO			DIFFIO RX B53p	DIFFOUT B53p	AF20	DO7B		DO3B	DO1B
3D	VREFB3D0	IO			DIFFIO TX B70n	DIFFOUT B70n	AH19				
3D	VREFB3D0	IO			DIFFIO TX B70p	DIFFOUT B70p	AJ19	DO8B		DO4B	
3D	VREFB3D0	IO			DIFFIO RX B71n	DIFFOUT B71n	AL19	DO8B		DO4B	
3D	VREFB3D0	IO			DIFFIO RX B71p	DIFFOUT B71p	AM19	DO8B		DO4B	
3D	VREFB3D0	IO			DIFFIO TX B72n	DIFFOUT B72n	AA19				
3D	VREFB3D0	IO			DIFFIO TX B72p	DIFFOUT B72p	AC19	DO8B		DO4B	
3D	VREFB3D0	IO			DIFFIO RX B73n	DIFFOUT B73n	AN18	DQ8nB/QK8B		DO4B	
3D	VREFB3D0	IO			DIFFIO RX B73p	DIFFOUT B73p	AP19	DQ8nB/CQ8nB/CO8nB/QK8nB		DO4B	
3D	VREFB3D0	IO			DIFFIO TX B74n	DIFFOUT B74n	AE19				
3D	VREFB3D0	IO			DIFFIO TX B74p	DIFFOUT B74p	AF19	DO8B		DO4B	
3D	VREFB3D0	IO			DIFFIO RX B75n	DIFFOUT B75n	AK18	DO8B		DO4B	
3D	VREFB3D0	IO			DIFFIO RX B75p	DIFFOUT B75p	AL18	DO8B		DO4B	
3D	VREFB3D0	IO	VREFB3D0				AB18				
3D	VREFB3D0	IO					AA18	DO8B		DO4B	
3D	VREFB3D0	IO	CLK4n		DIFFIO RX B76n	DIFFOUT B76n	AG18	DO8B		DO4B	
3D	VREFB3D0	IO	CLK4p		DIFFIO RX B76p	DIFFOUT B76p	AH18	DO8B		DO4B	



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F152	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
3D	VREFB3D0N	IO			DIFFIO TX B77n	DIFFOUT B77n	AN17				
3D	VREFB3D0N	IO			DIFFIO TX B77p	DIFFOUT B77p	AP17	DO9B		DO4B	
3D	VREFB3D0N	IO	CLK5n		DIFFIO RX B78n	DIFFOUT B78n	AG17	DO9B		DO4B	
3D	VREFB3D0N	IO	CLK5p		DIFFIO RX B78p	DIFFOUT B78p	AH17	DO9B		DO4B	
3D	VREFB3D0N	IO	FPLL_BC_CLKOUT1,FPLL_BC_CLKOUTn		DIFFIO TX B79n	DIFFOUT B79n	AA17				
3D	VREFB3D0N	IO	FPLL_BC_CLKOUT0,FPLL_BC_CLKOUTp,FPLL_BC_FB0		DIFFIO TX B79p	DIFFOUT B79p	AB17	DO9B		DO4B	
3D	VREFB3D0N	IO	FPLL_BC_CLKOUT3,FPLL_BC_FBn		DIFFIO RX B80n	DIFFOUT B80n	AJ17	DOSn9B/QK9B		DOSn4B/QK4B	
3D	VREFB3D0N	IO	FPLL_BC_CLKOUT2,FPLL_BC_FBp,FPLL_BC_FB1		DIFFIO RX B80p	DIFFOUT B80p	AK17	DOS9B/CO9B/CO9nB/QKn9B		DOS4B/CO4B/CO4nB/QKn4B	
3D	VREFB3D0N	IO			DIFFIO TX B81n	DIFFOUT B81n	AL17				
3D	VREFB3D0N	IO			DIFFIO TX B81p	DIFFOUT B81p	AM17	DO9B		DO4B	
3D	VREFB3D0N	IO	CLK6n		DIFFIO RX B82n	DIFFOUT B82n	AE17	DO9B		DO4B	
3D	VREFB3D0N	IO	CLK6p		DIFFIO RX B82p	DIFFOUT B82p	AF17	DO9B		DO4B	
3D	VREFB3D0N	IO			DIFFIO TX B83n	DIFFOUT B83n	AC17				
3D	VREFB3D0N	IO			DIFFIO TX B83p	DIFFOUT B83p	AC18	DO9B		DO4B	
3D	VREFB3D0N	IO	CLK7n		DIFFIO RX B84n	DIFFOUT B84n	AD17	DO9B		DO4B	
3D	VREFB3D0N	IO	CLK7p		DIFFIO RX B84p	DIFFOUT B84p	AE18	DO9B		DO4B	
		VCCD_FPLL					Y17				
		VCCA_FPLL					Y18				
		DN0					AD18				
4D	VREFB4D0N	IO			DIFFIO TX B93n	DIFFOUT B93n	AP16				CS#_4D_1
4D	VREFB4D0N	IO			DIFFIO TX B93p	DIFFOUT B93p	AN16	DO10B		DO5B	CS#_4D_0
4D	VREFB4D0N	IO			DIFFIO RX B94n	DIFFOUT B94n	AH16	DO10B		DO5B	
4D	VREFB4D0N	IO			DIFFIO RX B94p	DIFFOUT B94p	AJ16	DO10B		DO5B	A_4D_15
4D	VREFB4D0N	IO			DIFFIO TX B95n	DIFFOUT B95n	AE16				ODT_4D_1
4D	VREFB4D0N	IO			DIFFIO TX B95p	DIFFOUT B95p	AF16	DO10B		DO5B	ODT_4D_0
4D	VREFB4D0N	IO			DIFFIO RX B96n	DIFFOUT B96n	Y16	DOSn10B/QK10B		DO5B	WE#_4D
4D	VREFB4D0N	IO			DIFFIO RX B96p	DIFFOUT B96p	AA16	DOS10B/CO10B/CO10nB/QKn10B		DO5B	CAS#_4D
4D	VREFB4D0N	IO			DIFFIO TX B97n	DIFFOUT B97n	AB16				RAS#_4D
4D	VREFB4D0N	IO			DIFFIO TX B97p	DIFFOUT B97p	AC16	DO10B		DO5B	BA_4D_2
4D	VREFB4D0N	IO			DIFFIO RX B98n	DIFFOUT B98n	AL16	DO10B		DO5B	BA_4D_1
4D	VREFB4D0N	IO			DIFFIO RX B98p	DIFFOUT B98p	AM16	DO10B		DO5B	BA_4D_0
4D	VREFB4D0N	IO	VREFB4D0N				AL14				
4D	VREFB4D0N	IO					AK14	DO10B		DO5B	A_4D_14
4D	VREFB4D0N	IO			DIFFIO RX B99n	DIFFOUT B99n	AL14	DO10B		DO5B	A_4D_13
4D	VREFB4D0N	IO			DIFFIO RX B99p	DIFFOUT B99p	AM14	DO10B		DO5B	A_4D_12
4D	VREFB4D0N	IO			DIFFIO TX B100n	DIFFOUT B100n	AA14				A_4D_11
4D	VREFB4D0N	IO			DIFFIO TX B100p	DIFFOUT B100p	AB15	DO11B		DO5B	A_4D_10
4D	VREFB4D0N	IO			DIFFIO RX B101n	DIFFOUT B101n	AK15	DO11B		DO5B	A_4D_9
4D	VREFB4D0N	IO			DIFFIO RX B101p	DIFFOUT B101p	AL15	DO11B		DO5B	A_4D_8
4D	VREFB4D0N	IO			DIFFIO TX B102n	DIFFOUT B102n	AG14				A_4D_7
4D	VREFB4D0N	IO			DIFFIO TX B102p	DIFFOUT B102p	AH14	DO11B		DO5B	A_4D_6
4D	VREFB4D0N	IO			DIFFIO RX B103n	DIFFOUT B103n	AG15	DOSn11B/QK11B		DO5B	A_4D_5
4D	VREFB4D0N	IO			DIFFIO RX B103p	DIFFOUT B103p	AH15	DOS11B/CO11B/CO11nB/QKn11B		DO5B	A_4D_4
4D	VREFB4D0N	IO			DIFFIO TX B104n	DIFFOUT B104n	AD15				A_4D_3
4D	VREFB4D0N	IO			DIFFIO TX B104p	DIFFOUT B104p	AE15	DO11B		DO5B	A_4D_2
4D	VREFB4D0N	IO			DIFFIO RX B105n	DIFFOUT B105n	AE14	DO11B		DO5B	A_4D_1
4D	VREFB4D0N	IO			DIFFIO RX B105p	DIFFOUT B105p	AF14	DO11B		DO5B	A_4D_0
4D	VREFB4D0N	IO			DIFFIO TX B106n	DIFFOUT B106n	AB14				CKE_4D_1
4D	VREFB4D0N	IO			DIFFIO TX B106p	DIFFOUT B106p	AC15	DO11B		DO5B	CKE_4D_0
4D	VREFB4D0N	IO			DIFFIO RX B107n	DIFFOUT B107n	AC14	DO11B		DO5B	CK#_4D
4D	VREFB4D0N	IO			DIFFIO RX B107p	DIFFOUT B107p	AD14	DO11B		DO5B	CK_4D
4C	VREFB4C0N	IO			DIFFIO TX B108n	DIFFOUT B108n	AB13				RESET#_4D
4C	VREFB4C0N	IO			DIFFIO TX B108p	DIFFOUT B108p	AC13	DO12B		DO6B	DO1_4C_6
4C	VREFB4C0N	IO			DIFFIO RX B109n	DIFFOUT B109n	AN14	DO12B		DO6B	DO1_4C_7
4C	VREFB4C0N	IO			DIFFIO RX B109p	DIFFOUT B109p	AP14	DO12B		DO6B	DO1_4C_6
4C	VREFB4C0N	IO			DIFFIO TX B110n	DIFFOUT B110n	AN12				
4C	VREFB4C0N	IO			DIFFIO TX B110p	DIFFOUT B110p	AP13	DO12B		DO6B	DM1_4C
4C	VREFB4C0N	IO			DIFFIO RX B111n	DIFFOUT B111n	AL13	DOSn12B/QK12B		DO6B	DOS#1_4C
4C	VREFB4C0N	IO			DIFFIO RX B111p	DIFFOUT B111p	AM13	DOS12B/CO12B/CO12nB/QKn12B		DO6B	DOS1_4C
4C	VREFB4C0N	IO			DIFFIO TX B112n	DIFFOUT B112n	Y11				
4C	VREFB4C0N	IO			DIFFIO TX B112p	DIFFOUT B112p	AA12	DO12B		DO6B	DO1_4C_5
4C	VREFB4C0N	IO			DIFFIO RX B113n	DIFFOUT B113n	AK12	DO12B		DO6B	DO1_4C_4
4C	VREFB4C0N	IO			DIFFIO RX B113p	DIFFOUT B113p	AL12	DO12B		DO6B	DO1_4C_3
4C	VREFB4C0N	IO	VREFB4C0N				AK11				
4C	VREFB4C0N	IO					AL11	DO12B		DO6B	DO1_4C_2
4C	VREFB4C0N	IO			DIFFIO RX B114n	DIFFOUT B114n	AH13	DO12B		DO6B	DO1_4C_1
4C	VREFB4C0N	IO			DIFFIO RX B114p	DIFFOUT B114p	AJ13	DO12B		DO6B	DO1_4C_0
4C	VREFB4C0N	IO			DIFFIO TX B115n	DIFFOUT B115n	AB11				
4C	VREFB4C0N	IO			DIFFIO TX B115p	DIFFOUT B115p	AB12	DO13B		DO6B	DO2_4C_6
4C	VREFB4C0N	IO			DIFFIO RX B116n	DIFFOUT B116n	AG12	DO13B		DO6B	DO2_4C_7
4C	VREFB4C0N	IO			DIFFIO RX B116p	DIFFOUT B116p	AH12	DO13B		DO6B	DO2_4C_6
4C	VREFB4C0N	IO			DIFFIO TX B117n	DIFFOUT B117n	AH11				
4C	VREFB4C0N	IO			DIFFIO TX B117p	DIFFOUT B117p	AJ11	DO13B		DO6B	DM2_4C
4C	VREFB4C0N	IO			DIFFIO RX B118n	DIFFOUT B118n	AE13	DOSn13B/QK13B		DO6B	DOS#2_4C
4C	VREFB4C0N	IO			DIFFIO RX B118p	DIFFOUT B118p	AF13	DOS13B/CO13B/CO13nB/QKn13B		DO6B	DOS2_4C
4C	VREFB4C0N	IO			DIFFIO TX B119n	DIFFOUT B119n	AC11				
4C	VREFB4C0N	IO			DIFFIO TX B119p	DIFFOUT B119p	AC12	DO13B		DO6B	DO2_4C_5
4C	VREFB4C0N	IO			DIFFIO RX B120n	DIFFOUT B120n	AD12	DO13B		DO6B	DO2_4C_4
4C	VREFB4C0N	IO			DIFFIO RX B120p	DIFFOUT B120p	AE12	DO13B		DO6B	DO2_4C_3
4C	VREFB4C0N	IO			DIFFIO TX B121n	DIFFOUT B121n	AD11				
4C	VREFB4C0N	IO			DIFFIO TX B121p	DIFFOUT B121p	AE11	DO13B		DO6B	DO2_4C_2
4C	VREFB4C0N	IO			DIFFIO RX B122n	DIFFOUT B122n	AF11	DO13B		DO6B	DO2_4C_1
4C	VREFB4C0N	IO			DIFFIO RX B122p	DIFFOUT B122p	AG11	DO13B		DO6B	DO2_4C_0
4B	VREFB4B0N	IO			DIFFIO TX B123n	DIFFOUT B123n	AD9				
4B	VREFB4B0N	IO			DIFFIO TX B123p	DIFFOUT B123p	AE9	DO14B		DO7B	DO3_4B_8
4B	VREFB4B0N	IO			DIFFIO RX B124n	DIFFOUT B124n	AM11	DO14B		DO7B	DO3_4B_7
4B	VREFB4B0N	IO			DIFFIO RX B124p	DIFFOUT B124p	AN11	DO14B		DO7B	DO3_4B_6
4B	VREFB4B0N	IO			DIFFIO TX B125n	DIFFOUT B125n	AL10				
4B	VREFB4B0N	IO			DIFFIO TX B125p	DIFFOUT B125p	AM10	DO14B		DO7B	DM3_4B
4B	VREFB4B0N	IO			DIFFIO RX B126n	DIFFOUT B126n	AP10	DOSn14B/QK14B		DO7B	DOS#3_4B
4B	VREFB4B0N	IO			DIFFIO RX B126p	DIFFOUT B126p	AP11	DOS14B/CO14B/CO14nB/QKn14B		DO7B	DOS3_4B
4B	VREFB4B0N	IO			DIFFIO TX B127n	DIFFOUT B127n	AA10				
4B	VREFB4B0N	IO			DIFFIO TX B127p	DIFFOUT B127p	AB10	DO14B		DO7B	DO3_4B_5
4B	VREFB4B0N	IO			DIFFIO RX B128n	DIFFOUT B128n	AH10	DO14B		DO7B	DO3_4B_4
4B	VREFB4B0N	IO			DIFFIO RX B128p	DIFFOUT B128p	AJ10	DO14B		DO7B	DO3_4B_3
4B	VREFB4B0N	IO			DIFFIO TX B129n	DIFFOUT B129n	AK9				
4B	VREFB4B0N	IO			DIFFIO TX B129p	DIFFOUT B129p	AL9	DO14B		DO7B	DO3_4B_2
4B	VREFB4B0N	IO			DIFFIO RX B130n	DIFFOUT B130n	AN9	DO14B		DO7B	DO3_4B_1
4B	VREFB4B0N	IO			DIFFIO RX B130p	DIFFOUT B130p	AN8	DO14B		DO7B	DO3_4B_0



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F152	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
4B	VREFB4B0	IO			DIFFIO TX_B131n	DIFFOUT_B131n	AC9				
4B	VREFB4B0	IO			DIFFIO TX_B131p	DIFFOUT_B131p	AC10	DO15B	DO7B	DO2B	DQ4_4B_8
4B	VREFB4B0	IO			DIFFIO RX_B132n	DIFFOUT_B132n	AG9	DO15B	DO7B	DO2B	DQ4_4B_7
4B	VREFB4B0	IO			DIFFIO RX_B132p	DIFFOUT_B132p	AH9	DO15B	DO7B	DO2B	DQ4_4B_6
4B	VREFB4B0	IO			DIFFIO TX_B133n	DIFFOUT_B133n	AE10				
4B	VREFB4B0	IO			DIFFIO TX_B133p	DIFFOUT_B133p	AF10	DO15B	DO7B	DO2B	DM4_4B
4B	VREFB4B0	IO			DIFFIO RX_B134n	DIFFOUT_B134n	AL8	DOSn15B/QK15B	DO5n7B/QK7B	DO2B	DQS#4_4B
4B	VREFB4B0	IO			DIFFIO RX_B134p	DIFFOUT_B134p	AM8	DOS15B/CQ15B/CQn15B/QKn15B	DQS7B/CQ7B/CQn7B/QKn7B	DO2B	DQS#4_4B
4B	VREFB4B0	IO			DIFFIO TX_B135n	DIFFOUT_B135n	AC8				
4B	VREFB4B0	IO			DIFFIO TX_B135p	DIFFOUT_B135p	AD8	DO15B	DO7B	DO2B	DQ4_4B_5
4B	VREFB4B0	IO			DIFFIO RX_B136n	DIFFOUT_B136n	AJ8	DO15B	DO7B	DO2B	DQ4_4B_4
4B	VREFB4B0	IO			DIFFIO RX_B136p	DIFFOUT_B136p	AK8	DO15B	DO7B	DO2B	DQ4_4B_3
4B	VREFB4B0	IO	VREFB4B0				AE8				
4B	VREFB4B0	IO					AF8	DO15B	DO7B	DO2B	DQ4_4B_2
4B	VREFB4B0	IO			DIFFIO RX_B137n	DIFFOUT_B137n	AG8	DO15B	DO7B	DO2B	DQ4_4B_1
4B	VREFB4B0	IO			DIFFIO RX_B137p	DIFFOUT_B137p	AH8	DO15B	DO7B	DO2B	DQ4_4B_0
4A	VREFB4A0	IO		DATA10	DIFFIO TX_B154n	DIFFOUT_B154n	AP8				
4A	VREFB4A0	IO		DATA11	DIFFIO TX_B154p	DIFFOUT_B154p	AP7	DO16B	DO8B		
4A	VREFB4A0	IO		DATA5	DIFFIO RX_B155n	DIFFOUT_B155n	AL7	DO16B	DO8B		
4A	VREFB4A0	IO		DATA6	DIFFIO RX_B155p	DIFFOUT_B155p	AM7	DO16B	DO8B		
4A	VREFB4A0	IO		DATA12	DIFFIO TX_B156n	DIFFOUT_B156n	AM6				
4A	VREFB4A0	IO		DATA13	DIFFIO TX_B156p	DIFFOUT_B156p	AN6	DO16B	DO8B		
4A	VREFB4A0	IO		DATA7	DIFFIO RX_B157n	DIFFOUT_B157n	AP6	DOSn16B/QK16B	DO8B		
4A	VREFB4A0	IO		DATA8	DIFFIO RX_B157p	DIFFOUT_B157p	AP5	DOS16B/CQ16B/CQn16B/QKn16B	DO8B		
4A	VREFB4A0	IO		DATA14	DIFFIO TX_B158n	DIFFOUT_B158n	AE7				
4A	VREFB4A0	IO		DATA15	DIFFIO TX_B158p	DIFFOUT_B158p	AF7	DO16B	DO8B		
4A	VREFB4A0	IO		DATA9	DIFFIO RX_B159n	DIFFOUT_B159n	AM5	DO16B	DO8B		
4A	VREFB4A0	IO		CLKUSR	DIFFIO RX_B159p	DIFFOUT_B159p	AN5	DO16B	DO8B		
4A	VREFB4A0	IO	VREFB4A0				AK6				
4A	VREFB4A0	IO					AL6	DO16B	DO8B		
4A	VREFB4A0	IO		CLK11n	DIFFIO RX_B160n	DIFFOUT_B160n	AH7	DO16B	DO8B		
4A	VREFB4A0	IO		CLK11p	DIFFIO RX_B160p	DIFFOUT_B160p	AJ7	DO16B	DO8B		
4A	VREFB4A0	IO		FPLL_BR_CLKOUT1,FPLL_BR_CLKOUTn	DIFFIO TX_B161n	DIFFOUT_B161n	AD6				
4A	VREFB4A0	IO		FPLL_BR_CLKOUT0,FPLL_BR_CLKOUTp,FPLL_BR_FB0	DIFFIO TX_B161p	DIFFOUT_B161p	AE6	DO17B	DO8B		
4A	VREFB4A0	IO		FPLL_BR_CLKOUT3,FPLL_BR_FBn	DIFFIO RX_B162n	DIFFOUT_B162n	AP3	DO17B	DO8B		
4A	VREFB4A0	IO		FPLL_BR_CLKOUT2,FPLL_BR_FBp,FPLL_BR_FB1	DIFFIO RX_B162p	DIFFOUT_B162p	AP4	DO17B	DO8B		
4A	VREFB4A0	IO			DIFFIO TX_B163n	DIFFOUT_B163n	AH6				
4A	VREFB4A0	IO			DIFFIO TX_B163p	DIFFOUT_B163p	AJ6	DO17B	DO8B		
4A	VREFB4A0	IO		CLK10n	DIFFIO RX_B164n	DIFFOUT_B164n	AP2	DOSn17B/QK17B	DO8B		
4A	VREFB4A0	IO		CLK10p	DIFFIO RX_B164p	DIFFOUT_B164p	AN3	DOS17B/CQ17B/CQn17B/QKn17B	DQS#8B/CQ#8B/QKn#8B		
4A	VREFB4A0	IO			DIFFIO TX_B165n	DIFFOUT_B165n	AC7				
4A	VREFB4A0	IO			DIFFIO TX_B165p	DIFFOUT_B165p	AC6	DO17B	DO8B		
4A	VREFB4A0	IO		CLK9n	DIFFIO RX_B166n	DIFFOUT_B166n	AL4	DO17B	DO8B		
4A	VREFB4A0	IO		CLK9p	DIFFIO RX_B166p	DIFFOUT_B166p	AL5	DO17B	DO8B		
4A	VREFB4A0	IO			DIFFIO TX_B167n	DIFFOUT_B167n	AM3				
4A	VREFB4A0	IO		RZQ_1	DIFFIO TX_B167p	DIFFOUT_B167p	AMM	DO17B	DO8B		
4A	VREFB4A0	IO			DIFFIO RX_B168n	DIFFOUT_B168n	AF6	DO17B	DO8B		
4A	VREFB4A0	IO		CLK9p	DIFFIO RX_B168p	DIFFOUT_B168p	AG6	DO17B	DO8B		
		RREF_BR					AM1				
		DNU					AM2				
		DNU					AM3				
QXB_R0		REFCLK0Rp					AK8				
QXB_R0		REFCLK0Rn					AA7				
QXB_R0		GXB_RX_R0n,GXB_REFCLK_R0n					AK2				
QXB_R0		GXB_RX_R0p,GXB_REFCLK_R0p					AK1				
QXB_R0		GXB_TX_R0p					AJ3				
QXB_R0		GXB_TX_R0n					AJ4				
QXB_R0		GXB_RX_R1n,GXB_REFCLK_R1n					AH2				
QXB_R0		GXB_RX_R1p,GXB_REFCLK_R1p					AH1				
QXB_R0		GXB_TX_R1p					AG3				
QXB_R0		GXB_TX_R1n					AG4				
QXB_R0		GXB_RX_R2n,GXB_REFCLK_R2n					AF2				
QXB_R0		GXB_RX_R2p,GXB_REFCLK_R2p					AF1				
QXB_R0		GXB_TX_R2p					AE3				
QXB_R0		GXB_TX_R2n					AE4				
		GND					AD2				
		DNU					AD1				
		DNU					AC3				
		DNU					AC4				
		GND					AB2				
		DNU					AB1				
		DNU					AA3				
		DNU					AA4				
		GND					Y2				
		DNU					Y1				
		DNU					W3				
		DNU					W4				
		GND					W9				
		DNU					W8				
QXB_R1		REFCLK2Rp					U9				
QXB_R1		REFCLK2Rn					U8				
QXB_R1		GXB_RX_R6n,GXB_REFCLK_R6n					V2				
QXB_R1		GXB_RX_R6p,GXB_REFCLK_R6p					V1				
QXB_R1		GXB_TX_R6p					U3				
QXB_R1		GXB_TX_R6n					U4				
QXB_R1		GXB_RX_R7n,GXB_REFCLK_R7n					T2				
QXB_R1		GXB_RX_R7p,GXB_REFCLK_R7p					T1				
QXB_R1		GXB_TX_R7p					R3				
QXB_R1		GXB_TX_R7n					R4				
QXB_R1		GXB_RX_R8n,GXB_REFCLK_R8n					P2				
QXB_R1		GXB_RX_R8p,GXB_REFCLK_R8p					P1				
QXB_R1		GXB_TX_R8p					N3				
QXB_R1		GXB_TX_R8n					N4				
QXB_R1		GXB_RX_R9n,GXB_REFCLK_R9n					M2				
QXB_R1		GXB_RX_R9p,GXB_REFCLK_R9p					M1				
QXB_R1		GXB_TX_R9p					L3				
QXB_R1		GXB_TX_R9n					L4				
QXB_R1		GXB_RX_R10n,GXB_REFCLK_R10n					K2				
QXB_R1		GXB_RX_R10p,GXB_REFCLK_R10p					K1				



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F152	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
GXB_R1		GXB_TX_R10p					J3				
GXB_R1		GXB_TX_R10n					J4				
GXB_R1		GXB_RX_R11n,GXB_REFCLK_R11n					H2				
GXB_R1		GXB_RX_R11p,GXB_REFCLK_R11p					H1				
GXB_R1		GXB_TX_R11p					G3				
GXB_R1		GXB_TX_R11n					G4				
GXB_R1		REFCLK3R0					R9				
GXB_R1		REFCLK3Rn					R8				
7A		DN0					K5				
7A		GND					H5				
7A	VREFB7AN0		CLK12p		DIFFIO_RX_T1p	DIFFOUT_T1p	E3	DO1T		DO1T	
7A	VREFB7AN0		CLK12n		DIFFIO_RX_T1n	DIFFOUT_T1n	E4	DO1T		DO1T	
7A	VREFB7AN0		RZQ_5		DIFFIO_TX_T2p	DIFFOUT_T2p	E1	DO1T		DO1T	
7A	VREFB7AN0				DIFFIO_TX_T2n	DIFFOUT_T2n	F1				
7A	VREFB7AN0		CLK13p		DIFFIO_RX_T3p	DIFFOUT_T3p	D1	DO1T		DO1T	
7A	VREFB7AN0		CLK13n		DIFFIO_RX_T3n	DIFFOUT_T3n	E2	DO1T		DO1T	
7A	VREFB7AN0				DIFFIO_TX_T4p	DIFFOUT_T4p	G6	DO1T		DO1T	
7A	VREFB7AN0				DIFFIO_TX_T4n	DIFFOUT_T4n	H6				
7A	VREFB7AN0		CLK14p		DIFFIO_RX_T5p	DIFFOUT_T5p	C1	DQS1T/CO1T/COq1T/QKq1T	DQS1T/CO1T/COq1T/QKq1T		
7A	VREFB7AN0		CLK14n		DIFFIO_RX_T5n	DIFFOUT_T5n	C2	DQSn1T/QK1T	DQSn1T/QK1T		
7A	VREFB7AN0				DIFFIO_TX_T6p	DIFFOUT_T6p	E5	DO1T		DO1T	
7A	VREFB7AN0				DIFFIO_TX_T6n	DIFFOUT_T6n	F6				
7A	VREFB7AN0		FPLL_TR_CLKOUT2,FPLL_TR_FBp,FPLL_TR_FB1		DIFFIO_RX_T7p	DIFFOUT_T7p	C3	DO1T		DO1T	
7A	VREFB7AN0		FPLL_TR_CLKOUT3,FPLL_TR_FBn		DIFFIO_RX_T7n	DIFFOUT_T7n	D3	DO1T		DO1T	
7A	VREFB7AN0		FPLL_TR_CLKOUT0,FPLL_TR_CLKOUTp,FPLL_TR_FB0		DIFFIO_TX_T8p	DIFFOUT_T8p	J6	DO1T		DO1T	
7A	VREFB7AN0		FPLL_TR_CLKOUT1,FPLL_TR_CLKOUTn		DIFFIO_TX_T8n	DIFFOUT_T8n	K6				
7A	VREFB7AN0		CLK15p		DIFFIO_RX_T9p	DIFFOUT_T9p	A3	DO2T		DO1T	
7A	VREFB7AN0		CLK15n		DIFFIO_RX_T9n	DIFFOUT_T9n	B3	DO2T		DO1T	
7A	VREFB7AN0						L6	DO2T		DO1T	
7A	VREFB7AN0		VREFB7AN0				M7				
7A	VREFB7AN0			DEV OE	DIFFIO_RX_T10p	DIFFOUT_T10p	C8	DO2T		DO1T	
7A	VREFB7AN0			DEV CLRn	DIFFIO_RX_T10n	DIFFOUT_T10n	D5	DO2T		DO1T	
7A	VREFB7AN0				DIFFIO_TX_T11p	DIFFOUT_T11p	A2	DO2T		DO1T	
7A	VREFB7AN0			nPERSTL0	DIFFIO_TX_T11n	DIFFOUT_T11n	B2				
7A	VREFB7AN0			CAP_CONF_DONE	DIFFIO_RX_T12p	DIFFOUT_T12p	B5	DQS2T/CO2T/COq2T/QKq2T		DO1T	
7A	VREFB7AN0			CAC_ERROR	DIFFIO_RX_T12n	DIFFOUT_T12n	C4	DQSn2T/QK2T		DO1T	
7A	VREFB7AN0			PR_DONE	DIFFIO_TX_T13p	DIFFOUT_T13p	A5	DO2T		DO1T	
7A	VREFB7AN0			PR_REQUEST	DIFFIO_TX_T13n	DIFFOUT_T13n	A4				
7A	VREFB7AN0			INIT_DONE	DIFFIO_RX_T14p	DIFFOUT_T14p	D6	DO2T		DO1T	
7A	VREFB7AN0			nCEO	DIFFIO_RX_T14n	DIFFOUT_T14n	E6	DO2T		DO1T	
7A	VREFB7AN0			PR_ERROR	DIFFIO_TX_T15p	DIFFOUT_T15p	J7	DO2T		DO1T	
7A	VREFB7AN0			PR_READY	DIFFIO_TX_T15n	DIFFOUT_T15n	K7				
7B	VREFB7BN0				DIFFIO_RX_T32p	DIFFOUT_T32p	K9	DO3T		DO2T	DO4_7B_0
7B	VREFB7BN0				DIFFIO_RX_T32n	DIFFOUT_T32n	K8	DO3T		DO2T	DO4_7B_1
7B	VREFB7BN0						M10	DO3T		DO2T	DO4_7B_2
7B	VREFB7BN0		VREFB7BN0				P11				
7B	VREFB7BN0				DIFFIO_RX_T33p	DIFFOUT_T33p	C9	DO3T		DO2T	DO4_7B_3
7B	VREFB7BN0				DIFFIO_RX_T33n	DIFFOUT_T33n	D7	DO3T		DO2T	DO4_7B_4
7B	VREFB7BN0				DIFFIO_TX_T34p	DIFFOUT_T34p	E8	DO3T		DO2T	DO4_7B_5
7B	VREFB7BN0				DIFFIO_TX_T34n	DIFFOUT_T34n	F7				
7B	VREFB7BN0				DIFFIO_RX_T35p	DIFFOUT_T35p	N10	DQS3T/CO3T/COq3T/QKq3T	DQS3T/CO3T/COq3T/QKq3T	DO1T	DO54_7B
7B	VREFB7BN0				DIFFIO_RX_T35n	DIFFOUT_T35n	N11	DQSn3T/QK3T	DQSn3T/QK3T	DO1T	DO54_7B
7B	VREFB7BN0				DIFFIO_TX_T36p	DIFFOUT_T36p	G8	DO3T		DO2T	DM4_7B
7B	VREFB7BN0				DIFFIO_TX_T36n	DIFFOUT_T36n	G7				
7B	VREFB7BN0				DIFFIO_RX_T37p	DIFFOUT_T37p	H8	DO3T		DO2T	DO4_7B_6
7B	VREFB7BN0				DIFFIO_RX_T37n	DIFFOUT_T37n	J8	DO3T		DO2T	DO4_7B_7
7B	VREFB7BN0				DIFFIO_TX_T38p	DIFFOUT_T38p	L9	DO3T		DO2T	DO4_7B_8
7B	VREFB7BN0				DIFFIO_TX_T38n	DIFFOUT_T38n	M8				
7B	VREFB7BN0				DIFFIO_RX_T39p	DIFFOUT_T39p	B6	DO4T		DO2T	DO3_7B_0
7B	VREFB7BN0				DIFFIO_RX_T39n	DIFFOUT_T39n	C7	DO4T		DO2T	DO3_7B_1
7B	VREFB7BN0				DIFFIO_TX_T40p	DIFFOUT_T40p	E9	DO4T		DO2T	DO3_7B_2
7B	VREFB7BN0				DIFFIO_TX_T40n	DIFFOUT_T40n	F8				
7B	VREFB7BN0				DIFFIO_RX_T41p	DIFFOUT_T41p	A7	DO4T		DO2T	DO3_7B_3
7B	VREFB7BN0				DIFFIO_RX_T41n	DIFFOUT_T41n	A6	DO4T		DO2T	DO3_7B_4
7B	VREFB7BN0				DIFFIO_TX_T42p	DIFFOUT_T42p	G9	DO4T		DO2T	DO3_7B_5
7B	VREFB7BN0				DIFFIO_TX_T42n	DIFFOUT_T42n	H9				
7B	VREFB7BN0				DIFFIO_RX_T43p	DIFFOUT_T43p	D8	DQS4T/CO4T/COq4T/QKq4T		DO2T	DO53_7B
7B	VREFB7BN0				DIFFIO_RX_T43n	DIFFOUT_T43n	D9	DQSn4T/QK4T		DO2T	DO53_7B
7B	VREFB7BN0				DIFFIO_TX_T44p	DIFFOUT_T44p	A8	DO4T		DO2T	DM3_7B
7B	VREFB7BN0				DIFFIO_TX_T44n	DIFFOUT_T44n	B8				
7B	VREFB7BN0				DIFFIO_RX_T45p	DIFFOUT_T45p	A10	DO4T		DO2T	DO3_7B_6
7B	VREFB7BN0				DIFFIO_RX_T45n	DIFFOUT_T45n	B9	DO4T		DO2T	DO3_7B_7
7B	VREFB7BN0				DIFFIO_TX_T46p	DIFFOUT_T46p	I10	DO4T		DO2T	DO3_7B_8
7B	VREFB7BN0				DIFFIO_TX_T46n	DIFFOUT_T46n	K10				
7C	VREFB7CN0				DIFFIO_RX_T47p	DIFFOUT_T47p	F10	DO5T		DO3T	DO2_7C_0
7C	VREFB7CN0				DIFFIO_RX_T47n	DIFFOUT_T47n	G10	DO5T		DO3T	DO2_7C_1
7C	VREFB7CN0				DIFFIO_TX_T48p	DIFFOUT_T48p	J11	DO5T		DO3T	DO2_7C_2
7C	VREFB7CN0				DIFFIO_TX_T48n	DIFFOUT_T48n	K11				
7C	VREFB7CN0				DIFFIO_RX_T49p	DIFFOUT_T49p	G11	DO5T		DO3T	DO2_7C_3
7C	VREFB7CN0				DIFFIO_RX_T49n	DIFFOUT_T49n	H11	DO5T		DO3T	DO2_7C_4
7C	VREFB7CN0				DIFFIO_TX_T50p	DIFFOUT_T50p	K12	DO5T		DO3T	DO2_7C_5
7C	VREFB7CN0				DIFFIO_TX_T50n	DIFFOUT_T50n	L11				
7C	VREFB7CN0				DIFFIO_RX_T51p	DIFFOUT_T51p	E11	DQS5T/CO5T/COq5T/QKq5T	DQS3T/CO3T/COq3T/QKq3T	DO1T	DO52_7C
7C	VREFB7CN0				DIFFIO_RX_T51n	DIFFOUT_T51n	F11	DQSn5T/QK5T	DQSn3T/QK3T	DO1T	DO52_7C
7C	VREFB7CN0				DIFFIO_TX_T52p	DIFFOUT_T52p	C10	DO5T		DO3T	DM2_7C
7C	VREFB7CN0				DIFFIO_TX_T52n	DIFFOUT_T52n	D10				
7C	VREFB7CN0				DIFFIO_RX_T53p	DIFFOUT_T53p	G12	DO5T		DO3T	DO2_7C_6
7C	VREFB7CN0				DIFFIO_RX_T53n	DIFFOUT_T53n	H12	DO5T		DO3T	DO2_7C_7
7C	VREFB7CN0				DIFFIO_TX_T54p	DIFFOUT_T54p	L12	DO5T		DO3T	DO2_7C_8
7C	VREFB7CN0				DIFFIO_TX_T54n	DIFFOUT_T54n	M12				
7C	VREFB7CN0				DIFFIO_RX_T55p	DIFFOUT_T55p	A11	DO6T		DO3T	DO1_7C_0
7C	VREFB7CN0				DIFFIO_RX_T55n	DIFFOUT_T55n	B11	DO6T		DO3T	DO1_7C_1
7C	VREFB7CN0						N13	DO6T		DO3T	DO1_7C_2
7C	VREFB7CN0		VREFB7CN0				M13				
7C	VREFB7CN0				DIFFIO_RX_T56p	DIFFOUT_T56p	C11	DO6T		DO3T	DO1_7C_3
7C	VREFB7CN0				DIFFIO_RX_T56n	DIFFOUT_T56n	D11	DO6T		DO3T	DO1_7C_4
7C	VREFB7CN0				DIFFIO_TX_T57p	DIFFOUT_T57p	J13	DO6T		DO3T	DO1_7C_5
7C	VREFB7CN0				DIFFIO_TX_T57n	DIFFOUT_T57n	K13				
7C	VREFB7CN0				DIFFIO_RX_T58p	DIFFOUT_T58p	A13	DQS6T/CO6T/COq6T/QKq6T		DO3T	DQS1_7C



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
7C	VREFB7C0N	IO			DIFFIO_RX_T58n	DIFFOUT_T58n	B12	DQSh8T/QK8T	DQ3T	DO1T	DQS#_7C
7C	VREFB7C0N	IO			DIFFIO_TX_T59p	DIFFOUT_T59p	D12	DO8T	DQ3T	DO1T	DM1_7C
7C	VREFB7C0N	IO			DIFFIO_TX_T59n	DIFFOUT_T59n	E12				
7C	VREFB7C0N	IO			DIFFIO_RX_T60p	DIFFOUT_T60p	F13	DO6T	DQ3T	DO1T	DO1_7C_6
7C	VREFB7C0N	IO			DIFFIO_RX_T60n	DIFFOUT_T60n	G13	DO8T	DQ3T	DO1T	DO1_7C_7
7C	VREFB7C0N	IO			DIFFIO_TX_T61p	DIFFOUT_T61p	M11	DO6T	DQ3T	DO1T	DO1_7C_8
7C	VREFB7C0N	IO			DIFFIO_TX_T61n	DIFFOUT_T61n	N12				RESET#_7D
7D	VREFB7D0N	IO			DIFFIO_RX_T62p	DIFFOUT_T62p	H14	DO7T	DQ4T		CK_7D
7D	VREFB7D0N	IO			DIFFIO_RX_T62n	DIFFOUT_T62n	J14	DO7T	DQ4T		CK#_7D
7D	VREFB7D0N	IO			DIFFIO_TX_T63p	DIFFOUT_T63p	K14	DO7T	DQ4T		CKE_7D_0
7D	VREFB7D0N	IO			DIFFIO_TX_T63n	DIFFOUT_T63n	L14				CKE_7D_1
7D	VREFB7D0N	IO			DIFFIO_RX_T64p	DIFFOUT_T64p	F14	DO7T	DQ4T		A_7D_0
7D	VREFB7D0N	IO			DIFFIO_RX_T64n	DIFFOUT_T64n	G14	DO7T	DQ4T		A_7D_1
7D	VREFB7D0N	IO			DIFFIO_TX_T65p	DIFFOUT_T65p	M14	DO7T	DQ4T		A_7D_2
7D	VREFB7D0N	IO			DIFFIO_TX_T65n	DIFFOUT_T65n	M15				A_7D_3
7D	VREFB7D0N	IO			DIFFIO_RX_T66p	DIFFOUT_T66p	G15	DQS#T/CQ#T/CQn#T/QK#nT	DQS#T/CQ#T/CQn#T/QK#nT		A_7D_4
7D	VREFB7D0N	IO			DIFFIO_RX_T66n	DIFFOUT_T66n	H15	DQS#T/QK#T	DQS#T/QK#T		A_7D_5
7D	VREFB7D0N	IO			DIFFIO_TX_T67p	DIFFOUT_T67p	C13	DO7T	DQ4T		A_7D_6
7D	VREFB7D0N	IO			DIFFIO_TX_T67n	DIFFOUT_T67n	D13				A_7D_7
7D	VREFB7D0N	IO			DIFFIO_RX_T68p	DIFFOUT_T68p	D14	DO7T	DQ4T		A_7D_8
7D	VREFB7D0N	IO			DIFFIO_RX_T68n	DIFFOUT_T68n	E14	DO7T	DQ4T		A_7D_9
7D	VREFB7D0N	IO			DIFFIO_TX_T69p	DIFFOUT_T69p	K15	DO7T	DQ4T		A_7D_10
7D	VREFB7D0N	IO			DIFFIO_TX_T69n	DIFFOUT_T69n	L15				A_7D_11
7D	VREFB7D0N	IO			DIFFIO_RX_T70p	DIFFOUT_T70p	B14	DO8T	DQ4T		A_7D_12
7D	VREFB7D0N	IO			DIFFIO_RX_T70n	DIFFOUT_T70n	C14	DO8T	DQ4T		A_7D_13
7D	VREFB7D0N	IO					N14	DO8T	DQ4T		A_7D_14
7D	VREFB7D0N	IO	VREFB7D0N								
7D	VREFB7D0N	IO			DIFFIO_RX_T71p	DIFFOUT_T71p	A14	DO8T	DQ4T		BA_7D_0
7D	VREFB7D0N	IO			DIFFIO_RX_T71n	DIFFOUT_T71n	B15	DO8T	DQ4T		BA_7D_1
7D	VREFB7D0N	IO			DIFFIO_TX_T72p	DIFFOUT_T72p	D15	DO8T	DQ4T		BA_7D_2
7D	VREFB7D0N	IO			DIFFIO_TX_T72n	DIFFOUT_T72n	E15				RAS#_7D
7D	VREFB7D0N	IO			DIFFIO_RX_T73p	DIFFOUT_T73p	F16	DQS#T/CQ#T/CQn#T/QK#nT	DQ4T		CAS#_7D
7D	VREFB7D0N	IO			DIFFIO_RX_T73n	DIFFOUT_T73n	G16	DQS#8T/QK8T	DQ4T		WE#_7D
7D	VREFB7D0N	IO			DIFFIO_TX_T74p	DIFFOUT_T74p	J16	DO8T	DQ4T		ODT_7D_0
7D	VREFB7D0N	IO			DIFFIO_TX_T74n	DIFFOUT_T74n	K16				ODT_7D_1
7D	VREFB7D0N	IO			DIFFIO_RX_T75p	DIFFOUT_T75p	C16	DO8T	DQ4T		A_7D_15
7D	VREFB7D0N	IO			DIFFIO_RX_T75n	DIFFOUT_T75n	D16	DO8T	DQ4T		
7D	VREFB7D0N	IO			DIFFIO_TX_T76p	DIFFOUT_T76p	M16	DO8T	DQ4T		CS#_7D_0
7D	VREFB7D0N	IO			DIFFIO_TX_T76n	DIFFOUT_T76n	N16				CS#_7D_1
		VCCA_FPLL					R17				
		VCCD_FPLL					R16				
		DNV					L18				
8D	VREFB8D0N	IO	CLK18p		DIFFIO_RX_T85p	DIFFOUT_T85p	A16	DO8T	DQ5T		
8D	VREFB8D0N	IO	CLK19n		DIFFIO_RX_T85n	DIFFOUT_T85n	A17	DO8T	DQ5T		
8D	VREFB8D0N	IO			DIFFIO_TX_T86p	DIFFOUT_T86p	K17	DO8T	DQ5T		
8D	VREFB8D0N	IO			DIFFIO_TX_T86n	DIFFOUT_T86n	L17				
8D	VREFB8D0N	IO	CLK18p		DIFFIO_RX_T87p	DIFFOUT_T87p	K18	DO8T	DQ5T		
8D	VREFB8D0N	IO	CLK18n		DIFFIO_RX_T87n	DIFFOUT_T87n	K19	DO8T	DQ5T		
8D	VREFB8D0N	IO			DIFFIO_TX_T88p	DIFFOUT_T88p	D17	DO8T	DQ5T		
8D	VREFB8D0N	IO			DIFFIO_TX_T88n	DIFFOUT_T88n	E17				
8D	VREFB8D0N	IO		FPLL_TC_CLKOUT2,FPLL_TC_FBp,FPLL_TC_FB1	DIFFIO_RX_T89p	DIFFOUT_T89p	F17	DQS#T/CQ#T/CQn#T/QK#nT	DQS#T/CQ#T/CQn#T/QK#nT		
8D	VREFB8D0N	IO		FPLL_TC_CLKOUT3,FPLL_TC_FBn	DIFFIO_RX_T89n	DIFFOUT_T89n	G17	DQS#8T/QK8T	DQS#8T/QK8T		
8D	VREFB8D0N	IO		FPLL_TC_CLKOUT0,FPLL_TC_CLKOUTp,FPLL_TC_FB0	DIFFIO_TX_T90p	DIFFOUT_T90p	M17	DO8T	DQ5T		
8D	VREFB8D0N	IO		FPLL_TC_CLKOUT1,FPLL_TC_CLKOUTn	DIFFIO_TX_T90n	DIFFOUT_T90n	N17				
8D	VREFB8D0N	IO	CLK17p		DIFFIO_RX_T91p	DIFFOUT_T91p	H17	DO8T	DQ5T		
8D	VREFB8D0N	IO	CLK17n		DIFFIO_RX_T91n	DIFFOUT_T91n	J17	DO8T	DQ5T		
8D	VREFB8D0N	IO			DIFFIO_TX_T92p	DIFFOUT_T92p	B17	DO9T	DQ5T		
8D	VREFB8D0N	IO			DIFFIO_TX_T92n	DIFFOUT_T92n	C17				
8D	VREFB8D0N	IO	CLK16p		DIFFIO_RX_T93p	DIFFOUT_T93p	A19	DO10T	DQ5T		
8D	VREFB8D0N	IO	CLK16n		DIFFIO_RX_T93n	DIFFOUT_T93n	A20	DO10T	DQ5T		
8D	VREFB8D0N	IO					M18	DO10T	DQ5T		
8D	VREFB8D0N	IO		VREFB8D0N			N18				
8D	VREFB8D0N	IO			DIFFIO_RX_T94p	DIFFOUT_T94p	C19	DO10T	DQ5T		
8D	VREFB8D0N	IO			DIFFIO_RX_T94n	DIFFOUT_T94n	B18	DO10T	DQ5T		
8D	VREFB8D0N	IO			DIFFIO_TX_T95p	DIFFOUT_T95p	G18	DO10T	DQ5T		
8D	VREFB8D0N	IO			DIFFIO_TX_T95n	DIFFOUT_T95n	G19				
8D	VREFB8D0N	IO			DIFFIO_RX_T96p	DIFFOUT_T96p	H18	DQS#T/CQ#T/CQn#T/QK#nT	DQ5T		
8D	VREFB8D0N	IO			DIFFIO_RX_T96n	DIFFOUT_T96n	J19	DQS#T/QK#T	DQ5T		
8D	VREFB8D0N	IO			DIFFIO_TX_T97p	DIFFOUT_T97p	M19	DO10T	DQ5T		
8D	VREFB8D0N	IO			DIFFIO_TX_T97n	DIFFOUT_T97n	N19				
8D	VREFB8D0N	IO			DIFFIO_RX_T98p	DIFFOUT_T98p	D19	DO10T	DQ5T		
8D	VREFB8D0N	IO			DIFFIO_RX_T98n	DIFFOUT_T98n	D18	DO10T	DQ5T		
8D	VREFB8D0N	IO			DIFFIO_TX_T99p	DIFFOUT_T99p	E18	DO10T	DQ5T		
8D	VREFB8D0N	IO			DIFFIO_TX_T99n	DIFFOUT_T99n	F19				
8C	VREFB8C0N	IO			DIFFIO_RX_T116p	DIFFOUT_T116p	K20	DO11T	DQ6T	DO2T	
8C	VREFB8C0N	IO			DIFFIO_RX_T116n	DIFFOUT_T116n	L20	DO11T	DQ6T	DO2T	
8C	VREFB8C0N	IO					M20	DO11T	DQ6T	DO2T	
8C	VREFB8C0N	IO		VREFB8C0N			N20				
8C	VREFB8C0N	IO			DIFFIO_RX_T117p	DIFFOUT_T117p	A22	DO11T	DQ6T	DO2T	
8C	VREFB8C0N	IO			DIFFIO_RX_T117n	DIFFOUT_T117n	B21	DO11T	DQ6T	DO2T	
8C	VREFB8C0N	IO			DIFFIO_TX_T118p	DIFFOUT_T118p	B20	DO11T	DQ6T	DO2T	
8C	VREFB8C0N	IO			DIFFIO_TX_T118n	DIFFOUT_T118n	C20				
8C	VREFB8C0N	IO			DIFFIO_RX_T119p	DIFFOUT_T119p	D20	DQS#T/CQ#T/CQn#T/QK#nT	DQS#T/CQ#T/CQn#T/QK#nT	DO2T	
8C	VREFB8C0N	IO			DIFFIO_RX_T119n	DIFFOUT_T119n	E20	DQS#T/QK#T	DQS#T/QK#T	DO2T	
8C	VREFB8C0N	IO			DIFFIO_TX_T120p	DIFFOUT_T120p	K21	DO11T	DQ6T	DO2T	
8C	VREFB8C0N	IO			DIFFIO_TX_T120n	DIFFOUT_T120n	L21				
8C	VREFB8C0N	IO			DIFFIO_RX_T121p	DIFFOUT_T121p	F20	DO11T	DQ6T	DO2T	
8C	VREFB8C0N	IO			DIFFIO_RX_T121n	DIFFOUT_T121n	G20	DO11T	DQ6T	DO2T	
8C	VREFB8C0N	IO			DIFFIO_TX_T122p	DIFFOUT_T122p	H20	DO11T	DQ6T	DO2T	
8C	VREFB8C0N	IO			DIFFIO_TX_T122n	DIFFOUT_T122n	J20				
8C	VREFB8C0N	IO			DIFFIO_RX_T123p	DIFFOUT_T123p	D21	DO12T	DQ6T	DO2T	
8C	VREFB8C0N	IO			DIFFIO_RX_T123n	DIFFOUT_T123n	E21	DO12T	DQ6T	DO2T	
8C	VREFB8C0N	IO			DIFFIO_TX_T124p	DIFFOUT_T124p	M21	DO12T	DQ6T	DO2T	
8C	VREFB8C0N	IO			DIFFIO_TX_T124n	DIFFOUT_T124n	N21				
8C	VREFB8C0N	IO			DIFFIO_RX_T125p	DIFFOUT_T125p	C22	DO12T	DQ6T	DO2T	
8C	VREFB8C0N	IO			DIFFIO_RX_T125n	DIFFOUT_T125n	D22	DO12T	DQ6T	DO2T	
8C	VREFB8C0N	IO			DIFFIO_TX_T126p	DIFFOUT_T126p	G21	DO12T	DQ6T	DO2T	
8C	VREFB8C0N	IO			DIFFIO_TX_T126n	DIFFOUT_T126n	H21				
8C	VREFB8C0N	IO			DIFFIO_RX_T127p	DIFFOUT_T127p	F22	DQS#T/CQ#T/CQn#T/QK#nT	DQ6T	DQS#T/CQ#T/CQn#T/QK#nT	



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
8C	VREFB8C0	IO			DIFFIO_RX_T127n	DIFFOUT_T127n	G22	DQSn1T/QK12T	DQ6T	DQSn2T/QK2T	
8C	VREFB8C0	IO			DIFFIO_TX_T128p	DIFFOUT_T128p	M22	DO12T	DQ6T	DQ2T	
8C	VREFB8C0	IO			DIFFIO_TX_T128n	DIFFOUT_T128n	N22				
8C	VREFB8C0	IO			DIFFIO_RX_T129p	DIFFOUT_T129p	A23	DO12T	DQ6T	DO2T	
8C	VREFB8C0	IO			DIFFIO_RX_T129n	DIFFOUT_T129n	B23	DO12T	DQ6T	DO2T	
8C	VREFB8C0	IO			DIFFIO_TX_T130p	DIFFOUT_T130p	J23	DO12T		DQ6T	
8C	VREFB8C0	IO			DIFFIO_TX_T130n	DIFFOUT_T130n	K22				
8B	VREFB8B0	IO			DIFFIO_RX_T131p	DIFFOUT_T131p	H23	DO13T		DQ7T	DO2T
8B	VREFB8B0	IO			DIFFIO_RX_T131n	DIFFOUT_T131n	J23	DO13T		DQ7T	DO2T
8B	VREFB8B0	IO			DIFFIO_TX_T132p	DIFFOUT_T132p	K24	DO13T		DQ7T	DO2T
8B	VREFB8B0	IO			DIFFIO_TX_T132n	DIFFOUT_T132n	L24				
8B	VREFB8B0	IO			DIFFIO_RX_T133p	DIFFOUT_T133p	B24	DO13T		DQ7T	DO2T
8B	VREFB8B0	IO			DIFFIO_RX_T133n	DIFFOUT_T133n	C23	DO13T		DQ7T	DO2T
8B	VREFB8B0	IO			DIFFIO_TX_T134p	DIFFOUT_T134p	D23	DO13T		DQ7T	DO2T
8B	VREFB8B0	IO			DIFFIO_TX_T134n	DIFFOUT_T134n	E23				
8B	VREFB8B0	IO			DIFFIO_RX_T135p	DIFFOUT_T135p	F23	DQS13T/CQ13T/CQn13T/QKn13T	DQS7T/CQ7T/CQn7T/QKn7T	DO2T	
8B	VREFB8B0	IO			DIFFIO_RX_T135n	DIFFOUT_T135n	G23	DQSn13T/QK13T	DQSn7T/QK7T	DO2T	
8B	VREFB8B0	IO			DIFFIO_TX_T136p	DIFFOUT_T136p	M23	DO13T		DQ7T	DO2T
8B	VREFB8B0	IO			DIFFIO_TX_T136n	DIFFOUT_T136n	N23				
8B	VREFB8B0	IO			DIFFIO_RX_T137p	DIFFOUT_T137p	D24	DO13T		DQ7T	DO2T
8B	VREFB8B0	IO			DIFFIO_RX_T137n	DIFFOUT_T137n	E24	DO13T		DQ7T	DO2T
8B	VREFB8B0	IO			DIFFIO_TX_T138p	DIFFOUT_T138p	K23	DO13T		DQ7T	DO2T
8B	VREFB8B0	IO			DIFFIO_TX_T138n	DIFFOUT_T138n	L23				
8B	VREFB8B0	IO			DIFFIO_RX_T139p	DIFFOUT_T139p	G24	DO14T		DQ7T	DO2T
8B	VREFB8B0	IO			DIFFIO_RX_T139n	DIFFOUT_T139n	H24	DO14T		DQ7T	DO2T
8B	VREFB8B0	IO					N24	DO14T		DQ7T	DO2T
8B	VREFB8B0	IO	VREFB8B0				N24				
8B	VREFB8B0	IO			DIFFIO_RX_T140p	DIFFOUT_T140p	A26	DO14T		DQ7T	DO2T
8B	VREFB8B0	IO			DIFFIO_RX_T140n	DIFFOUT_T140n	A25	DO14T		DQ7T	DO2T
8B	VREFB8B0	IO			DIFFIO_TX_T141p	DIFFOUT_T141p	C25	DO14T		DQ7T	DO2T
8B	VREFB8B0	IO			DIFFIO_TX_T141n	DIFFOUT_T141n	D25				
8B	VREFB8B0	IO			DIFFIO_RX_T142p	DIFFOUT_T142p	F26	DQS14T/CQ14T/CQn14T/QKn14T	DO7T	DO2T	
8B	VREFB8B0	IO			DIFFIO_RX_T142n	DIFFOUT_T142n	G25	DQSn14T/QK14T	DQ7T	DO2T	
8B	VREFB8B0	IO			DIFFIO_TX_T143p	DIFFOUT_T143p	M25	DO14T		DQ7T	DO2T
8B	VREFB8B0	IO			DIFFIO_TX_T143n	DIFFOUT_T143n	N25				
8B	VREFB8B0	IO			DIFFIO_RX_T144p	DIFFOUT_T144p	B26	DO14T		DQ7T	DO2T
8B	VREFB8B0	IO			DIFFIO_RX_T144n	DIFFOUT_T144n	C26	DO14T		DQ7T	DO2T
8B	VREFB8B0	IO			DIFFIO_TX_T145p	DIFFOUT_T145p	J25	DO14T		DQ7T	DO2T
8B	VREFB8B0	IO			DIFFIO_TX_T145n	DIFFOUT_T145n	K25				
8A	VREFB8A0	IO			DIFFIO_RX_T146p	DIFFOUT_T146p	E26	DO15T		DQ8T	
8A	VREFB8A0	IO			DIFFIO_RX_T146n	DIFFOUT_T146n	F26	DO15T		DQ8T	
8A	VREFB8A0	IO			DIFFIO_TX_T147p	DIFFOUT_T147p	K29	DO15T		DQ8T	
8A	VREFB8A0	IO			DIFFIO_TX_T147n	DIFFOUT_T147n	L29				
8A	VREFB8A0	IO			DIFFIO_RX_T148p	DIFFOUT_T148p	D26	DO15T		DQ8T	
8A	VREFB8A0	IO			DIFFIO_RX_T148n	DIFFOUT_T148n	E27	DO15T		DQ8T	
8A	VREFB8A0	IO			DIFFIO_TX_T149p	DIFFOUT_T149p	A27	DO15T		DQ8T	
8A	VREFB8A0	IO			DIFFIO_TX_T149n	DIFFOUT_T149n	B27				
8A	VREFB8A0	IO			DIFFIO_RX_T150p	DIFFOUT_T150p	G26	DQS15T/CQ15T/CQn15T/QKn15T	DQS8T/CQ8T/CQn8T/QKn8T		
8A	VREFB8A0	IO			DIFFIO_RX_T150n	DIFFOUT_T150n	H26	DQSn15T/QK15T	DQS8T/QK8T		
8A	VREFB8A0	IO			DIFFIO_TX_T151p	DIFFOUT_T151p	K27	DO15T		DQ8T	
8A	VREFB8A0	IO			DIFFIO_TX_T151n	DIFFOUT_T151n	L27				
8A	VREFB8A0	IO			DIFFIO_RX_T152p	DIFFOUT_T152p	D27	DO15T		DQ8T	
8A	VREFB8A0	IO			DIFFIO_RX_T152n	DIFFOUT_T152n	C28	DO15T		DQ8T	
8A	VREFB8A0	IO			DIFFIO_TX_T153p	DIFFOUT_T153p	C29	DO15T		DQ8T	
8A	VREFB8A0	IO			DIFFIO_TX_T153n	DIFFOUT_T153n	D28				
8A	VREFB8A0	IO			DIFFIO_RX_T154p	DIFFOUT_T154p	G27	DO16T		DQ8T	
8A	VREFB8A0	IO			DIFFIO_RX_T154n	DIFFOUT_T154n	G28	DO16T		DQ8T	
8A	VREFB8A0	IO			DIFFIO_TX_T155p	DIFFOUT_T155p	J26	DO16T		DQ8T	
8A	VREFB8A0	IO			DIFFIO_TX_T155n	DIFFOUT_T155n	K26				
8A	VREFB8A0	IO			DIFFIO_RX_T156p	DIFFOUT_T156p	A29	DO16T		DQ8T	
8A	VREFB8A0	IO			DIFFIO_RX_T156n	DIFFOUT_T156n	A28	DO16T		DQ8T	
8A	VREFB8A0	IO			DIFFIO_TX_T157p	DIFFOUT_T157p	B29	DO16T		DQ8T	
8A	VREFB8A0	IO			DIFFIO_TX_T157n	DIFFOUT_T157n	B30				
8A	VREFB8A0	IO			DIFFIO_RX_T158p	DIFFOUT_T158p	F28	DQS16T/CQ16T/CQn16T/QKn16T	DQ8T		
8A	VREFB8A0	IO			DIFFIO_RX_T158n	DIFFOUT_T158n	F29	DQSn16T/QK16T	DQ8T		
8A	VREFB8A0	IO			DIFFIO_TX_T159p	DIFFOUT_T159p	H27	DO16T		DQ8T	
8A	VREFB8A0	IO			DIFFIO_TX_T159n	DIFFOUT_T159n	J27				
8A	VREFB8A0	IO	CLK23p		DIFFIO_RX_T160p	DIFFOUT_T160p	D29	DO16T		DQ8T	
8A	VREFB8A0	IO	CLK23n		DIFFIO_RX_T160n	DIFFOUT_T160n	E29	DO16T		DQ8T	
8A	VREFB8A0	IO			DIFFIO_TX_T161p	DIFFOUT_T161p	D30	DO16T		DQ8T	
8A	VREFB8A0	IO			DIFFIO_TX_T161n	DIFFOUT_T161n	E30				
8A	VREFB8A0	IO	CLK22p		DIFFIO_RX_T162p	DIFFOUT_T162p	G29	DO17T			
8A	VREFB8A0	IO	CLK22n		DIFFIO_RX_T162n	DIFFOUT_T162n	H29	DO17T			
8A	VREFB8A0	IO					L26	DO17T			
8A	VREFB8A0	IO	VREFB8A0				M27				
8A	VREFB8A0	IO	FPLL_TL_CLKOUT2,FPLL_TL_FBp,FPLL_TL_FB1		DIFFIO_RX_T163p	DIFFOUT_T163p	A31	DO17T			
8A	VREFB8A0	IO	FPLL_TL_CLKOUT3,FPLL_TL_FBn		DIFFIO_RX_T163n	DIFFOUT_T163n	A30	DO17T			
8A	VREFB8A0	IO	FPLL_TL_CLKOUT0,FPLL_TL_CLKOUTp,FPLL_TL_FB0		DIFFIO_TX_T164p	DIFFOUT_T164p	C31	DO17T			
8A	VREFB8A0	IO	FPLL_TL_CLKOUT1,FPLL_TL_CLKOUTn		DIFFIO_TX_T164n	DIFFOUT_T164n	D31				
8A	VREFB8A0	IO	CLK21p		DIFFIO_RX_T165p	DIFFOUT_T165p	A32	DQS17T/CQ17T/CQn17T/QKn17T			
8A	VREFB8A0	IO	CLK21n		DIFFIO_RX_T165n	DIFFOUT_T165n	B32	DQSn17T/QK17T			
8A	VREFB8A0	IO			DIFFIO_TX_T166p	DIFFOUT_T166p	J28	DO17T			
8A	VREFB8A0	IO			DIFFIO_TX_T166n	DIFFOUT_T166n	K28				
8A	VREFB8A0	IO	CLK20p		DIFFIO_RX_T167p	DIFFOUT_T167p	D33	DO17T			
8A	VREFB8A0	IO	CLK20n		DIFFIO_RX_T167n	DIFFOUT_T167n	C32	DO17T			
8A	VREFB8A0	IO			DIFFIO_TX_T168p	DIFFOUT_T168p	D32	DO17T			
8A	VREFB8A0	IO	RZQ_6		DIFFIO_TX_T168n	DIFFOUT_T168n	E32				
8A		MSEL0		MSEL0						D34	
8A		MSEL1		MSEL1						H30	
8A		MSEL2		MSEL2						K30	
8A		MSEL3		MSEL3						M29	
8A		MSEL4		MSEL4						M30	
8A	CONF_DONE			CONF_DONE						G34	
8A	nSTATUS			nSTATUS						B34	
8A	nCE			nCE						A33	
8A	nCONFIG			nCONFIG						C33	
8A	GND									B33	
8A	GND									A28	
8A	GND									A33	



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
		GND					AA34				
		GND					AB27				
		GND					AB28				
		GND					AB29				
		GND					AB30				
		GND					AB31				
		GND					AB32				
		GND					AC30				
		GND					AC33				
		GND					AC34				
		GND					AD31				
		GND					AD32				
		GND					AE30				
		GND					AE33				
		GND					AE34				
		GND					AF31				
		GND					AF32				
		GND					AG30				
		GND					AG33				
		GND					AG34				
		GND					AH31				
		GND					AH32				
		GND					AJ30				
		GND					AJ33				
		GND					AJ34				
		GND					AK31				
		GND					AK32				
		GND					AL33				
		GND					AL34				
		GND					E34				
		GND					F31				
		GND					F32				
		GND					G30				
		GND					G33				
		GND					G34				
		GND					H31				
		GND					H32				
		GND					J30				
		GND					J33				
		GND					J34				
		GND					K31				
		GND					K32				
		GND					L30				
		GND					L33				
		GND					L34				
		GND					M31				
		GND					M32				
		GND					N28				
		GND					N29				
		GND					N33				
		GND					N34				
		GND					P27				
		GND					P31				
		GND					P32				
		GND					R28				
		GND					R30				
		GND					R33				
		GND					R34				
		GND					T27				
		GND					T29				
		GND					T31				
		GND					T32				
		GND					U28				
		GND					U33				
		GND					U34				
		GND					V27				
		GND					V31				
		GND					V32				
		GND					W28				
		GND					W30				
		GND					W33				
		GND					W34				
		GND					Y27				
		GND					Y29				
		GND					Y31				
		GND					Y32				
		GND					AA1				
		GND					AA2				
		GND					AA9				
		GND					AB3				
		GND					AB4				
		GND					AB5				
		GND					AB7				
		GND					AB8				
		GND					AC1				
		GND					AC2				
		GND					AC5				
		GND					AD3				
		GND					AD4				
		GND					AE1				
		GND					AE2				
		GND					AE5				
		GND					AF3				
		GND					AF4				
		GND					AG1				
		GND					AG2				
		GND					AG5				
		GND					AH3				
		GND					AH4				



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
		GND					AJ1				
		GND					AJ2				
		GND					AJ5				
		GND					AK3				
		GND					AK4				
		GND					AL1				
		GND					AL2				
		GND					AL3				
		GND					AN1				
		GND					F3				
		GND					F4				
		GND					G1				
		GND					G2				
		GND					G5				
		GND					H3				
		GND					H4				
		GND					J1				
		GND					J2				
		GND					J5				
		GND					K3				
		GND					K4				
		GND					L1				
		GND					L2				
		GND					L5				
		GND					M3				
		GND					M4				
		GND					M5				
		GND					N1				
		GND					N2				
		GND					N6				
		GND					P3				
		GND					P4				
		GND					P6				
		GND					R1				
		GND					R2				
		GND					R5				
		GND					R7				
		GND					T3				
		GND					T4				
		GND					T6				
		GND					T8				
		GND					U1				
		GND					U2				
		GND					U7				
		GND					V3				
		GND					V4				
		GND					V8				
		GND					W1				
		GND					W2				
		GND					W5				
		GND					W7				
		GND					Y3				
		GND					Y4				
		GND					Y6				
		GND					Y8				
		VCCP					P18				
		VCCP					R13				
		VCCP					R21				
		VCCP					T10				
		VCCP					U25				
		VCCP					V10				
		VCCP					W25				
		VCCP					Y12				
		VCCP					Y19				
		VCCP					Y22				
		VCCA_FPLL					V26				
		VCCA_FPLL					V9				
		VCCA_FPLL					T26				
		VCCA_FPLL					T9				
		VCCBAT					M28				
		VCC_AUX					P12				
		VCC_AUX					P24				
		VCC_AUX					W11				
		VCC_AUX					Y24				
		VCCD_FPLL					Y26				
		VCCD_FPLL					Y9				
		VCCD_FPLL					P26				
		VCCD_FPLL					P9				
		VCCA_GXBLO					V28				
		VCCA_GXBRO					Y7				
		VCCA_GXBL1					T28				
		VCCA_GXBR1					T7				
		VCCH_GXBLO					V28				
		VCCH_GXBRO					V7				
		VCCH_GXBL1					P28				
		VCCH_GXBR1					P7				
		VCCL_GXBLO					V29				
		VCCL_GXBLO					V30				
		VCCL_GXBRO					V5				
		VCCL_GXBRO					V6				
		VCCL_GXBL1					P29				
		VCCL_GXBL1					P30				
		VCCL_GXBR1					P5				
		VCCL_GXBR1					P6				
		VCCR_GXBL					AA29				
		VCCR_GXBL					AA30				
		VCCR_GXBL					N30				
		VCCR_GXBL					U29				
		VCCR_GXBL					U30				



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F152	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
		VCCR_GXBR					AA5				
		VCCR_GXBR					AA6				
		VCCR_GXBR					N5				
		VCCR_GXBR					U5				
		VCCR_GXBR					U6				
		VCCT_GXBLO					W29				
		VCCT_GXBLO					Y30				
		VCCT_GXBR0					W6				
		VCCT_GXBR0					Y5				
		VCCT_GXBL1					R29				
		VCCT_GXBL1					T30				
		VCCT_GXBR1					R6				
		VCCT_GXBR1					T5				
		VCC					R14				
		VCC					R15				
		VCC					R19				
		VCC					R23				
		VCC					R25				
		VCC					T12				
		VCC					T14				
		VCC					T16				
		VCC					T18				
		VCC					T20				
		VCC					T22				
		VCC					T24				
		VCC					U11				
		VCC					U12				
		VCC					U13				
		VCC					U15				
		VCC					U17				
		VCC					U19				
		VCC					U20				
		VCC					U21				
		VCC					U22				
		VCC					U23				
		VCC					V12				
		VCC					V14				
		VCC					V16				
		VCC					V20				
		VCC					V22				
		VCC					V24				
		VCC					W13				
		VCC					W15				
		VCC					W17				
		VCC					W19				
		VCC					W21				
		VCC					W23				
		VCC					Y13				
		VCC					Y20				
		VCC					V18				
		VCCIO3A					AD30				
		VCCIO3A					AF27				
		VCCIO3A					AH30				
		VCCIO3A					AJ27				
		VCCIO3A					AK30				
		VCCIO3A					AM27				
		VCCIO3B					AF24				
		VCCIO3B					AJ24				
		VCCIO3B					AM24				
		VCCIO3B					AP24				
		VCCIO3C					AF21				
		VCCIO3C					AJ21				
		VCCIO3C					AM21				
		VCCIO3C					AP21				
		VCCIO3D					AF18				
		VCCIO3D					AJ18				
		VCCIO3D					AM18				
		VCCIO3D					AP18				
		VCCIO4A					AD5				
		VCCIO4A					AF5				
		VCCIO4A					AH5				
		VCCIO4A					AK5				
		VCCIO4B					AF9				
		VCCIO4B					AJ9				
		VCCIO4B					AM9				
		VCCIO4B					AP9				
		VCCIO4C					AF12				
		VCCIO4C					AJ12				
		VCCIO4C					AM12				
		VCCIO4C					AP12				
		VCCIO4D					AF15				
		VCCIO4D					AJ15				
		VCCIO4D					AM15				
		VCCIO4D					AP15				
		VCCIO7A					C5				
		VCCIO7A					F2				
		VCCIO7A					F5				
		VCCIO7A					L7				
		VCCIO7B					A9				
		VCCIO7B					C9				
		VCCIO7B					F9				
		VCCIO7B					J9				
		VCCIO7C					A12				
		VCCIO7C					C12				
		VCCIO7C					F12				
		VCCIO7C					J12				
		VCCIO7D					A15				
		VCCIO7D					C15				
		VCCIO7D					F15				



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F152	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
		VCCIO7D					J15				
		VCCIO8A					C27				
		VCCIO8A					C30				
		VCCIO8A					F27				
		VCCIO8A					F30				
		VCCIO8A					J29				
		VCCIO8A					M25				
		VCCIO8B					A24				
		VCCIO8B					C24				
		VCCIO8B					F24				
		VCCIO8B					J24				
		VCCIO8C					A21				
		VCCIO8C					C21				
		VCCIO8C					F21				
		VCCIO8C					J21				
		VCCIO8D					A18				
		VCCIO8D					C18				
		VCCIO8D					F18				
		VCCIO8D					J18				
		VCCPD3					AB26				
		VCCPD3					AC27				
		VCCPD3					Y21				
		VCCPD3					Y25				
		VCCPD4A					AB6				
		VCCPD4A					AB9				
		VCCPD4BCD					N10				
		VCCPD4BCD					Y14				
		VCCPD4BCD					Y16				
		VCCPD7A					N8				
		VCCPD7A					N9				
		VCCPD7BCD					P14				
		VCCPD7BCD					P16				
		VCCPD7BCD					R11				
		VCCPD8					N26				
		VCCPD8					N27				
		VCCPD8					P20				
		VCCPD8					P22				
		VCCPGM					M0				
		VCCPGM					AC26				
		GND					AA11				
		GND					AA13				
		GND					AA16				
		GND					AA19				
		GND					AA22				
		GND					AA24				
		GND					AD10				
		GND					AD13				
		GND					AD16				
		GND					AD19				
		GND					AD22				
		GND					AD25				
		GND					AD28				
		GND					AD7				
		GND					AG10				
		GND					AG13				
		GND					AG16				
		GND					AG19				
		GND					AG22				
		GND					AG25				
		GND					AG28				
		GND					AG7				
		GND					AK10				
		GND					AK13				
		GND					AK16				
		GND					AK19				
		GND					AK22				
		GND					AK25				
		GND					AK28				
		GND					AK7				
		GND					AN10				
		GND					AN13				
		GND					AN16				
		GND					AN19				
		GND					AN22				
		GND					AN25				
		GND					AN28				
		GND					AN31				
		GND					AN4				
		GND					AN7				
		GND					B1				
		GND					B10				
		GND					B13				
		GND					B16				
		GND					B19				
		GND					B22				
		GND					B25				
		GND					B28				
		GND					B31				
		GND					B4				
		GND					B7				
		GND					D2				
		GND					D4				
		GND					E10				
		GND					E13				
		GND					E16				
		GND					E19				
		GND					E22				
		GND					E25				
		GND					E28				



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
		GND					E31				
		GND					E7				
		GND					H10				
		GND					H13				
		GND					H16				
		GND					H19				
		GND					H22				
		GND					H25				
		GND					H28				
		GND					H7				
		GND					L10				
		GND					L13				
		GND					L16				
		GND					L19				
		GND					L22				
		GND					L25				
		GND					L28				
		GND					L8				
		GND					M6				
		GND					N7				
		GND					P10				
		GND					P13				
		GND					P15				
		GND					P17				
		GND					P19				
		GND					P21				
		GND					P23				
		GND					P25				
		GND					R10				
		GND					R12				
		GND					R16				
		GND					R20				
		GND					R22				
		GND					R24				
		GND					T11				
		GND					T13				
		GND					T15				
		GND					T17				
		GND					T19				
		GND					T21				
		GND					T23				
		GND					T25				
		GND					U10				
		GND					U14				
		GND					U16				
		GND					U24				
		GND					V11				
		GND					V13				
		GND					V15				
		GND					V17				
		GND					V19				
		GND					V21				
		GND					V23				
		GND					V25				
		GND					W10				
		GND					W12				
		GND					W14				
		GND					W16				
		GND					W18				
		GND					W20				
		GND					W22				
		GND					W24				
		GND					U18				

Notes:

- (1) For more information about pin definitions and pin connection guidelines, refer to the [Arria V Device Family Pin Connection Guidelines](#).
- (2) GXB_REFCLK pin is not supported in current Quartus II version, but will be supported in future Quartus II release version.
- (3) RESET pin is only applicable for DDR3 device.



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1517	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
		DNU					A38				
		DNU					B38				
		RREF_TL					B39				
		GND					AA32				
		GND					AA31				
		DNU					R36				
		DNU					R37				
		GND					T39				
		GND					T38				
		DNU					U36				
		DNU					U37				
		GND					V39				
		GND					Y38				
		DNU					W36				
		DNU					W37				
		GND					Y39				
		GND					Y38				
		GND					AA36				
		GXB TX L8n					AA37				
		GXB TX L8p					AB39				
		GXB RX L8p,GXB REFCLK L8p					AB38				
		GXB RX L8n,GXB REFCLK L8n					AC36				
		GXB TX L7n					AC37				
		GXB TX L7p					AD39				
		GXB RX L7p,GXB REFCLK L7p					AD38				
		GXB RX L7n,GXB REFCLK L7n					AE36				
		GXB TX L6n					AE37				
		GXB TX L6p					AF39				
		GXB RX L6p,GXB REFCLK L6p					AF38				
		GXB RX L6n,GXB REFCLK L6n					AG36				
		REFCLK2Ln					AG37				
		REFCLK2Lp					AH39				
		REFCLK1Ln					AH38				
		REFCLK1Lp					AJ36				
		GXB TX L5n					AJ37				
		GXB TX L5p					AK39				
		GXB RX L5p,GXB REFCLK L5p					AK38				
		GXB RX L5n,GXB REFCLK L5n					AL36				
		GXB TX L4n					AL37				
		GXB TX L4p					AM39				
		GXB RX L4p,GXB REFCLK L4p					AM38				
		GXB RX L4n,GXB REFCLK L4n					AN36				
		GXB TX L3n					AN37				
		GXB TX L3p					AP39				
		GXB RX L3p,GXB REFCLK L3p					AP38				
		GXB RX L3n,GXB REFCLK L3n					AR36				
		GXB TX L2n					AR37				
		GXB TX L2p					AT39				
		GXB RX L2p,GXB REFCLK L2p					AT38				
		GXB RX L2n,GXB REFCLK L2n					AU36				
		GXB TX L1n					AU37				
		GXB TX L1p					AW37				
		GXB RX L1p,GXB REFCLK L1p					AW36				
		GXB RX L1n,GXB REFCLK L1n					AG33				
		GXB TX L0n					AG32				
		GXB TX L0p					AH31				
		GXB RX L0p,GXB REFCLK L0p					AT34				
		GXB RX L0n,GXB REFCLK L0n					AM35				
		REFCLK0Ln					AV34				
		REFCLK0Lp					AT33				
		DNU					AU34				
		TD0		TD0			AR34				
		TMS		TMS			AU34				
		TCK		TCK			AR34				
		TDI		TDI			AU34				
		DCLK		DCLK			AR34				
		HCSO		DATA4			AR34				
		AS_DATA3		DATA3			AU34				
		AS_DATA2		DATA2			AR33				
		AS_DATA1		DATA1			AU33				
		AS_DATA0,ASDO		DATA0			AU33				
	VREFB3AN0	IO	RZQ_0				DIFFIO TX B1n	DIFFOUT B1n			
	VREFB3AN0	IO					DIFFIO TX B1p	DIFFOUT B1p		DQ1B	
	VREFB3AN0	IO	CLK0n				DIFFIO RX B2n	DIFFOUT B2n		DQ1B	
	VREFB3AN0	IO	CLK0p				DIFFIO RX B2p	DIFFOUT B2p		DQ1B	
	VREFB3AN0	IO					DIFFIO TX B3n	DIFFOUT B3n			
	VREFB3AN0	IO					DIFFIO TX B3p	DIFFOUT B3p		DQ1B	
	VREFB3AN0	IO	CLK1n				DIFFIO RX B4n	DIFFOUT B4n		DQS1B/OK1B	
	VREFB3AN0	IO	CLK1p				DIFFIO RX B4p	DIFFOUT B4p		DQS1B/OK1B	
	VREFB3AN0	IO	FPLL_BL_CLKOUT1,FPLL_BL_CLKOUTn				DIFFIO TX B5n	DIFFOUT B5n			
	VREFB3AN0	IO	FPLL_BL_CLKOUT0,FPLL_BL_CLKOUTp,FPLL_BL_FB0				DIFFIO TX B5p	DIFFOUT B5p		DQ1B	
	VREFB3AN0	IO	FPLL_BL_CLKOUT3,FPLL_BL_FBn				DIFFIO RX B6n	DIFFOUT B6n		DQ1B	
	VREFB3AN0	IO	FPLL_BL_CLKOUT2,FPLL_BL_FBp,FPLL_BL_FB1				DIFFIO RX B6p	DIFFOUT B6p		DQ1B	
	VREFB3AN0	IO	VREFB3AN0								
	VREFB3AN0	IO					AK31			DQ1B	
	VREFB3AN0	IO	CLK2n				DIFFIO RX B7n	DIFFOUT B7n		DQ1B	
	VREFB3AN0	IO	CLK2p				DIFFIO RX B7p	DIFFOUT B7p		DQ1B	
	VREFB3AN0	IO					DIFFIO TX B8n	DIFFOUT B8n			
	VREFB3AN0	IO					DIFFIO TX B8p	DIFFOUT B8p		DQ2B	DQ1B
	VREFB3AN0	IO	CLK3n				DIFFIO RX B9n	DIFFOUT B9n		DQ2B	DQ1B
	VREFB3AN0	IO	CLK3p				DIFFIO RX B9p	DIFFOUT B9p		DQ2B	DQ1B
	VREFB3AN0	IO					DIFFIO TX B10n	DIFFOUT B10n			
	VREFB3AN0	IO					DIFFIO TX B10p	DIFFOUT B10p		DQ2B	DQ1B
	VREFB3AN0	IO					DIFFIO RX B11n	DIFFOUT B11n		DQS2B/OK2B	DQ1B
	VREFB3AN0	IO					DIFFIO RX B11p	DIFFOUT B11p		DQS2B/OK2B	DQ1B
	VREFB3AN0	IO					DIFFIO TX B12n	DIFFOUT B12n			
	VREFB3AN0	IO					DIFFIO TX B12p	DIFFOUT B12p		DQ2B	DQ1B



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Output Channel	Emulated LVDS Output Channel	F1517	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
3A	VREFB3A0	IO			DIFFIO RX B13n	DIFFOUT B13n	AR31	DQ2B			DQ1B
3A	VREFB3A0	IO			DIFFIO RX B13p	DIFFOUT B13p	AT31	DQ2B			DQ1B
3A	VREFB3A0	IO			DIFFIO TX B14n	DIFFOUT B14n	AD29				
3A	VREFB3A0	IO			DIFFIO TX B14p	DIFFOUT B14p	AE29	DQ2B			DQ1B
3A	VREFB3A0	IO			DIFFIO RX B15n	DIFFOUT B15n	AG30	DQ2B			DQ1B
3A	VREFB3A0	IO			DIFFIO RX B15p	DIFFOUT B15p	AH30	DQ2B			DQ1B
3A	VREFB3A0	IO			DIFFIO TX B16n	DIFFOUT B16n	AU31				
3A	VREFB3A0	IO			DIFFIO TX B16p	DIFFOUT B16p	AV31	DQ3B			DQ1B
3A	VREFB3A0	IO			DIFFIO RX B17n	DIFFOUT B17n	AW30	DQ3B			DQ1B
3A	VREFB3A0	IO			DIFFIO RX B17p	DIFFOUT B17p	AW31	DQ3B			DQ1B
3A	VREFB3A0	IO			DIFFIO TX B18n	DIFFOUT B18n	AK30				
3A	VREFB3A0	IO			DIFFIO TX B18p	DIFFOUT B18p	AL30	DQ3B			DQ1B
3A	VREFB3A0	IO			DIFFIO RX B19n	DIFFOUT B19n	AR30	DQS3B/CQ3B			DQS1B/OK1B
3A	VREFB3A0	IO			DIFFIO RX B19p	DIFFOUT B19p	AT30	DQS3B/CQ3B/CQn3B/QKn3B			DQS1B/CQ1B/CQn1B/QKn1B
3A	VREFB3A0	IO			DIFFIO TX B20n	DIFFOUT B20n	AU30				
3A	VREFB3A0	IO			DIFFIO TX B20p	DIFFOUT B20p	AV30	DQ3B			DQ1B
3A	VREFB3A0	IO			DIFFIO RX B21n	DIFFOUT B21n	AT29	DQ3B			DQ1B
3A	VREFB3A0	IO			DIFFIO RX B21p	DIFFOUT B21p	AU29	DQ3B			DQ1B
3A	VREFB3A0	IO			DIFFIO TX B22n	DIFFOUT B22n	AK30				
3A	VREFB3A0	IO			DIFFIO TX B22p	DIFFOUT B22p	AP30	DQ3B			DQ1B
3A	VREFB3A0	IO			DIFFIO RX B23n	DIFFOUT B23n	AN29	DQ3B			DQ1B
3A	VREFB3A0	IO			DIFFIO RX B23p	DIFFOUT B23p	AP29	DQ3B			DQ1B
3B	VREFB3B0	IO			DIFFIO TX B24n	DIFFOUT B24n	AB29				
3B	VREFB3B0	IO			DIFFIO TX B24p	DIFFOUT B24p	AC29	DQ4B			DQ1B
3B	VREFB3B0	IO			DIFFIO TX B25n	DIFFOUT B25n	AF28	DQ4B			DQ1B
3B	VREFB3B0	IO			DIFFIO RX B25p	DIFFOUT B25p	AG28	DQ4B			DQ1B
3B	VREFB3B0	IO			DIFFIO TX B26n	DIFFOUT B26n	AK29				
3B	VREFB3B0	IO			DIFFIO TX B26p	DIFFOUT B26p	AL29	DQ4B			DQ1B
3B	VREFB3B0	IO			DIFFIO RX B27n	DIFFOUT B27n	AH28	DQS4B/OK4B			DQ1B
3B	VREFB3B0	IO			DIFFIO RX B27p	DIFFOUT B27p	AJ28	DQS4B/CQ4B/CQn4B/QKn4B			DQ1B
3B	VREFB3B0	IO			DIFFIO TX B28n	DIFFOUT B28n	AD28				
3B	VREFB3B0	IO			DIFFIO TX B28p	DIFFOUT B28p	AE28	DQ4B			DQ1B
3B	VREFB3B0	IO			DIFFIO RX B29n	DIFFOUT B29n	AB27	DQ4B			DQ1B
3B	VREFB3B0	IO			DIFFIO RX B29p	DIFFOUT B29p	AB28	DQ4B			DQ1B
3B	VREFB3B0	IO	VREFB3B0				AL28				
3B	VREFB3B0	IO					AM28	DQ4B			DQ1B
3B	VREFB3B0	IO			DIFFIO RX B30n	DIFFOUT B30n	AC27	DQ4B			DQ1B
3B	VREFB3B0	IO			DIFFIO RX B30p	DIFFOUT B30p	AD27	DQ4B			DQ1B
3B	VREFB3B0	IO			DIFFIO TX B31n	DIFFOUT B31n	AP28				
3B	VREFB3B0	IO			DIFFIO TX B31p	DIFFOUT B31p	AR28	DQ5B			DQ1B
3B	VREFB3B0	IO			DIFFIO RX B32n	DIFFOUT B32n	AU28	DQ5B			DQ1B
3B	VREFB3B0	IO			DIFFIO RX B32p	DIFFOUT B32p	AV28	DQ5B			DQ1B
3B	VREFB3B0	IO			DIFFIO TX B33n	DIFFOUT B33n	AJ27				
3B	VREFB3B0	IO			DIFFIO TX B33p	DIFFOUT B33p	AK27	DQ5B			DQ1B
3B	VREFB3B0	IO			DIFFIO RX B34n	DIFFOUT B34n	AW29	DQS5B/OK5B			DQ1B
3B	VREFB3B0	IO			DIFFIO RX B34p	DIFFOUT B34p	AW28	DQS5B/CQ5B/CQn5B/QKn5B			DQ1B
3B	VREFB3B0	IO			DIFFIO TX B35n	DIFFOUT B35n	AP27				
3B	VREFB3B0	IO			DIFFIO TX B35p	DIFFOUT B35p	AR27	DQ5B			DQ1B
3B	VREFB3B0	IO			DIFFIO RX B36n	DIFFOUT B36n	AT27	DQ5B			DQ1B
3B	VREFB3B0	IO			DIFFIO RX B36p	DIFFOUT B36p	AU27	DQ5B			DQ1B
3B	VREFB3B0	IO			DIFFIO TX B37n	DIFFOUT B37n	AM27				
3B	VREFB3B0	IO			DIFFIO TX B37p	DIFFOUT B37p	AN27	DQ5B			DQ1B
3B	VREFB3B0	IO			DIFFIO RX B38n	DIFFOUT B38n	AU27	DQ5B			DQ1B
3B	VREFB3B0	IO			DIFFIO RX B38p	DIFFOUT B38p	AV27	DQ5B			DQ1B
3C	VREFB3C0	IO			DIFFIO TX B39n	DIFFOUT B39n	AG27				
3C	VREFB3C0	IO			DIFFIO TX B39p	DIFFOUT B39p	AH27	DQ6B			DQ1B
3C	VREFB3C0	IO			DIFFIO RX B40n	DIFFOUT B40n	AB25	DQ6B			DQ1B
3C	VREFB3C0	IO			DIFFIO RX B40p	DIFFOUT B40p	AC25	DQ6B			DQ1B
3C	VREFB3C0	IO			DIFFIO TX B41n	DIFFOUT B41n	AE27				
3C	VREFB3C0	IO			DIFFIO TX B41p	DIFFOUT B41p	AF27	DQ6B			DQ1B
3C	VREFB3C0	IO			DIFFIO RX B42n	DIFFOUT B42n	AE25	DQS6B/OK6B			DQ1B
3C	VREFB3C0	IO			DIFFIO RX B42p	DIFFOUT B42p	AF25	DQS6B/CQ6B/CQn6B/QKn6B			DQ1B
3C	VREFB3C0	IO			DIFFIO TX B43n	DIFFOUT B43n	AC24				
3C	VREFB3C0	IO			DIFFIO TX B43p	DIFFOUT B43p	AD25	DQ6B			DQ1B
3C	VREFB3C0	IO			DIFFIO RX B44n	DIFFOUT B44n	AC26	DQ6B			DQ1B
3C	VREFB3C0	IO			DIFFIO RX B44p	DIFFOUT B44p	AH26	DQ6B			DQ1B
3C	VREFB3C0	IO			DIFFIO TX B45n	DIFFOUT B45n	AD26				
3C	VREFB3C0	IO			DIFFIO TX B45p	DIFFOUT B45p	AE26	DQ6B			DQ1B
3C	VREFB3C0	IO			DIFFIO RX B46n	DIFFOUT B46n	AG25	DQ6B			DQ1B
3C	VREFB3C0	IO			DIFFIO RX B46p	DIFFOUT B46p	AH25	DQ6B			DQ1B
3C	VREFB3C0	IO			DIFFIO TX B47n	DIFFOUT B47n	AK26				
3C	VREFB3C0	IO			DIFFIO TX B47p	DIFFOUT B47p	AP26	DQ7B			DQ1B
3C	VREFB3C0	IO			DIFFIO RX B48n	DIFFOUT B48n	AM25	DQ7B			DQ1B
3C	VREFB3C0	IO			DIFFIO RX B48p	DIFFOUT B48p	AN25	DQ7B			DQ1B
3C	VREFB3C0	IO			DIFFIO TX B49n	DIFFOUT B49n	AJ25				
3C	VREFB3C0	IO			DIFFIO TX B49p	DIFFOUT B49p	AK25	DQ7B			DQ1B
3C	VREFB3C0	IO			DIFFIO RX B50n	DIFFOUT B50n	AT26	DQS7B/OK7B			DQ1B
3C	VREFB3C0	IO			DIFFIO RX B50p	DIFFOUT B50p	AU26	DQS7B/CQ7B/CQn7B/QKn7B			DQ1B
3C	VREFB3C0	IO			DIFFIO TX B51n	DIFFOUT B51n	AR25				
3C	VREFB3C0	IO			DIFFIO TX B51p	DIFFOUT B51p	AT25	DQ7B			DQ1B
3C	VREFB3C0	IO			DIFFIO RX B52n	DIFFOUT B52n	AW25	DQ7B			DQ1B
3C	VREFB3C0	IO			DIFFIO RX B52p	DIFFOUT B52p	AV26	DQ7B			DQ1B
3C	VREFB3C0	IO	VREFB3C0				AK26				
3C	VREFB3C0	IO					AL26	DQ7B			DQ1B
3C	VREFB3C0	IO			DIFFIO RX B53n	DIFFOUT B53n	AV25	DQ7B			DQ1B
3C	VREFB3C0	IO			DIFFIO RX B53p	DIFFOUT B53p	AV24	DQ7B			DQ1B
3C	VREFB3C0	IO			DIFFIO TX B54n	DIFFOUT B54n	AD23				
3C	VREFB3C0	IO			DIFFIO TX B54p	DIFFOUT B54p	AD24	DQ8B			DQ2B
3C	VREFB3C0	IO			DIFFIO RX B55n	DIFFOUT B55n	AT24	DQ8B			DQ2B
3C	VREFB3C0	IO			DIFFIO RX B55p	DIFFOUT B55p	AU24	DQ8B			DQ2B
3C	VREFB3C0	IO			DIFFIO TX B56n	DIFFOUT B56n	AK24				
3C	VREFB3C0	IO			DIFFIO TX B56p	DIFFOUT B56p	AL24	DQ8B			DQ2B
3C	VREFB3C0	IO			DIFFIO RX B57n	DIFFOUT B57n	AE24	DQS8B/OK8B			DQ2B
3C	VREFB3C0	IO			DIFFIO RX B57p	DIFFOUT B57p	AF24	DQS8B/CQ8B/CQn8B/QKn8B			DQ2B
3C	VREFB3C0	IO			DIFFIO TX B58n	DIFFOUT B58n	AG24				
3C	VREFB3C0	IO			DIFFIO TX B58p	DIFFOUT B58p	AH24	DQ8B			DQ2B



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1517	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
3C	VREFB3C0	IO			DIFFIO RX B59n	DIFFOUT B59n	AW23	DQ8B		DQ4B	DQ2B
3C	VREFB3C0	IO			DIFFIO RX B59p	DIFFOUT B59p	AW24	DQ8B		DQ4B	DQ2B
3C	VREFB3C0	IO			DIFFIO TX B60n	DIFFOUT B60n	AN24	DQ8B			
3C	VREFB3C0	IO			DIFFIO TX B60p	DIFFOUT B60p	AP24	DQ8B		DQ4B	DQ2B
3C	VREFB3C0	IO			DIFFIO RX B61n	DIFFOUT B61n	AT23	DQ8B		DQ4B	DQ2B
3C	VREFB3C0	IO			DIFFIO RX B61p	DIFFOUT B61p	AU23	DQ8B		DQ4B	DQ2B
3D	VREFB3D0	IO			DIFFIO TX B62n	DIFFOUT B62n	AN23				
3D	VREFB3D0	IO			DIFFIO TX B62p	DIFFOUT B62p	AP23	DQ9B		DQ4B	DQ2B
3D	VREFB3D0	IO			DIFFIO RX B63n	DIFFOUT B63n	AD22	DQ9B		DQ4B	DQ2B
3D	VREFB3D0	IO			DIFFIO RX B63p	DIFFOUT B63p	AE23	DQ9B		DQ4B	DQ2B
3D	VREFB3D0	IO			DIFFIO TX B64n	DIFFOUT B64n	AK23				
3D	VREFB3D0	IO			DIFFIO TX B64p	DIFFOUT B64p	AL23	DQ9B		DQ4B	DQ2B
3D	VREFB3D0	IO			DIFFIO RX B65n	DIFFOUT B65n	AT22	DQS9B/CQ9B/QK9B		DQS4B/QK4B	DQ2B
3D	VREFB3D0	IO			DIFFIO RX B65p	DIFFOUT B65p	AU22	DQS9B/CQ9B/CQn9B/QKn9B		DQS4B/CQ4B/CQn4B/QKn4B	DQ2B
3D	VREFB3D0	IO			DIFFIO TX B66n	DIFFOUT B66n	AV22				
3D	VREFB3D0	IO			DIFFIO TX B66p	DIFFOUT B66p	AW22	DQ9B		DQ4B	DQ2B
3D	VREFB3D0	IO			DIFFIO RX B67n	DIFFOUT B67n	AV21	DQ9B		DQ4B	DQ2B
3D	VREFB3D0	IO			DIFFIO RX B67p	DIFFOUT B67p	AW21	DQ9B		DQ4B	DQ2B
3D	VREFB3D0	IO			DIFFIO TX B68n	DIFFOUT B68n	AC23				
3D	VREFB3D0	IO			DIFFIO TX B68p	DIFFOUT B68p	AH23	DQ9B		DQ4B	DQ2B
3D	VREFB3D0	IO			DIFFIO RX B69n	DIFFOUT B69n	AE22	DQ9B		DQ4B	DQ2B
3D	VREFB3D0	IO			DIFFIO RX B69p	DIFFOUT B69p	AF22	DQ9B		DQ4B	DQ2B
3D	VREFB3D0	IO			DIFFIO TX B70n	DIFFOUT B70n	AN22				
3D	VREFB3D0	IO			DIFFIO TX B70p	DIFFOUT B70p	AP22	DQ10B		DQ5B	DQ2B
3D	VREFB3D0	IO			DIFFIO RX B71n	DIFFOUT B71n	AW19	DQ10B		DQ5B	DQ2B
3D	VREFB3D0	IO			DIFFIO RX B71p	DIFFOUT B71p	AW20	DQ10B		DQ5B	DQ2B
3D	VREFB3D0	IO			DIFFIO TX B72n	DIFFOUT B72n	AK22				
3D	VREFB3D0	IO			DIFFIO TX B72p	DIFFOUT B72p	AL22	DQ10B		DQ5B	DQ2B
3D	VREFB3D0	IO			DIFFIO RX B73n	DIFFOUT B73n	AR21	DQS10B/QK10B		DQ5B	DQS2B/QK2B
3D	VREFB3D0	IO			DIFFIO RX B73p	DIFFOUT B73p	AT21	DQS10B/CQ10B/CQn10B/QKn10B		DQ5B	DQS2B/CQ2B/CQn2B/QKn2B
3D	VREFB3D0	IO			DIFFIO TX B74n	DIFFOUT B74n	AC22				
3D	VREFB3D0	IO			DIFFIO TX B74p	DIFFOUT B74p	AH22	DQ10B		DQ5B	DQ2B
3D	VREFB3D0	IO			DIFFIO RX B75n	DIFFOUT B75n	AT20	DQ10B		DQ5B	DQ2B
3D	VREFB3D0	IO			DIFFIO RX B75p	DIFFOUT B75p	AU20	DQ10B		DQ5B	DQ2B
3D	VREFB3D0	IO		VREFB3D0			AJ21				
3D	VREFB3D0	IO					AK21	DQ10B		DQ5B	DQ2B
3D	VREFB3D0	IO	CLK4n		DIFFIO RX B76n	DIFFOUT B76n	AJ19	DQ10B		DQ5B	DQ2B
3D	VREFB3D0	IO	CLK4p		DIFFIO RX B76p	DIFFOUT B76p	AV19	DQ10B		DQ5B	DQ2B
3D	VREFB3D0	IO			DIFFIO TX B77n	DIFFOUT B77n	AM21				
3D	VREFB3D0	IO			DIFFIO TX B77p	DIFFOUT B77p	AN21	DQ11B		DQ5B	DQ2B
3D	VREFB3D0	IO	CLK5n		DIFFIO RX B78n	DIFFOUT B78n	AE21	DQ11B		DQ5B	DQ2B
3D	VREFB3D0	IO	CLK5p		DIFFIO RX B78p	DIFFOUT B78p	AF21	DQ11B		DQ5B	DQ2B
3D	VREFB3D0	IO	FPLL_BC_CLKOUT1.FPLL_BC_CLKOUTn		DIFFIO TX B79n	DIFFOUT B79n	AD21				
3D	VREFB3D0	IO	FPLL_BC_CLKOUT0.FPLL_BC_CLKOUT.FPLL_BC_FB0		DIFFIO TX B79p	DIFFOUT B79p	AC22	DQ11B		DQ5B	DQ2B
3D	VREFB3D0	IO	FPLL_BC_CLKOUT3.FPLL_BC_FBn		DIFFIO RX B80n	DIFFOUT B80n	AG21	DQS11B/QK11B		DQ5B	DQ2B
3D	VREFB3D0	IO	FPLL_BC_CLKOUT2.FPLL_BC_FBp.FPLL_BC_FB1		DIFFIO RX B80p	DIFFOUT B80p	AH21	DQS11B/CQ11B/CQn11B/QKn11B		DQ5B	DQ2B
3D	VREFB3D0	IO			DIFFIO TX B81n	DIFFOUT B81n	AN20				
3D	VREFB3D0	IO			DIFFIO TX B81p	DIFFOUT B81p	AP20	DQ11B		DQ5B	DQ2B
3D	VREFB3D0	IO	CLK6n		DIFFIO RX B82n	DIFFOUT B82n	AC21	DQ11B		DQ5B	DQ2B
3D	VREFB3D0	IO	CLK6p		DIFFIO RX B82p	DIFFOUT B82p	AD20	DQ11B		DQ5B	DQ2B
3D	VREFB3D0	IO			DIFFIO TX B83n	DIFFOUT B83n	AG20				
3D	VREFB3D0	IO			DIFFIO TX B83p	DIFFOUT B83p	AK20	DQ11B		DQ5B	DQ2B
3D	VREFB3D0	IO	CLK7n		DIFFIO RX B84n	DIFFOUT B84n	AK20	DQ11B		DQ5B	DQ2B
3D	VREFB3D0	IO	CLK7p		DIFFIO RX B84p	DIFFOUT B84p	AL20	DQ11B		DQ5B	DQ2B
		VCCD_FPLL					AB20				
		VCCA_FPLL					AB21				
		DNU					AE20				
4D	VREFB4D0	IO			DIFFIO TX B85n	DIFFOUT B85n	AV18				
4D	VREFB4D0	IO			DIFFIO TX B85p	DIFFOUT B85p	AW18	DQ12B			
4D	VREFB4D0	IO			DIFFIO RX B86n	DIFFOUT B86n	AG19	DQ12B			
4D	VREFB4D0	IO			DIFFIO RX B86p	DIFFOUT B86p	AH19	DQ12B			
4D	VREFB4D0	IO			DIFFIO TX B87n	DIFFOUT B87n	AN19				
4D	VREFB4D0	IO			DIFFIO TX B87p	DIFFOUT B87p	AP19	DQ12B			
4D	VREFB4D0	IO			DIFFIO RX B88n	DIFFOUT B88n	AK19	DQS12B/QK12B			
4D	VREFB4D0	IO			DIFFIO RX B88p	DIFFOUT B88p	AL19	DQS12B/CQ12B/CQn12B/QKn12B			
4D	VREFB4D0	IO			DIFFIO TX B89n	DIFFOUT B89n	AH18				
4D	VREFB4D0	IO			DIFFIO TX B89p	DIFFOUT B89p	AJ18	DQ12B			
4D	VREFB4D0	IO			DIFFIO RX B90n	DIFFOUT B90n	AU18	DQ12B			
4D	VREFB4D0	IO			DIFFIO RX B90p	DIFFOUT B90p	AT19	DQ12B			
4D	VREFB4D0	IO			DIFFIO TX B91n	DIFFOUT B91n	AE19				
4D	VREFB4D0	IO			DIFFIO TX B91p	DIFFOUT B91p	AF19	DQ12B			
4D	VREFB4D0	IO			DIFFIO RX B92n	DIFFOUT B92n	AW17	DQ12B			
4D	VREFB4D0	IO			DIFFIO RX B92p	DIFFOUT B92p	AW16	DQ12B			
4D	VREFB4D0	IO			DIFFIO TX B93n	DIFFOUT B93n	AK17				CS#_4D_1
4D	VREFB4D0	IO			DIFFIO TX B93p	DIFFOUT B93p	AL17	DQ13B		DQ6B	CS#_4D_0
4D	VREFB4D0	IO			DIFFIO RX B94n	DIFFOUT B94n	AT17	DQ13B		DQ6B	
4D	VREFB4D0	IO			DIFFIO RX B94p	DIFFOUT B94p	AU17	DQ13B		DQ6B	
4D	VREFB4D0	IO			DIFFIO TX B95n	DIFFOUT B95n	AC19				A_4D_15
4D	VREFB4D0	IO			DIFFIO TX B95p	DIFFOUT B95p	AD19	DQ13B		DQ6B	ODT_4D_1
4D	VREFB4D0	IO			DIFFIO RX B96n	DIFFOUT B96n	AP18	DQS13B/QK13B		DQ6B	WE#_4D
4D	VREFB4D0	IO			DIFFIO RX B96p	DIFFOUT B96p	AR18	DQS13B/CQ13B/CQn13B/QKn13B		DQ6B	CAS#_4D
4D	VREFB4D0	IO			DIFFIO TX B97n	DIFFOUT B97n	AD17				RA#_4D
4D	VREFB4D0	IO			DIFFIO TX B97p	DIFFOUT B97p	AC18	DQ13B		DQ6B	BA_4D_2
4D	VREFB4D0	IO			DIFFIO RX B98n	DIFFOUT B98n	AD18	DQ13B		DQ6B	SA_4D_1
4D	VREFB4D0	IO			DIFFIO RX B98p	DIFFOUT B98p	AE18	DQ13B		DQ6B	SA_4D_0
4D	VREFB4D0	IO		VREFB4D0			AF18				
4D	VREFB4D0	IO					AG18	DQ13B		DQ6B	A_4D_14
4D	VREFB4D0	IO			DIFFIO RX B99n	DIFFOUT B99n	AL18	DQ13B		DQ6B	A_4D_13
4D	VREFB4D0	IO			DIFFIO RX B99p	DIFFOUT B99p	AM18	DQ13B		DQ6B	A_4D_12
4D	VREFB4D0	IO			DIFFIO TX B100n	DIFFOUT B100n	AG17				A_4D_11
4D	VREFB4D0	IO			DIFFIO TX B100p	DIFFOUT B100p	AH17	DQ14B		DQ6B	A_4D_10
4D	VREFB4D0	IO			DIFFIO RX B101n	DIFFOUT B101n	AN17	DQ14B		DQ6B	A_4D_9
4D	VREFB4D0	IO			DIFFIO RX B101p	DIFFOUT B101p	AP17	DQ14B		DQ6B	A_4D_8
4D	VREFB4D0	IO			DIFFIO TX B102n	DIFFOUT B102n	AF16				A_4D_7
4D	VREFB4D0	IO			DIFFIO TX B102p	DIFFOUT B102p	AT16	DQ14B		DQ6B	A_4D_6
4D	VREFB4D0	IO			DIFFIO RX B103n	DIFFOUT B103n	AU16	DQS14B/QK14B		DQ6B	A_4D_5



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1517	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
4D	VREFB4DN0	IO			DIFFIO RX B103p	DIFFOUT B103p	AV16	DQS14B/CQ14B/CQn14B/QKn14B	DQS6B/CQ6B/CQn6B/QKn6B		A_4D_4
4D	VREFB4DN0	IO			DIFFIO TX B104n	DIFFOUT B104n	AJ16				A_4D_3
4D	VREFB4DN0	IO			DIFFIO TX B104p	DIFFOUT B104p	AK16	DQ14B	DQ6B		A_4D_2
4D	VREFB4DN0	IO			DIFFIO RX B105n	DIFFOUT B105n	AN16	DQ14B	DQ6B		A_4D_1
4D	VREFB4DN0	IO			DIFFIO RX B105p	DIFFOUT B105p	AP16	DQ14B	DQ6B		A_4D_0
4D	VREFB4DN0	IO			DIFFIO TX B106n	DIFFOUT B106n	AL16				CKE_4D_1
4D	VREFB4DN0	IO			DIFFIO TX B106p	DIFFOUT B106p	AM16	DQ14B	DQ6B		CKE_4D_0
4D	VREFB4DN0	IO			DIFFIO RX B107n	DIFFOUT B107n	AE17	DQ14B	DQ6B		CK#_4D
4D	VREFB4DN0	IO			DIFFIO RX B107p	DIFFOUT B107p	AF16	DQ14B	DQ6B		CK_4D
4C	VREFB4CN0	IO			DIFFIO TX B108n	DIFFOUT B108n	AN15				RESET#_4D
4C	VREFB4CN0	IO			DIFFIO TX B108p	DIFFOUT B108p	AP15	DQ15B	DQ7B	DQ3B	DQ1_4C_8
4C	VREFB4CN0	IO			DIFFIO RX B109n	DIFFOUT B109n	AW14	DQ15B	DQ7B	DQ3B	DQ1_4C_7
4C	VREFB4CN0	IO			DIFFIO RX B109p	DIFFOUT B109p	AW15	DQ15B	DQ7B	DQ3B	DQ1_4C_6
4C	VREFB4CN0	IO			DIFFIO TX B110n	DIFFOUT B110n	AC16				
4C	VREFB4CN0	IO			DIFFIO TX B110p	DIFFOUT B110p	AD16	DQ15B	DQ7B	DQ3B	DM1_4C
4C	VREFB4CN0	IO			DIFFIO RX B111n	DIFFOUT B111n	AG16	DQS15B/QK15B	DQ7B	DQ3B	DQS#1_4C
4C	VREFB4CN0	IO			DIFFIO RX B111p	DIFFOUT B111p	AH16	DQS15B/CQ15B/CQn15B/QKn15B	DQ7B	DQ3B	DQS1_4C
4C	VREFB4CN0	IO			DIFFIO TX B112n	DIFFOUT B112n	AK15				
4C	VREFB4CN0	IO			DIFFIO TX B112p	DIFFOUT B112p	AL15	DQ15B	DQ7B	DQ3B	DQ1_4C_5
4C	VREFB4CN0	IO			DIFFIO RX B113n	DIFFOUT B113n	AV13	DQ15B	DQ7B	DQ3B	DQ1_4C_4
4C	VREFB4CN0	IO			DIFFIO RX B113p	DIFFOUT B113p	AW13	DQ15B	DQ7B	DQ3B	DQ1_4C_3
4C	VREFB4CN0	IO	VREFB4CN0				AG15				
4C	VREFB4CN0	IO					AH15	DQ15B	DQ7B	DQ3B	DQ1_4C_2
4C	VREFB4CN0	IO			DIFFIO RX B114n	DIFFOUT B114n	AT15	DQ15B	DQ7B	DQ3B	DQ1_4C_1
4C	VREFB4CN0	IO			DIFFIO RX B114p	DIFFOUT B114p	AU15	DQ15B	DQ7B	DQ3B	DQ1_4C_0
4C	VREFB4CN0	IO			DIFFIO TX B115n	DIFFOUT B115n	AC15				
4C	VREFB4CN0	IO			DIFFIO TX B115p	DIFFOUT B115p	AD14	DQ16B	DQ7B	DQ3B	DQ2_4C_8
4C	VREFB4CN0	IO			DIFFIO RX B116n	DIFFOUT B116n	AT14	DQ16B	DQ7B	DQ3B	DQ2_4C_7
4C	VREFB4CN0	IO			DIFFIO RX B116p	DIFFOUT B116p	AU14	DQ16B	DQ7B	DQ3B	DQ2_4C_6
4C	VREFB4CN0	IO			DIFFIO TX B117n	DIFFOUT B117n	AT13	DQ16B	DQ7B	DQ3B	DQ2_4C_5
4C	VREFB4CN0	IO			DIFFIO TX B117p	DIFFOUT B117p	AU13	DQ16B	DQ7B	DQ3B	DQ2_4C_4
4C	VREFB4CN0	IO			DIFFIO RX B118n	DIFFOUT B118n	AE16	DQS16B/QK16B	DQS#7B/QK7B	DQ3B	DQS#2_4C
4C	VREFB4CN0	IO			DIFFIO RX B118p	DIFFOUT B118p	AF15	DQS16B/CQ16B/CQn16B/QKn16B	DQS#7B/CQ7B/CQn7B/QKn7B	DQ3B	DQS2_4C
4C	VREFB4CN0	IO			DIFFIO TX B119n	DIFFOUT B119n	AK14				
4C	VREFB4CN0	IO			DIFFIO TX B119p	DIFFOUT B119p	AL14	DQ16B	DQ7B	DQ3B	DQ2_4C_5
4C	VREFB4CN0	IO			DIFFIO RX B120n	DIFFOUT B120n	AW14	DQ16B	DQ7B	DQ3B	DQ2_4C_4
4C	VREFB4CN0	IO			DIFFIO RX B120p	DIFFOUT B120p	AP14	DQ16B	DQ7B	DQ3B	DQ2_4C_3
4C	VREFB4CN0	IO			DIFFIO TX B121n	DIFFOUT B121n	AG14				
4C	VREFB4CN0	IO			DIFFIO TX B121p	DIFFOUT B121p	AH14	DQ16B	DQ7B	DQ3B	DQ2_4C_2
4C	VREFB4CN0	IO			DIFFIO RX B122n	DIFFOUT B122n	AD15	DQ16B	DQ7B	DQ3B	DQ2_4C_1
4C	VREFB4CN0	IO			DIFFIO RX B122p	DIFFOUT B122p	AE15	DQ16B	DQ7B	DQ3B	DQ2_4C_0
4B	VREFB4BN0	IO			DIFFIO TX B123n	DIFFOUT B123n	AR13	DQ17B	DQ8B	DQ3B	DQ3_4B_8
4B	VREFB4BN0	IO			DIFFIO TX B123p	DIFFOUT B123p	AR13	DQ17B	DQ8B	DQ3B	DQ3_4B_7
4B	VREFB4BN0	IO			DIFFIO RX B124n	DIFFOUT B124n	AE14	DQ17B	DQ8B	DQ3B	DQ3_4B_6
4B	VREFB4BN0	IO			DIFFIO RX B124p	DIFFOUT B124p	AE13	DQ17B	DQ8B	DQ3B	DQ3_4B_5
4B	VREFB4BN0	IO			DIFFIO TX B125n	DIFFOUT B125n	AT12				
4B	VREFB4BN0	IO			DIFFIO TX B125p	DIFFOUT B125p	AU12	DQ17B	DQ8B	DQ3B	DM3_4B
4B	VREFB4BN0	IO			DIFFIO RX B126n	DIFFOUT B126n	AW12	DQS17B/QK17B	DQS#3B/QK3B	DQ3B	DQS#3_4B
4B	VREFB4BN0	IO			DIFFIO RX B126p	DIFFOUT B126p	AW12	DQS17B/CQ17B/CQn17B/QKn17B	DQS#3B/CQ3B/CQn3B/QKn3B	DQ3B	DQS3_4B
4B	VREFB4BN0	IO			DIFFIO TX B127n	DIFFOUT B127n	AL13				
4B	VREFB4BN0	IO			DIFFIO TX B127p	DIFFOUT B127p	AM13	DQ17B	DQ8B	DQ3B	DQ3_4B_5
4B	VREFB4BN0	IO			DIFFIO RX B128n	DIFFOUT B128n	AW10	DQ17B	DQ8B	DQ3B	DQ3_4B_4
4B	VREFB4BN0	IO			DIFFIO RX B128p	DIFFOUT B128p	AW11	DQ17B	DQ8B	DQ3B	DQ3_4B_3
4B	VREFB4BN0	IO			DIFFIO TX B129n	DIFFOUT B129n	AM12				
4B	VREFB4BN0	IO			DIFFIO TX B129p	DIFFOUT B129p	AP12	DQ17B	DQ8B	DQ3B	DQ3_4B_2
4B	VREFB4BN0	IO			DIFFIO RX B130n	DIFFOUT B130n	AH13	DQ17B	DQ8B	DQ3B	DQ3_4B_1
4B	VREFB4BN0	IO			DIFFIO RX B130p	DIFFOUT B130p	AJ13	DQ17B	DQ8B	DQ3B	DQ3_4B_0
4B	VREFB4BN0	IO			DIFFIO TX B131n	DIFFOUT B131n	AH12				
4B	VREFB4BN0	IO			DIFFIO TX B131p	DIFFOUT B131p	AJ12	DQ19B	DQ8B	DQ3B	DQ4_4B_8
4B	VREFB4BN0	IO			DIFFIO RX B132n	DIFFOUT B132n	AF13	DQ19B	DQ8B	DQ3B	DQ4_4B_7
4B	VREFB4BN0	IO			DIFFIO RX B132p	DIFFOUT B132p	AG13	DQ19B	DQ8B	DQ3B	DQ4_4B_6
4B	VREFB4BN0	IO			DIFFIO TX B133n	DIFFOUT B133n	AU10				
4B	VREFB4BN0	IO			DIFFIO TX B133p	DIFFOUT B133p	AV10	DQ19B	DQ8B	DQ3B	DM4_4B
4B	VREFB4BN0	IO			DIFFIO RX B134n	DIFFOUT B134n	AT11	DQS18B/QK18B	DQS#4B/QK4B	DQ3B	DQS#4_4B
4B	VREFB4BN0	IO			DIFFIO RX B134p	DIFFOUT B134p	AU11	DQS18B/CQ18B/CQn18B/QKn18B	DQS#4B/CQ4B/CQn4B/QKn4B	DQ3B	DQS4_4B
4B	VREFB4BN0	IO			DIFFIO TX B135n	DIFFOUT B135n	AK12				
4B	VREFB4BN0	IO			DIFFIO TX B135p	DIFFOUT B135p	AL12	DQ19B	DQ8B	DQ3B	DQ4_4B_5
4B	VREFB4BN0	IO			DIFFIO RX B136n	DIFFOUT B136n	AC13	DQ19B	DQ8B	DQ3B	DQ4_4B_4
4B	VREFB4BN0	IO			DIFFIO RX B136p	DIFFOUT B136p	AD13	DQ19B	DQ8B	DQ3B	DQ4_4B_3
4B	VREFB4BN0	IO	VREFB4BN0				AN11				
4B	VREFB4BN0	IO					AP11	DQ19B	DQ8B	DQ3B	DQ4_4B_2
4B	VREFB4BN0	IO			DIFFIO RX B137n	DIFFOUT B137n	AV9	DQ19B	DQ8B	DQ3B	DQ4_4B_1
4B	VREFB4BN0	IO			DIFFIO RX B137p	DIFFOUT B137p	AW9	DQ19B	DQ8B	DQ3B	DQ4_4B_0
4B	VREFB4BN0	IO			DIFFIO TX B138n	DIFFOUT B138n	AC12				
4B	VREFB4BN0	IO			DIFFIO TX B138p	DIFFOUT B138p	AD11	DQ19B	DQ8B	DQ3B	DQ5_4B_8
4B	VREFB4BN0	IO			DIFFIO RX B139n	DIFFOUT B139n	AF12	DQ19B	DQ8B	DQ3B	DQ5_4B_7
4B	VREFB4BN0	IO			DIFFIO RX B139p	DIFFOUT B139p	AG12	DQ19B	DQ8B	DQ3B	DQ5_4B_6
4B	VREFB4BN0	IO			DIFFIO TX B140n	DIFFOUT B140n	AT9				
4B	VREFB4BN0	IO			DIFFIO TX B140p	DIFFOUT B140p	AU9	DQ19B	DQ8B	DQ3B	DM5_4B
4B	VREFB4BN0	IO			DIFFIO RX B141n	DIFFOUT B141n	AG11	DQS19B/QK19B	DQ9B	DQ4B	DQS#5_4B
4B	VREFB4BN0	IO			DIFFIO RX B141p	DIFFOUT B141p	AH11	DQS19B/CQ19B/CQn19B/QKn19B	DQ9B	DQ4B	DQS5_4B
4B	VREFB4BN0	IO			DIFFIO TX B142n	DIFFOUT B142n	AD12				
4B	VREFB4BN0	IO			DIFFIO TX B142p	DIFFOUT B142p	AE12	DQ19B	DQ8B	DQ4B	DQ5_4B_5
4B	VREFB4BN0	IO			DIFFIO RX B143n	DIFFOUT B143n	AP10	DQ19B	DQ8B	DQ4B	DQ5_4B_4
4B	VREFB4BN0	IO			DIFFIO RX B143p	DIFFOUT B143p	AR10	DQ19B	DQ8B	DQ4B	DQ5_4B_3
4B	VREFB4BN0	IO			DIFFIO TX B144n	DIFFOUT B144n	AK11				
4B	VREFB4BN0	IO			DIFFIO TX B144p	DIFFOUT B144p	AL11	DQ19B	DQ8B	DQ4B	DQ5_4B_2
4B	VREFB4BN0	IO			DIFFIO RX B145n	DIFFOUT B145n	AW10	DQ19B	DQ8B	DQ4B	DQ5_4B_1
4B	VREFB4BN0	IO			DIFFIO RX B145p	DIFFOUT B145p	AM10	DQ19B	DQ8B	DQ4B	DQ5_4B_0
4A	VREFB4AN0	IO			DIFFIO TX B146n	DIFFOUT B146n	AL9				
4A	VREFB4AN0	IO			DIFFIO TX B146p	DIFFOUT B146p	AM9	DQ20B	DQ9B	DQ4B	
4A	VREFB4AN0	IO			DIFFIO RX B147n	DIFFOUT B147n	AW7	DQ20B	DQ9B	DQ4B	
4A	VREFB4AN0	IO			DIFFIO RX B147p	DIFFOUT B147p	AW8	DQ20B	DQ9B	DQ4B	
4A	VREFB4AN0	IO			DIFFIO TX B148n	DIFFOUT B148n	AV7				
4A	VREFB4AN0	IO			DIFFIO TX B148p	DIFFOUT B148p	AV6	DQ20B	DQ9B	DQ4B	
4A	VREFB4AN0	IO			DIFFIO RX B149n	DIFFOUT B149n	AW6	DQS20B/QK20B	DQS#9B/QK9B	DQ4B	



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1517	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
4A	VREFB4AN0	IO			DIFFIO RX B149p	DIFFOUT B149p	AW5	DQS20B/CQ20B/CQn20B/QKn20B	DQS9B/CQ9B/CQn9B/QKn9B	DO4B	
4A	VREFB4AN0	IO			DIFFIO TX B150n	DIFFOUT B150n	AK9				
4A	VREFB4AN0	IO			DIFFIO TX B150p	DIFFOUT B150p	AK10	DO20B	DO9B	DO4B	
4A	VREFB4AN0	IO			DIFFIO RX B151n	DIFFOUT B151n	AU7	DO20B	DO9B	DO4B	
4A	VREFB4AN0	IO			DIFFIO RX B151p	DIFFOUT B151p	AU8	DO20B	DO9B	DO4B	
4A	VREFB4AN0	IO			DIFFIO TX B152n	DIFFOUT B152n	AN9				
4A	VREFB4AN0	IO			DIFFIO TX B152p	DIFFOUT B152p	AP9	DO20B	DO9B	DO4B	
4A	VREFB4AN0	IO			DIFFIO RX B153n	DIFFOUT B153n	AT8	DO20B	DO9B	DO4B	
4A	VREFB4AN0	IO			DIFFIO RX B153p	DIFFOUT B153p	AR9	DO20B	DO9B	DO4B	
4A	VREFB4AN0	IO		DATA10	DIFFIO TX B154n	DIFFOUT B154n	AH10				
4A	VREFB4AN0	IO		DATA11	DIFFIO TX B154p	DIFFOUT B154p	AJ10	DO21B	DO10B	DO4B	
4A	VREFB4AN0	IO		DATA5	DIFFIO RX B155n	DIFFOUT B155n	AF10	DO21B	DO10B	DO4B	
4A	VREFB4AN0	IO		DATA6	DIFFIO RX B155p	DIFFOUT B155p	AE11	DO21B	DO10B	DO4B	
4A	VREFB4AN0	IO		DATA12	DIFFIO TX B156n	DIFFOUT B156n	AK6				
4A	VREFB4AN0	IO		DATA13	DIFFIO TX B156p	DIFFOUT B156p	AL6	DO21B	DO10B	DO4B	
4A	VREFB4AN0	IO		DATA7	DIFFIO RX B157n	DIFFOUT B157n	AH6	DQS21B/QK21B	DO10B	DQS4B/QK4B	
4A	VREFB4AN0	IO		DATA8	DIFFIO RX B157p	DIFFOUT B157p	AJ6	DQS21B/CQ21B/CQn21B/QKn21B	DO10B	DQS4B/CQ4B/CQn4B/QKn4B	
4A	VREFB4AN0	IO		DATA14	DIFFIO TX B158n	DIFFOUT B158n	AH9				
4A	VREFB4AN0	IO		DATA15	DIFFIO TX B158p	DIFFOUT B158p	AJ9	DO21B	DO10B	DO4B	
4A	VREFB4AN0	IO		DATA9	DIFFIO RX B159n	DIFFOUT B159n	AM6	DO21B	DO10B	DO4B	
4A	VREFB4AN0	IO		CLKUSR	DIFFIO RX B159p	DIFFOUT B159p	AN6	DO21B	DO10B	DO4B	
4A	VREFB4AN0	IO	VREFB4AN0				AH7				
4A	VREFB4AN0	IO					AH8	DO21B	DO10B	DO4B	
4A	VREFB4AN0	IO		CLK11n	DIFFIO RX B160n	DIFFOUT B160n	AJ7	DO21B	DO10B	DO4B	
4A	VREFB4AN0	IO		CLK11p	DIFFIO RX B160p	DIFFOUT B160p	AK7	DO21B	DO10B	DO4B	
4A	VREFB4AN0	IO		FPLL_BR_CLKOUT1,FPLL_BR_CLKOUTn	DIFFIO TX B161n	DIFFOUT B161n	AL7				
4A	VREFB4AN0	IO		FPLL_BR_CLKOUT0,FPLL_BR_CLKOUTp,FPLL_BR_FB0	DIFFIO TX B161p	DIFFOUT B161p	AM7	DO22B	DO10B	DO4B	
4A	VREFB4AN0	IO		FPLL_BR_CLKOUT3,FPLL_BR_FBp,FPLL_BR_FB1	DIFFIO RX B162n	DIFFOUT B162n	AN8	DO22B	DO10B	DO4B	
4A	VREFB4AN0	IO		FPLL_BR_CLKOUT2,FPLL_BR_FBp,FPLL_BR_FB1	DIFFIO RX B162p	DIFFOUT B162p	AP8	DO22B	DO10B	DO4B	
4A	VREFB4AN0	IO			DIFFIO TX B163n	DIFFOUT B163n	AT6				
4A	VREFB4AN0	IO			DIFFIO TX B163p	DIFFOUT B163p	AU6	DO22B	DO10B	DO4B	
4A	VREFB4AN0	IO		CLK10n	DIFFIO RX B164n	DIFFOUT B164n	AR7	DQS22B/QK22B	DQS10B/QK10B	DO4B	
4A	VREFB4AN0	IO		CLK10p	DIFFIO RX B164p	DIFFOUT B164p	AT7	DQS22B/CQ22B/CQn22B/QKn22B	DQS10B/CQ10B/CQn10B/QKn10B	DO4B	
4A	VREFB4AN0	IO			DIFFIO TX B165n	DIFFOUT B165n	AK8				
4A	VREFB4AN0	IO			DIFFIO TX B165p	DIFFOUT B165p	AL8	DO22B	DO10B	DO4B	
4A	VREFB4AN0	IO		CLK9n	DIFFIO RX B166n	DIFFOUT B166n	AU4	DO22B	DO10B	DO4B	
4A	VREFB4AN0	IO		CLK9p	DIFFIO RX B166p	DIFFOUT B166p	AW4	DO22B	DO10B	DO4B	
4A	VREFB4AN0	IO			DIFFIO TX B167n	DIFFOUT B167n	AN7				
4A	VREFB4AN0	IO		RZQ_1	DIFFIO TX B167p	DIFFOUT B167p	AP7	DO22B	DO10B	DO4B	
4A	VREFB4AN0	IO		CLK8n	DIFFIO RX B168n	DIFFOUT B168n	AP6	DO22B	DO10B	DO4B	
4A	VREFB4AN0	IO		CLK8p	DIFFIO RX B168p	DIFFOUT B168p	AR6	DO22B	DO10B	DO4B	
		RREF_BR					AW2				
		DNU					AV3				
		DNU					AW3				
		REFCLK0Rp					AF8				
GXB_R0		REFCLK0Rn					AF7				
GXB_R0		GXB_RX_R0n,GXB_REFCLK_R0n					AU2				
GXB_R0		GXB_RX_R0p,GXB_REFCLK_R0p					AU1				
GXB_R0		GXB_TX_R0p					AT3				
GXB_R0		GXB_TX_R0n					AT4				
GXB_R0		GXB_RX_R1n,GXB_REFCLK_R1n					AR2				
GXB_R0		GXB_RX_R1p,GXB_REFCLK_R1p					AR1				
GXB_R0		GXB_TX_R1n					AP3				
GXB_R0		GXB_TX_R1p					AP4				
GXB_R0		GXB_RX_R2n,GXB_REFCLK_R2n					AN2				
GXB_R0		GXB_RX_R2p,GXB_REFCLK_R2p					AN1				
GXB_R0		GXB_TX_R2p					AM3				
GXB_R0		GXB_TX_R2n					AM4				
		GND					AL2				
		GND					AL1				
		DNU					AK3				
		DNU					AK4				
		GND					AJ2				
		DNU					AJ1				
		DNU					AH3				
		DNU					AH4				
		GND					AG2				
		GND					AG1				
		DNU					AF3				
		DNU					AF4				
		GND					AD9				
		GND					AD8				
GXB_R1		REFCLK2Rp					AB9				
GXB_R1		REFCLK2Rn					AB8				
GXB_R1		GXB_RX_R6n,GXB_REFCLK_R6n					AE2				
GXB_R1		GXB_RX_R6p,GXB_REFCLK_R6p					AE1				
GXB_R1		GXB_TX_R6p					AD3				
GXB_R1		GXB_TX_R6n					AD4				
GXB_R1		GXB_RX_R7n,GXB_REFCLK_R7n					AC2				
GXB_R1		GXB_RX_R7p,GXB_REFCLK_R7p					AC1				
GXB_R1		GXB_TX_R7p					AB3				
GXB_R1		GXB_TX_R7n					AB4				
GXB_R1		GXB_RX_R8n,GXB_REFCLK_R8n					AA2				
GXB_R1		GXB_RX_R8p,GXB_REFCLK_R8p					AA1				
GXB_R1		GXB_TX_R8p					Y3				
GXB_R1		GXB_TX_R8n					Y4				
GXB_R1		GXB_RX_R9n,GXB_REFCLK_R9n					W2				
GXB_R1		GXB_RX_R9p,GXB_REFCLK_R9p					W1				
GXB_R1		GXB_TX_R9p					V3				
GXB_R1		GXB_TX_R9n					V4				
GXB_R1		GXB_RX_R10n,GXB_REFCLK_R10n					U2				
GXB_R1		GXB_RX_R10p,GXB_REFCLK_R10p					U1				
GXB_R1		GXB_TX_R10p					T3				
GXB_R1		GXB_TX_R10n					T4				
GXB_R1		GXB_RX_R11n,GXB_REFCLK_R11n					R2				
GXB_R1		GXB_RX_R11p,GXB_REFCLK_R11p					R1				



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1517	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
GXB_R1		GXB_TX_R11p					P3				
GXB_R1		GXB_TX_R11n					P4				
GXB_R1		REFCLK3Rp					Y9				
GXB_R1		REFCLK3Rn					Y8				
		DNU					C5				
7A		GND					N8				
7A	VREFB7A0	IO	CLK12p		DIFFIO_RX_T1p	DIFFOUT_T1p	C8	DQ1T		DQ1T	
7A	VREFB7A0	IO	CLK12n		DIFFIO_RX_T1n	DIFFOUT_T1n	D8	DQ1T		DQ1T	
7A	VREFB7A0	IO	RZ0_5		DIFFIO_TX_T2p	DIFFOUT_T2p	F6	DQ1T		DQ1T	
7A	VREFB7A0	IO			DIFFIO_TX_T2n	DIFFOUT_T2n	G6				
7A	VREFB7A0	IO	CLK13p		DIFFIO_RX_T3p	DIFFOUT_T3p	A6	DQ1T		DQ1T	
7A	VREFB7A0	IO	CLK13n		DIFFIO_RX_T3n	DIFFOUT_T3n	B6	DQ1T		DQ1T	
7A	VREFB7A0	IO			DIFFIO_TX_T4p	DIFFOUT_T4p	F7	DQ1T		DQ1T	
7A	VREFB7A0	IO			DIFFIO_TX_T4n	DIFFOUT_T4n	G7				
7A	VREFB7A0	IO	CLK14p		DIFFIO_RX_T5p	DIFFOUT_T5p	E6	DQS1T/CQ1T/CQn1T/QKn1T	DQS1T/CQ1T/CQn1T/QKn1T	DQ1T	
7A	VREFB7A0	IO	CLK14n		DIFFIO_RX_T5n	DIFFOUT_T5n	E7	DQSn1T/QKn1T		DQ1T	
7A	VREFB7A0	IO			DIFFIO_TX_T6p	DIFFOUT_T6p	C7	DQ1T		DQ1T	
7A	VREFB7A0	IO			DIFFIO_TX_T6n	DIFFOUT_T6n	D7				
7A	VREFB7A0	IO	FPLL_TR_CLKOUT2.FPLL_TR_FBp.FPLL_TR_FB1		DIFFIO_RX_T7p	DIFFOUT_T7p	F8	DQ1T		DQ1T	
7A	VREFB7A0	IO	FPLL_TR_CLKOUT3.FPLL_TR_FBn		DIFFIO_RX_T7n	DIFFOUT_T7n	G8	DQ1T		DQ1T	
7A	VREFB7A0	IO	FPLL_TR_CLKOUT0.FPLL_TR_CLKOUTp.FPLL_TR_FB0		DIFFIO_TX_T8p	DIFFOUT_T8p	J8	DQ1T		DQ1T	
7A	VREFB7A0	IO	FPLL_TR_CLKOUT1.FPLL_TR_CLKOUTn		DIFFIO_TX_T8n	DIFFOUT_T8n	K8				
7A	VREFB7A0	IO	CLK15p		DIFFIO_RX_T9p	DIFFOUT_T9p	H6	DQ2T		DQ1T	
7A	VREFB7A0	IO	CLK15n		DIFFIO_RX_T9n	DIFFOUT_T9n	J6	DQ2T		DQ1T	
7A	VREFB7A0	IO					K7	DQ2T		DQ1T	
7A	VREFB7A0	IO	VREFB7A0				J7				
7A	VREFB7A0	IO		DEV OE	DIFFIO_RX_T10p	DIFFOUT_T10p	K6	DQ2T		DQ1T	
7A	VREFB7A0	IO		DEV CLRn	DIFFIO_RX_T10n	DIFFOUT_T10n	L6	DQ2T		DQ1T	
7A	VREFB7A0	IO			DIFFIO_TX_T11p	DIFFOUT_T11p	M8	DQ2T		DQ1T	
7A	VREFB7A0	IO	HPERSTL0		DIFFIO_TX_T11n	DIFFOUT_T11n	N8				
7A	VREFB7A0	IO	CvP_CONFDONE		DIFFIO_RX_T12p	DIFFOUT_T12p	P10	DQS2T/CQ2T/CQn2T/QKn2T	DQ1T	DQS1T/CQ1T/CQn1T/QKn1T	
7A	VREFB7A0	IO	CRC_ERROR		DIFFIO_RX_T12n	DIFFOUT_T12n	P9	DQS2T/CQ2T		DQ1T	
7A	VREFB7A0	IO	PR_DONE		DIFFIO_TX_T13p	DIFFOUT_T13p	L7	DQ2T		DQ1T	
7A	VREFB7A0	IO	PR_REQUEST		DIFFIO_TX_T13n	DIFFOUT_T13n	M6				
7A	VREFB7A0	IO	INIT_DONE		DIFFIO_RX_T14p	DIFFOUT_T14p	M7	DQ2T		DQ1T	
7A	VREFB7A0	IO	HCEO		DIFFIO_TX_T14n	DIFFOUT_T14n	N7	DQ2T		DQ1T	
7A	VREFB7A0	IO	PR_ERROR		DIFFIO_TX_T15p	DIFFOUT_T15p	L10	DQ2T		DQ1T	
7A	VREFB7A0	IO	PR_READY		DIFFIO_TX_T15n	DIFFOUT_T15n	M10				
7A	VREFB7A0	IO			DIFFIO_RX_T16p	DIFFOUT_T16p	D9	DQ3T		DQ2T	
7A	VREFB7A0	IO			DIFFIO_RX_T16n	DIFFOUT_T16n	E9	DQ3T		DQ2T	
7A	VREFB7A0	IO			DIFFIO_TX_T17p	DIFFOUT_T17p	F9	DQ3T		DQ1T	
7A	VREFB7A0	IO			DIFFIO_TX_T17n	DIFFOUT_T17n	G9				
7A	VREFB7A0	IO			DIFFIO_RX_T18p	DIFFOUT_T18p	C8	DQ3T		DQ2T	
7A	VREFB7A0	IO			DIFFIO_RX_T18n	DIFFOUT_T18n	D8	DQ3T		DQ2T	
7A	VREFB7A0	IO			DIFFIO_TX_T19p	DIFFOUT_T19p	K9	DQ3T		DQ2T	
7A	VREFB7A0	IO			DIFFIO_TX_T19n	DIFFOUT_T19n	L9				
7A	VREFB7A0	IO			DIFFIO_RX_T20p	DIFFOUT_T20p	A7	DQS3T/CQ3T/CQn3T/QKn3T	DQS2T/CQ2T/CQn2T/QKn2T	DQ1T	
7A	VREFB7A0	IO			DIFFIO_RX_T20n	DIFFOUT_T20n	B7	DQS3T/CQ3T		DQ1T	
7A	VREFB7A0	IO			DIFFIO_TX_T21p	DIFFOUT_T21p	B9	DQ3T		DQ2T	
7A	VREFB7A0	IO			DIFFIO_TX_T21n	DIFFOUT_T21n	C9				
7A	VREFB7A0	IO			DIFFIO_RX_T22p	DIFFOUT_T22p	A9	DQ3T		DQ2T	
7A	VREFB7A0	IO			DIFFIO_RX_T22n	DIFFOUT_T22n	A8	DQ3T		DQ1T	
7A	VREFB7A0	IO			DIFFIO_TX_T23p	DIFFOUT_T23p	H9	DQ3T		DQ2T	
7A	VREFB7A0	IO			DIFFIO_TX_T23n	DIFFOUT_T23n	J9				
7B	VREFB7B0	IO			DIFFIO_RX_T24p	DIFFOUT_T24p	E10	DQ4T		DQ1T	DQ5_7B_0
7B	VREFB7B0	IO			DIFFIO_RX_T24n	DIFFOUT_T24n	F10	DQ4T		DQ1T	DQ5_7B_1
7B	VREFB7B0	IO			DIFFIO_TX_T25p	DIFFOUT_T25p	N10	DQ4T		DQ1T	DQ5_7B_2
7B	VREFB7B0	IO			DIFFIO_TX_T25n	DIFFOUT_T25n	M11				
7B	VREFB7B0	IO			DIFFIO_RX_T26p	DIFFOUT_T26p	B10	DQ4T		DQ2T	DQ5_7B_3
7B	VREFB7B0	IO			DIFFIO_RX_T26n	DIFFOUT_T26n	C10	DQ4T		DQ2T	DQ5_7B_4
7B	VREFB7B0	IO			DIFFIO_TX_T27p	DIFFOUT_T27p	H10	DQ4T		DQ2T	DQ5_7B_5
7B	VREFB7B0	IO			DIFFIO_TX_T27n	DIFFOUT_T27n	J10				
7B	VREFB7B0	IO			DIFFIO_RX_T28p	DIFFOUT_T28p	P12	DQS4T/CQ4T/CQn4T/QKn4T	DQ2T	DQ1T	DQ5_7B_6
7B	VREFB7B0	IO			DIFFIO_RX_T28n	DIFFOUT_T28n	R12	DQS4T/QKn4T		DQ1T	DQ5_7B_7
7B	VREFB7B0	IO			DIFFIO_TX_T29p	DIFFOUT_T29p	R11	DQ4T		DQ1T	DQ5_7B_8
7B	VREFB7B0	IO			DIFFIO_TX_T29n	DIFFOUT_T29n	T11				
7B	VREFB7B0	IO			DIFFIO_RX_T30p	DIFFOUT_T30p	A11	DQ4T		DQ2T	DQ5_7B_9
7B	VREFB7B0	IO			DIFFIO_RX_T30n	DIFFOUT_T30n	A10	DQ4T		DQ1T	DQ5_7B_10
7B	VREFB7B0	IO			DIFFIO_TX_T31p	DIFFOUT_T31p	J11	DQ4T		DQ2T	DQ5_7B_11
7B	VREFB7B0	IO			DIFFIO_TX_T31n	DIFFOUT_T31n	K11				
7B	VREFB7B0	IO			DIFFIO_RX_T32p	DIFFOUT_T32p	M12	DQ5T		DQ3T	DQ4_7B_0
7B	VREFB7B0	IO			DIFFIO_RX_T32n	DIFFOUT_T32n	N12	DQ5T		DQ3T	DQ4_7B_1
7B	VREFB7B0	IO					F11	DQ5T		DQ3T	DQ4_7B_2
7B	VREFB7B0	IO	VREFB7B0				G11				
7B	VREFB7B0	IO			DIFFIO_RX_T33p	DIFFOUT_T33p	C11	DQ5T		DQ3T	DQ4_7B_3
7B	VREFB7B0	IO			DIFFIO_RX_T33n	DIFFOUT_T33n	D11	DQ5T		DQ3T	DQ4_7B_4
7B	VREFB7B0	IO			DIFFIO_TX_T34p	DIFFOUT_T34p	K12	DQ5T		DQ3T	DQ4_7B_5
7B	VREFB7B0	IO			DIFFIO_TX_T34n	DIFFOUT_T34n	L12				
7B	VREFB7B0	IO			DIFFIO_RX_T35p	DIFFOUT_T35p	D12	DQS5T/CQ5T/CQn5T/QKn5T	DQS3T/CQ3T/CQn3T/QKn3T	DQ2T	DQ5_7B_6
7B	VREFB7B0	IO			DIFFIO_RX_T35n	DIFFOUT_T35n	E12	DQS5T/QKn5T		DQ2T	DQ5_7B_7
7B	VREFB7B0	IO			DIFFIO_TX_T36p	DIFFOUT_T36p	F12	DQ5T		DQ3T	DQ5_7B_8
7B	VREFB7B0	IO			DIFFIO_TX_T36n	DIFFOUT_T36n	G12				
7B	VREFB7B0	IO			DIFFIO_RX_T37p	DIFFOUT_T37p	P13	DQ5T		DQ3T	DQ4_7B_6
7B	VREFB7B0	IO			DIFFIO_RX_T37n	DIFFOUT_T37n	R13	DQ5T		DQ3T	DQ4_7B_7
7B	VREFB7B0	IO			DIFFIO_TX_T38p	DIFFOUT_T38p	H12	DQ5T		DQ3T	DQ4_7B_8
7B	VREFB7B0	IO			DIFFIO_TX_T38n	DIFFOUT_T38n	J12				
7B	VREFB7B0	IO			DIFFIO_RX_T39p	DIFFOUT_T39p	B12	DQ6T		DQ3T	DQ3_7B_0
7B	VREFB7B0	IO			DIFFIO_RX_T39n	DIFFOUT_T39n	C12	DQ6T		DQ3T	DQ3_7B_1
7B	VREFB7B0	IO			DIFFIO_TX_T40p	DIFFOUT_T40p	M13	DQ6T		DQ3T	DQ3_7B_2
7B	VREFB7B0	IO			DIFFIO_TX_T40n	DIFFOUT_T40n	N13				
7B	VREFB7B0	IO			DIFFIO_RX_T41p	DIFFOUT_T41p	A13	DQ6T		DQ3T	DQ3_7B_3
7B	VREFB7B0	IO			DIFFIO_RX_T41n	DIFFOUT_T41n	A12	DQ6T		DQ3T	DQ3_7B_4
7B	VREFB7B0	IO			DIFFIO_TX_T42p	DIFFOUT_T42p	J13	DQ6T		DQ3T	DQ3_7B_5
7B	VREFB7B0	IO			DIFFIO_TX_T42n	DIFFOUT_T42n	K13				
7B	VREFB7B0	IO			DIFFIO_RX_T43p	DIFFOUT_T43p	D13	DQS6T/CQ6T/CQn6T/QKn6T	DQ3T	DQS2T/CQ2T/CQn2T/QKn2T	DQS3_7B_6
7B	VREFB7B0	IO			DIFFIO_RX_T43n	DIFFOUT_T43n	E13	DQS6T/QKn6T		DQ3T	DQS3_7B_7



Pin Information for the Arria® V 5AGXMB3 Device
Version 1.7
Note (1)

Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Output Channel	Emulated LVDS Output Channel	F1517	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
7B	VREFB7B0	IO			DIFFIO TX T44p	DIFFOUT T44p	A14	DQ6T		DQ3T	DM3_7B
7B	VREFB7B0	IO			DIFFIO TX T44n	DIFFOUT T44n	B13			DQ2T	
7B	VREFB7B0	IO			DIFFIO RX T45p	DIFFOUT T45p	C14	DQ6T		DQ3T	DQ3_7B_6
7B	VREFB7B0	IO			DIFFIO RX T45n	DIFFOUT T45n	D14	DQ6T		DQ3T	DQ3_7B_7
7B	VREFB7B0	IO			DIFFIO TX T46p	DIFFOUT T46p	G13	DQ6T		DQ3T	DQ3_7B_8
7B	VREFB7B0	IO			DIFFIO TX T46n	DIFFOUT T46n	H13				
7C	VREFB7C0	IO			DIFFIO RX T47p	DIFFOUT T47p	R14	DQ7T		DQ4T	DQ2_7C_0
7C	VREFB7C0	IO			DIFFIO RX T47n	DIFFOUT T47n	T14	DQ7T		DQ4T	DQ2_7C_1
7C	VREFB7C0	IO			DIFFIO TX T48p	DIFFOUT T48p	M14	DQ7T		DQ4T	DQ2_7C_2
7C	VREFB7C0	IO			DIFFIO TX T48n	DIFFOUT T48n	N14				
7C	VREFB7C0	IO			DIFFIO RX T49p	DIFFOUT T49p	F14	DQ7T		DQ4T	DQ2_7C_3
7C	VREFB7C0	IO			DIFFIO RX T49n	DIFFOUT T49n	G14	DQ7T		DQ4T	DQ2_7C_4
7C	VREFB7C0	IO			DIFFIO TX T50p	DIFFOUT T50p	L15	DQ7T		DQ4T	DQ2_7C_5
7C	VREFB7C0	IO			DIFFIO TX T50n	DIFFOUT T50n	M15				
7C	VREFB7C0	IO			DIFFIO RX T51p	DIFFOUT T51p	R15	DQS7T/CQ7T/CQn7T/QKn7T	DQS4T/CQ4T/CQn4T/QKn4T	DQ2T	DQS2_7C
7C	VREFB7C0	IO			DIFFIO RX T51n	DIFFOUT T51n	T15	DQSn7T/QKn7T	DQSn4T/QKn4T	DQ2T	DQS2_7C
7C	VREFB7C0	IO			DIFFIO TX T52p	DIFFOUT T52p	N15	DQ7T		DQ4T	DM2_7C
7C	VREFB7C0	IO			DIFFIO TX T52n	DIFFOUT T52n	P14				
7C	VREFB7C0	IO			DIFFIO RX T53p	DIFFOUT T53p	E15	DQ7T		DQ4T	DQ2_7C_6
7C	VREFB7C0	IO			DIFFIO RX T53n	DIFFOUT T53n	F15	DQ7T		DQ4T	DQ2_7C_7
7C	VREFB7C0	IO			DIFFIO TX T54p	DIFFOUT T54p	J14	DQ7T		DQ4T	DQ2_7C_8
7C	VREFB7C0	IO			DIFFIO TX T54n	DIFFOUT T54n	K14				
7C	VREFB7C0	IO			DIFFIO RX T55p	DIFFOUT T55p	P16	DQ8T		DQ4T	DQ1_7C_0
7C	VREFB7C0	IO			DIFFIO RX T55n	DIFFOUT T55n	R16	DQ8T		DQ4T	DQ1_7C_1
7C	VREFB7C0	IO					C15	DQ8T		DQ4T	DQ1_7C_2
7C	VREFB7C0	IO	VREFB7CNO				D15				
7C	VREFB7C0	IO			DIFFIO RX T56p	DIFFOUT T56p	M16	DQ8T		DQ4T	DQ1_7C_3
7C	VREFB7C0	IO			DIFFIO RX T56n	DIFFOUT T56n	N16	DQ8T		DQ4T	DQ1_7C_4
7C	VREFB7C0	IO			DIFFIO TX T57p	DIFFOUT T57p	H15	DQ8T		DQ4T	DQ1_7C_5
7C	VREFB7C0	IO			DIFFIO TX T57n	DIFFOUT T57n	J15				
7C	VREFB7C0	IO			DIFFIO RX T58p	DIFFOUT T58p	G16	DQS8T/CQ8T/CQn8T/QKn8T	DQ4T	DQ2T	DQS1_7C
7C	VREFB7C0	IO			DIFFIO RX T58n	DIFFOUT T58n	H16	DQS8n8T/QKn8T	DQ4T	DQ2T	DQS1_7C
7C	VREFB7C0	IO			DIFFIO TX T59p	DIFFOUT T59p	A15	DQ8T		DQ4T	DM1_7C
7C	VREFB7C0	IO			DIFFIO TX T59n	DIFFOUT T59n	B15				
7C	VREFB7C0	IO			DIFFIO RX T60p	DIFFOUT T60p	D16	DQ8T		DQ4T	DQ1_7C_6
7C	VREFB7C0	IO			DIFFIO RX T60n	DIFFOUT T60n	E16	DQ8T		DQ4T	DQ1_7C_7
7C	VREFB7C0	IO			DIFFIO TX T61p	DIFFOUT T61p	J16	DQ8T		DQ4T	DQ1_7C_8
7C	VREFB7C0	IO			DIFFIO TX T61n	DIFFOUT T61n	K16				RESET#_7D
7D	VREFB7D0	IO			DIFFIO RX T62p	DIFFOUT T62p	N18	DQ9T		DQ5T	CK_7D
7D	VREFB7D0	IO			DIFFIO RX T62n	DIFFOUT T62n	P18	DQ9T		DQ5T	CK#_7D
7D	VREFB7D0	IO			DIFFIO TX T63p	DIFFOUT T63p	M17	DQ9T		DQ5T	CKE_7D_0
7D	VREFB7D0	IO			DIFFIO TX T63n	DIFFOUT T63n	N17				CKE_7D_1
7D	VREFB7D0	IO			DIFFIO RX T64p	DIFFOUT T64p	B16	DQ9T		DQ5T	A_7D_0
7D	VREFB7D0	IO			DIFFIO RX T64n	DIFFOUT T64n	C16	DQ9T		DQ5T	A_7D_1
7D	VREFB7D0	IO			DIFFIO TX T65p	DIFFOUT T65p	J17	DQ9T		DQ5T	A_7D_2
7D	VREFB7D0	IO			DIFFIO TX T65n	DIFFOUT T65n	K17				A_7D_3
7D	VREFB7D0	IO			DIFFIO RX T66p	DIFFOUT T66p	F17	DQS9T/CQ9T/CQn9T/QKn9T	DQS5T/CQ5T/CQn5T/QKn5T	DQ5T	A_7D_4
7D	VREFB7D0	IO			DIFFIO RX T66n	DIFFOUT T66n	G17	DQS9n9T/QKn9T	DQS9n5T/QKn9T	DQ5T	A_7D_5
7D	VREFB7D0	IO			DIFFIO TX T67p	DIFFOUT T67p	R17	DQ9T		DQ5T	A_7D_6
7D	VREFB7D0	IO			DIFFIO TX T67n	DIFFOUT T67n	T17				A_7D_7
7D	VREFB7D0	IO			DIFFIO RX T68p	DIFFOUT T68p	C17	DQ9T		DQ5T	A_7D_8
7D	VREFB7D0	IO			DIFFIO RX T68n	DIFFOUT T68n	D17	DQ9T		DQ5T	A_7D_9
7D	VREFB7D0	IO			DIFFIO TX T69p	DIFFOUT T69p	K18	DQ9T		DQ5T	A_7D_10
7D	VREFB7D0	IO			DIFFIO TX T69n	DIFFOUT T69n	L18				A_7D_11
7D	VREFB7D0	IO			DIFFIO RX T70p	DIFFOUT T70p	R19	DQ10T		DQ5T	A_7D_12
7D	VREFB7D0	IO			DIFFIO RX T70n	DIFFOUT T70n	T19	DQ10T		DQ5T	A_7D_13
7D	VREFB7D0	IO					R18	DQ10T		DQ5T	A_7D_14
7D	VREFB7D0	IO	VREFB7DNO				T18				
7D	VREFB7D0	IO			DIFFIO RX T71p	DIFFOUT T71p	E18	DQ10T		DQ5T	BA_7D_0
7D	VREFB7D0	IO			DIFFIO RX T71n	DIFFOUT T71n	F18	DQ10T		DQ5T	BA_7D_1
7D	VREFB7D0	IO			DIFFIO TX T72p	DIFFOUT T72p	H18	DQ10T		DQ5T	BA_7D_2
7D	VREFB7D0	IO			DIFFIO TX T72n	DIFFOUT T72n	J18				RAS#_7D
7D	VREFB7D0	IO			DIFFIO RX T73p	DIFFOUT T73p	N19	DQS10T/CQ10T/CQn10T/QKn10T	DQ5T	DQ5T	CAS#_7D
7D	VREFB7D0	IO			DIFFIO RX T73n	DIFFOUT T73n	P19	DQS10n10T/QKn10T	DQ5T	DQ5T	WE#_7D
7D	VREFB7D0	IO			DIFFIO TX T74p	DIFFOUT T74p	B18	DQ10T		DQ5T	ODT_7D_0
7D	VREFB7D0	IO			DIFFIO TX T74n	DIFFOUT T74n	C18				ODT_7D_1
7D	VREFB7D0	IO			DIFFIO RX T75p	DIFFOUT T75p	A17	DQ10T		DQ5T	A_7D_15
7D	VREFB7D0	IO			DIFFIO RX T75n	DIFFOUT T75n	A16	DQ10T		DQ5T	
7D	VREFB7D0	IO			DIFFIO TX T76p	DIFFOUT T76p	L19	DQ10T		DQ5T	CS#_7D_0
7D	VREFB7D0	IO			DIFFIO TX T76n	DIFFOUT T76n	M19				CS#_7D_1
7D	VREFB7D0	IO			DIFFIO RX T77p	DIFFOUT T77p	F19	DQ11T			
7D	VREFB7D0	IO			DIFFIO RX T77n	DIFFOUT T77n	G19	DQ11T			
7D	VREFB7D0	IO			DIFFIO TX T78p	DIFFOUT T78p	J19	DQ11T			
7D	VREFB7D0	IO			DIFFIO TX T78n	DIFFOUT T78n	K19				
7D	VREFB7D0	IO			DIFFIO RX T79p	DIFFOUT T79p	C19	DQ11T			
7D	VREFB7D0	IO			DIFFIO RX T79n	DIFFOUT T79n	D19	DQ11T			
7D	VREFB7D0	IO			DIFFIO TX T80p	DIFFOUT T80p	J20	DQ11T			
7D	VREFB7D0	IO			DIFFIO TX T80n	DIFFOUT T80n	K20				
7D	VREFB7D0	IO			DIFFIO RX T81p	DIFFOUT T81p	A18	DQS11T/CQ11T/CQn11T/QKn11T			
7D	VREFB7D0	IO			DIFFIO RX T81n	DIFFOUT T81n	A19	DQS11n11T/QKn11T			
7D	VREFB7D0	IO			DIFFIO TX T82p	DIFFOUT T82p	R20	DQ11T			
7D	VREFB7D0	IO			DIFFIO TX T82n	DIFFOUT T82n	T20				
7D	VREFB7D0	IO			DIFFIO RX T83p	DIFFOUT T83p	F20	DQ11T			
7D	VREFB7D0	IO			DIFFIO RX T83n	DIFFOUT T83n	G20	DQ11T			
7D	VREFB7D0	IO			DIFFIO TX T84p	DIFFOUT T84p	M20	DQ11T			
7D	VREFB7D0	IO			DIFFIO TX T84n	DIFFOUT T84n	N20				
	VCCA_FPLL						V20				
	VCCO_FPLL						V19				
	DNU						P21				
8D	VREFB8D0	IO	CLK19p		DIFFIO RX T85p	DIFFOUT T85p	C20	DQ12T		DQ6T	DQ3T
8D	VREFB8D0	IO	CLK19n		DIFFIO RX T85n	DIFFOUT T85n	D20	DQ12T		DQ6T	DQ3T
8D	VREFB8D0	IO			DIFFIO TX T86p	DIFFOUT T86p	M21	DQ12T		DQ6T	DQ3T
8D	VREFB8D0	IO			DIFFIO TX T86n	DIFFOUT T86n	N21				
8D	VREFB8D0	IO	CLK18p		DIFFIO RX T87p	DIFFOUT T87p	G21	DQ12T		DQ6T	DQ3T
8D	VREFB8D0	IO	CLK18n		DIFFIO RX T87n	DIFFOUT T87n	H21	DQ12T		DQ6T	DQ3T
8D	VREFB8D0	IO			DIFFIO TX T88p	DIFFOUT T88p	D21	DQ12T		DQ6T	DQ3T



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1517	DQS for X8/X9	DQS for X16/X18	DQS for X32/X36	DDR3/DDR2 hard memory PHY (3)
8D	VREFB8D0	IO			DIFFIO TX T88h	DIFFOUT T88h	E21				
8D	VREFB8D0	IO	FPLL TC_CLKOUT2.FPLL TC_FBp.FPLL TC_FB1		DIFFIO RX T89p	DIFFOUT T89p	A20	DQS12T/CQ12T/CQn12T/QKn12T	DQS6T/CQ6T/CQn6T/QKn6T	DQ3T	
8D	VREFB8D0	IO	FPLL TC_CLKOUT3.FPLL TC_FBn		DIFFIO RX T89h	DIFFOUT T89h	B21	DQSn12T/QK12T	DQSn6T/QK6T	DQ3T	
8D	VREFB8D0	IO	FPLL TC_CLKOUT0.FPLL TC_CLKOUTp.FPLL TC_FB0		DIFFIO TX T90p	DIFFOUT T90p	J21	DQ12T	DQ6T	DQ3T	
8D	VREFB8D0	IO	FPLL TC_CLKOUT1.FPLL TC_CLKOUTn		DIFFIO TX T90h	DIFFOUT T90h	K21				
8D	VREFB8D0	IO	CLK17p		DIFFIO RX T91p	DIFFOUT T91p	A22	DQ12T	DQ6T	DQ3T	
8D	VREFB8D0	IO	CLK17h		DIFFIO RX T91h	DIFFOUT T91h	A21	DQ12T	DQ6T	DQ3T	
8D	VREFB8D0	IO			DIFFIO TX T92p	DIFFOUT T92p	R21	DQ12T	DQ6T	DQ3T	
8D	VREFB8D0	IO			DIFFIO TX T92h	DIFFOUT T92h	T21				
8D	VREFB8D0	IO	CLK16p		DIFFIO RX T93p	DIFFOUT T93p	B22	DQ13T	DQ6T	DQ3T	
8D	VREFB8D0	IO	CLK16h		DIFFIO RX T93h	DIFFOUT T93h	C22	DQ13T	DQ6T	DQ3T	
8D	VREFB8D0	IO		VREFB8D0			J22	DQ13T	DQ6T	DQ3T	
8D	VREFB8D0	IO					H22				
8D	VREFB8D0	IO			DIFFIO RX T94p	DIFFOUT T94p	E22	DQ13T	DQ6T	DQ3T	
8D	VREFB8D0	IO			DIFFIO RX T94h	DIFFOUT T94h	F22	DQ13T	DQ6T	DQ3T	
8D	VREFB8D0	IO			DIFFIO TX T95p	DIFFOUT T95p	A23	DQ13T	DQ6T	DQ3T	
8D	VREFB8D0	IO			DIFFIO TX T95h	DIFFOUT T95h	A24				
8D	VREFB8D0	IO			DIFFIO RX T96p	DIFFOUT T96p	C23	DQS13T/CQ13T/CQn13T/QKn13T	DQ6T	DQS3T/CQ3T/CQn3T/QKn3T	
8D	VREFB8D0	IO			DIFFIO RX T96h	DIFFOUT T96h	D23	DQSn13T/QK13T	DQ6T	DQSn3T/QK3T	
8D	VREFB8D0	IO			DIFFIO TX T97p	DIFFOUT T97p	L22	DQ13T	DQ6T	DQ3T	
8D	VREFB8D0	IO			DIFFIO TX T97h	DIFFOUT T97h	M22				
8D	VREFB8D0	IO			DIFFIO RX T98p	DIFFOUT T98p	N22	DQ13T	DQ6T	DQ3T	
8D	VREFB8D0	IO			DIFFIO RX T98h	DIFFOUT T98h	P22	DQ13T	DQ6T	DQ3T	
8D	VREFB8D0	IO			DIFFIO TX T99p	DIFFOUT T99p	R22	DQ13T	DQ6T	DQ3T	
8D	VREFB8D0	IO			DIFFIO TX T99h	DIFFOUT T99h	T22				
8D	VREFB8D0	IO			DIFFIO RX T100p	DIFFOUT T100p	F23	DQ14T	DQ7T	DQ3T	
8D	VREFB8D0	IO			DIFFIO RX T100h	DIFFOUT T100h	G23	DQ14T	DQ7T	DQ3T	
8D	VREFB8D0	IO			DIFFIO TX T101p	DIFFOUT T101p	R23	DQ14T	DQ7T	DQ3T	
8D	VREFB8D0	IO			DIFFIO TX T101h	DIFFOUT T101h	T23				
8D	VREFB8D0	IO			DIFFIO RX T102p	DIFFOUT T102p	L24	DQ14T	DQ7T	DQ3T	
8D	VREFB8D0	IO			DIFFIO RX T102h	DIFFOUT T102h	C24	DQ14T	DQ7T	DQ3T	
8D	VREFB8D0	IO			DIFFIO TX T103p	DIFFOUT T103p	M23	DQ14T	DQ7T	DQ3T	
8D	VREFB8D0	IO			DIFFIO TX T103h	DIFFOUT T103h	N23				
8D	VREFB8D0	IO			DIFFIO RX T104p	DIFFOUT T104p	D24	DQS14T/CQ14T/CQn14T/QKn14T	DQS7T/CQ7T/CQn7T/QKn7T	DQ3T	
8D	VREFB8D0	IO			DIFFIO RX T104h	DIFFOUT T104h	E24	DQSn14T/QK14T	DQS7T/QK7T	DQ3T	
8D	VREFB8D0	IO			DIFFIO TX T105p	DIFFOUT T105p	J23	DQ14T	DQ7T	DQ3T	
8D	VREFB8D0	IO			DIFFIO TX T105h	DIFFOUT T105h	K23				
8D	VREFB8D0	IO			DIFFIO RX T106p	DIFFOUT T106p	F24	DQ14T	DQ7T	DQ3T	
8D	VREFB8D0	IO			DIFFIO RX T106h	DIFFOUT T106h	G24	DQ14T	DQ7T	DQ3T	
8D	VREFB8D0	IO			DIFFIO TX T107p	DIFFOUT T107p	H24	DQ14T	DQ7T	DQ3T	
8D	VREFB8D0	IO			DIFFIO TX T107h	DIFFOUT T107h	J24				
8C	VREFB8C0	IO			DIFFIO RX T108p	DIFFOUT T108p	A26	DQ15T	DQ7T	DQ3T	
8C	VREFB8C0	IO			DIFFIO RX T108h	DIFFOUT T108h	T25	DQ15T	DQ7T	DQ3T	
8C	VREFB8C0	IO			DIFFIO TX T109p	DIFFOUT T109p	G25	DQ15T	DQ7T	DQ3T	
8C	VREFB8C0	IO			DIFFIO TX T109h	DIFFOUT T109h	H25				
8C	VREFB8C0	IO			DIFFIO RX T110p	DIFFOUT T110p	N24	DQ15T	DQ7T	DQ3T	
8C	VREFB8C0	IO			DIFFIO RX T110h	DIFFOUT T110h	P24	DQ15T	DQ7T	DQ3T	
8C	VREFB8C0	IO			DIFFIO TX T111p	DIFFOUT T111p	R24	DQ15T	DQ7T	DQ3T	
8C	VREFB8C0	IO			DIFFIO TX T111h	DIFFOUT T111h	T24				
8C	VREFB8C0	IO			DIFFIO RX T112p	DIFFOUT T112p	A25	DQS15T/CQ15T/CQn15T/QKn15T	DQ7T	DQ3T	
8C	VREFB8C0	IO			DIFFIO RX T112h	DIFFOUT T112h	B25	DQSn15T/QK15T	DQ7T	DQ3T	
8C	VREFB8C0	IO			DIFFIO TX T113p	DIFFOUT T113p	K24	DQ15T	DQ7T	DQ3T	
8C	VREFB8C0	IO			DIFFIO TX T113h	DIFFOUT T113h	L24				
8C	VREFB8C0	IO			DIFFIO RX T114p	DIFFOUT T114p	D25	DQ15T	DQ7T	DQ3T	
8C	VREFB8C0	IO			DIFFIO RX T114h	DIFFOUT T114h	E25	DQ15T	DQ7T	DQ3T	
8C	VREFB8C0	IO			DIFFIO TX T115p	DIFFOUT T115p	P25	DQ15T	DQ7T	DQ3T	
8C	VREFB8C0	IO			DIFFIO TX T115h	DIFFOUT T115h	R25				
8C	VREFB8C0	IO			DIFFIO RX T116p	DIFFOUT T116p	C26	DQ16T	DQ8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO RX T116h	DIFFOUT T116h	D26	DQ16T	DQ8T	DQ4T	
8C	VREFB8C0	IO	VREFB8C0				K25	DQ16T	DQ8T	DQ4T	
8C	VREFB8C0	IO					L25				
8C	VREFB8C0	IO			DIFFIO RX T117p	DIFFOUT T117p	R26	DQ16T	DQ8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO RX T117h	DIFFOUT T117h	T27	DQ16T	DQ8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO TX T118p	DIFFOUT T118p	A26	DQ16T	DQ8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO TX T118h	DIFFOUT T118h	A27				
8C	VREFB8C0	IO			DIFFIO RX T119p	DIFFOUT T119p	M26	DQS16T/CQ16T/CQn16T/QKn16T	DQS8T/CQ8T/CQn8T/QKn8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO RX T119h	DIFFOUT T119h	N26	DQSn16T/QK16T	DQS8T/QK8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO TX T120p	DIFFOUT T120p	J26	DQ16T	DQ8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO TX T120h	DIFFOUT T120h	K26				
8C	VREFB8C0	IO			DIFFIO RX T121p	DIFFOUT T121p	F26	DQ16T	DQ8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO RX T121h	DIFFOUT T121h	G26	DQ16T	DQ8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO TX T122p	DIFFOUT T122p	M25	DQ16T	DQ8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO TX T122h	DIFFOUT T122h	N25				
8C	VREFB8C0	IO			DIFFIO RX T123p	DIFFOUT T123p	P27	DQ17T	DQ8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO RX T123h	DIFFOUT T123h	R27	DQ17T	DQ8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO TX T124p	DIFFOUT T124p	H27	DQ17T	DQ8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO TX T124h	DIFFOUT T124h	J27				
8C	VREFB8C0	IO			DIFFIO RX T125p	DIFFOUT T125p	B27	DQ17T	DQ8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO RX T125h	DIFFOUT T125h	C27	DQ17T	DQ8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO TX T126p	DIFFOUT T126p	E27	DQ17T	DQ8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO TX T126h	DIFFOUT T126h	F27				
8C	VREFB8C0	IO			DIFFIO RX T127p	DIFFOUT T127p	R28	DQS17T/CQ17T/CQn17T/QKn17T	DQ8T	DQS4T/CQ4T/CQn4T/QKn4T	
8C	VREFB8C0	IO			DIFFIO RX T127h	DIFFOUT T127h	T28	DQSn17T/QK17T	DQ8T	DQSn4T/QK4T	
8C	VREFB8C0	IO			DIFFIO TX T128p	DIFFOUT T128p	K27	DQ17T	DQ8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO TX T128h	DIFFOUT T128h	L27				
8C	VREFB8C0	IO			DIFFIO RX T129p	DIFFOUT T129p	M27	DQ17T	DQ8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO RX T129h	DIFFOUT T129h	N27	DQ17T	DQ8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO TX T130p	DIFFOUT T130p	C28	DQ17T	DQ8T	DQ4T	
8C	VREFB8C0	IO			DIFFIO TX T130h	DIFFOUT T130h	P28				
8B	VREFB8B0	IO			DIFFIO RX T131p	DIFFOUT T131p	L28	DQ18T	DQ9T	DQ4T	
8B	VREFB8B0	IO			DIFFIO RX T131h	DIFFOUT T131h	M28	DQ18T	DQ9T	DQ4T	
8B	VREFB8B0	IO			DIFFIO TX T132p	DIFFOUT T132p	H28	DQ18T	DQ9T	DQ4T	
8B	VREFB8B0	IO			DIFFIO TX T132h	DIFFOUT T132h	J28				
8B	VREFB8B0	IO			DIFFIO RX T133p	DIFFOUT T133p	C29	DQ18T	DQ9T	DQ4T	
8B	VREFB8B0	IO			DIFFIO RX T133h	DIFFOUT T133h	D28	DQ18T	DQ9T	DQ4T	
8B	VREFB8B0	IO			DIFFIO TX T134p	DIFFOUT T134p	F28	DQ18T	DQ9T	DQ4T	



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1517	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
BB	VREFB8N0	IO			DIFFIO TX T134n	DIFFOUT T134n	G28				
BB	VREFB8N0	IO			DIFFIO RX T135p	DIFFOUT T135p	R29	DQS18T/CO18T/CQn18T/QKn18T	DQS9T/CO9T/CQn9T/QKn9T	DO4T	
BB	VREFB8N0	IO			DIFFIO RX T135n	DIFFOUT T135n	T29	DQSn18T/QKn18T	DQSn9T/QKn9T	DO4T	
BB	VREFB8N0	IO			DIFFIO TX T136p	DIFFOUT T136p	J29	DO18T		DO4T	
BB	VREFB8N0	IO			DIFFIO TX T136n	DIFFOUT T136n	K29				
BB	VREFB8N0	IO			DIFFIO RX T137p	DIFFOUT T137p	M29	DO18T		DO4T	
BB	VREFB8N0	IO			DIFFIO RX T137n	DIFFOUT T137n	N30	DO18T		DO4T	
BB	VREFB8N0	IO			DIFFIO TX T138p	DIFFOUT T138p	F29	DO18T		DO4T	
BB	VREFB8N0	IO			DIFFIO TX T138n	DIFFOUT T138n	G29				
BB	VREFB8N0	IO			DIFFIO RX T139p	DIFFOUT T139p	B28	DO19T		DO4T	
BB	VREFB8N0	IO			DIFFIO RX T139n	DIFFOUT T139n	C29	DO19T		DO4T	
BB	VREFB8N0	IO					R30	DO19T		DO4T	
BB	VREFB8N0	IO	VREFB8N0								
BB	VREFB8N0	IO			DIFFIO RX T140p	DIFFOUT T140p	A29	DO19T		DO4T	
BB	VREFB8N0	IO			DIFFIO RX T140n	DIFFOUT T140n	A28	DO19T		DO4T	
BB	VREFB8N0	IO			DIFFIO TX T141p	DIFFOUT T141p	L30	DO19T		DO4T	
BB	VREFB8N0	IO			DIFFIO TX T141n	DIFFOUT T141n	M30				
BB	VREFB8N0	IO			DIFFIO RX T142p	DIFFOUT T142p	N30	DQS19T/CO19T/CQn19T/QKn19T		DO4T	
BB	VREFB8N0	IO			DIFFIO RX T142n	DIFFOUT T142n	P30	DQSn19T/QKn19T		DO4T	
BB	VREFB8N0	IO			DIFFIO TX T143p	DIFFOUT T143p	J30	DO19T		DO4T	
BB	VREFB8N0	IO			DIFFIO TX T143n	DIFFOUT T143n	K30				
BB	VREFB8N0	IO			DIFFIO RX T144p	DIFFOUT T144p	D30	DO19T		DO4T	
BB	VREFB8N0	IO			DIFFIO RX T144n	DIFFOUT T144n	D29	DO19T		DO4T	
BB	VREFB8N0	IO			DIFFIO TX T145p	DIFFOUT T145p	F30	DO19T		DO4T	
BB	VREFB8N0	IO			DIFFIO TX T145n	DIFFOUT T145n	G30				
BA	VREFB8A0	IO			DIFFIO RX T146p	DIFFOUT T146p	B30	DO20T		DO10T	
BA	VREFB8A0	IO			DIFFIO RX T146n	DIFFOUT T146n	C30	DO20T		DO10T	
BA	VREFB8A0	IO			DIFFIO TX T147p	DIFFOUT T147p	E31	DO20T		DO10T	
BA	VREFB8A0	IO			DIFFIO TX T147n	DIFFOUT T147n	F31				
BA	VREFB8A0	IO			DIFFIO RX T148p	DIFFOUT T148p	M31	DO20T		DO10T	
BA	VREFB8A0	IO			DIFFIO RX T148n	DIFFOUT T148n	A30	DO20T		DO10T	
BA	VREFB8A0	IO			DIFFIO TX T149p	DIFFOUT T149p	A31	DO20T		DO10T	
BA	VREFB8A0	IO			DIFFIO TX T149n	DIFFOUT T149n	A32				
BA	VREFB8A0	IO			DIFFIO RX T150p	DIFFOUT T150p	A33	DQS20T/CO20T/CQn20T/QKn20T		DQS10T/CO10T/CQn10T/QKn10T	
BA	VREFB8A0	IO			DIFFIO RX T150n	DIFFOUT T150n	B33	DQSn20T/QKn20T		DQSn10T/QKn10T	
BA	VREFB8A0	IO			DIFFIO TX T151p	DIFFOUT T151p	D31	DO20T		DO10T	
BA	VREFB8A0	IO			DIFFIO TX T151n	DIFFOUT T151n	J31				
BA	VREFB8A0	IO			DIFFIO RX T152p	DIFFOUT T152p	C31	DO20T		DO10T	
BA	VREFB8A0	IO			DIFFIO RX T152n	DIFFOUT T152n	D31	DO20T		DO10T	
BA	VREFB8A0	IO			DIFFIO TX T153p	DIFFOUT T153p	C32	DO20T		DO10T	
BA	VREFB8A0	IO			DIFFIO TX T153n	DIFFOUT T153n	D32				
BA	VREFB8A0	IO			DIFFIO RX T154p	DIFFOUT T154p	D31	DO21T		DO10T	
BA	VREFB8A0	IO			DIFFIO RX T154n	DIFFOUT T154n	P31	DO21T		DO10T	
BA	VREFB8A0	IO			DIFFIO TX T155p	DIFFOUT T155p	J32	DO21T		DO10T	
BA	VREFB8A0	IO			DIFFIO TX T155n	DIFFOUT T155n	K32				
BA	VREFB8A0	IO			DIFFIO RX T156p	DIFFOUT T156p	M32	DO21T		DO10T	
BA	VREFB8A0	IO			DIFFIO RX T156n	DIFFOUT T156n	N32	DO21T		DO10T	
BA	VREFB8A0	IO			DIFFIO TX T157p	DIFFOUT T157p	J34	DO21T		DO10T	
BA	VREFB8A0	IO			DIFFIO TX T157n	DIFFOUT T157n	K34				
BA	VREFB8A0	IO			DIFFIO RX T158p	DIFFOUT T158p	L33	DQS21T/CO21T/CQn21T/QKn21T		DO10T	
BA	VREFB8A0	IO			DIFFIO RX T158n	DIFFOUT T158n	M33	DQSn21T/QKn21T		DO10T	
BA	VREFB8A0	IO			DIFFIO TX T159p	DIFFOUT T159p	L31	DO21T		DO10T	
BA	VREFB8A0	IO			DIFFIO TX T159n	DIFFOUT T159n	M31				
BA	VREFB8A0	IO	CLK23p		DIFFIO TX T160p	DIFFOUT T160p	N34	DO21T		DO10T	
BA	VREFB8A0	IO	CLK23n		DIFFIO RX T160n	DIFFOUT T160n	N33	DO21T		DO10T	
BA	VREFB8A0	IO			DIFFIO TX T161p	DIFFOUT T161p	L34	DO21T		DO10T	
BA	VREFB8A0	IO			DIFFIO TX T161n	DIFFOUT T161n	M34				
BA	VREFB8A0	IO		CLK22p	DIFFIO RX T162p	DIFFOUT T162p	E34	DO22T			
BA	VREFB8A0	IO		CLK22n	DIFFIO RX T162n	DIFFOUT T162n	F34	DO22T			
BA	VREFB8A0	IO					J33	DO22T			
BA	VREFB8A0	IO		VREFB8A0			H33				
BA	VREFB8A0	IO			FPLL TL CLKOUT2,FPLL TL F8p,FPLL TL FB1	DIFFIO RX T163p	B34	DO22T			
BA	VREFB8A0	IO			FPLL TL CLKOUT3,FPLL TL FBn	DIFFIO RX T163n	A35	DO22T			
BA	VREFB8A0	IO			FPLL TL CLKOUT0,FPLL TL CLKOUTp,FPLL TL FB0	DIFFIO TX T164p	C33	DO22T			
BA	VREFB8A0	IO			FPLL TL CLKOUT1,FPLL TL CLKOUTn	DIFFIO TX T164n	D33				
BA	VREFB8A0	IO			CLK21p	DIFFIO RX T165p	G34	DQS22T/CO22T/CQn22T/QKn22T			
BA	VREFB8A0	IO			CLK21n	DIFFIO RX T165n	H34	DQSn22T/QKn22T			
BA	VREFB8A0	IO				DIFFIO TX T166p	F32	DO22T			
BA	VREFB8A0	IO				DIFFIO TX T166n	G32				
BA	VREFB8A0	IO		CLK20p	DIFFIO RX T167p	DIFFOUT T167p	C34	DO22T			
BA	VREFB8A0	IO		CLK20n	DIFFIO RX T167n	DIFFOUT T167n	D34	DO22T			
BA	VREFB8A0	IO				DIFFIO TX T168p	E33	DO22T			
BA	VREFB8A0	IO		RZQ_6	DIFFIO TX T168n	DIFFOUT T168n	F33				
BA	MSEL0			MSEL0			H35				
BA	MSEL1			MSEL1			A34				
BA	MSEL2			MSEL2			D35				
BA	MSEL3			MSEL3			A37				
BA	MSEL4			MSEL4			P34				
BA	CONF_DONE			CONF_DONE			K35				
BA	nSTATUS			nSTATUS			F35				
BA	nCE			nCE			M35				
BA	nCONFIG			nCONFIG			A36				
BA	GND						P35				
	GND						AA33				
	GND						AA35				
	GND						AA38				
	GND						AA39				
	GND						AB31				
	GND						AB32				
	GND						AB34				
	GND						AB36				
	GND						AB37				
	GND						AC33				
	GND						AC38				
	GND						AC39				
	GND						AD30				



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1517	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
		GND					AD32				
		GND					AD36				
		GND					AD37				
		GND					AE33				
		GND					AE35				
		GND					AE38				
		GND					AE39				
		GND					AF31				
		GND					AF32				
		GND					AF34				
		GND					AF36				
		GND					AF37				
		GND					AG38				
		GND					AG39				
		GND					AH32				
		GND					AH33				
		GND					AH34				
		GND					AH35				
		GND					AH36				
		GND					AH37				
		GND					AJ35				
		GND					AJ38				
		GND					AJ39				
		GND					AK36				
		GND					AK37				
		GND					AL35				
		GND					AL38				
		GND					AL39				
		GND					AM36				
		GND					AM37				
		GND					AN35				
		GND					AN38				
		GND					AN39				
		GND					AP36				
		GND					AP37				
		GND					AR35				
		GND					AR38				
		GND					AR39				
		GND					AT36				
		GND					AT37				
		GND					AU35				
		GND					AU38				
		GND					AU39				
		GND					AV35				
		GND					AV36				
		GND					AV37				
		GND					AV38				
		GND					AV39				
		GND					AW35				
		GND					AW38				
		GND					B36				
		GND					B37				
		GND					C35				
		GND					C38				
		GND					C39				
		GND					D36				
		GND					D37				
		GND					E35				
		GND					E38				
		GND					E39				
		GND					F36				
		GND					F37				
		GND					G35				
		GND					G38				
		GND					G39				
		GND					H36				
		GND					H37				
		GND					J35				
		GND					J38				
		GND					J39				
		GND					K36				
		GND					K37				
		GND					L35				
		GND					L38				
		GND					L39				
		GND					M36				
		GND					M37				
		GND					N35				
		GND					N38				
		GND					N39				
		GND					P36				
		GND					P37				
		GND					R34				
		GND					R38				
		GND					R39				
		GND					T32				
		GND					T36				
		GND					T37				
		GND					U33				
		GND					U35				
		GND					U38				
		GND					U39				
		GND					V32				
		GND					V34				
		GND					V36				
		GND					V37				



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1517	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
		GND					W33				
		GND					W38				
		GND					W39				
		GND					Y31				
		GND					Y32				
		GND					Y36				
		GND					Y37				
		GND					A2				
		GND					A3				
		GND					A4				
		GND					A5				
		GND					AA3				
		GND					AA4				
		GND					AA6				
		GND					AA8				
		GND					AB1				
		GND					AB2				
		GND					AB7				
		GND					AC3				
		GND					AC4				
		GND					AC8				
		GND					AD1				
		GND					AD10				
		GND					AD2				
		GND					AD6				
		GND					AD7				
		GND					AE3				
		GND					AE4				
		GND					AE6				
		GND					AE8				
		GND					AF1				
		GND					AF2				
		GND					AF9				
		GND					AG3				
		GND					AG4				
		GND					AG5				
		GND					AG6				
		GND					AG7				
		GND					AG8				
		GND					AH1				
		GND					AH2				
		GND					AH5				
		GND					AJ3				
		GND					AJ4				
		GND					AK1				
		GND					AK2				
		GND					AK5				
		GND					AL3				
		GND					AL4				
		GND					AM1				
		GND					AM2				
		GND					AM5				
		GND					AN3				
		GND					AN4				
		GND					AP1				
		GND					AP2				
		GND					AP5				
		GND					AR3				
		GND					AR4				
		GND					AT1				
		GND					AT2				
		GND					AT5				
		GND					AU3				
		GND					AU4				
		GND					AV1				
		GND					AV2				
		GND					B1				
		GND					B2				
		GND					B5				
		GND					C3				
		GND					C4				
		GND					D1				
		GND					D2				
		GND					D5				
		GND					E3				
		GND					E4				
		GND					F1				
		GND					F2				
		GND					F5				
		GND					G3				
		GND					G4				
		GND					H1				
		GND					H2				
		GND					H5				
		GND					J3				
		GND					J4				
		GND					K1				
		GND					K2				
		GND					K5				
		GND					L3				
		GND					L4				
		GND					M1				
		GND					M2				
		GND					M5				
		GND					N3				
		GND					N4				



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1517	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
		GND					N5				
		GND					P1				
		GND					P2				
		GND					P6				
		GND					P7				
		GND					R3				
		GND					R4				
		GND					R8				
		GND					T1				
		GND					T10				
		GND					T2				
		GND					T5				
		GND					T7				
		GND					U3				
		GND					U4				
		GND					U6				
		GND					U8				
		GND					V1				
		GND					V2				
		GND					V7				
		GND					W3				
		GND					W4				
		GND					W8				
		GND					Y1				
		GND					Y2				
		GND					Y5				
		GND					Y7				
		VCCP					AA21				
		VCCP					AA25				
		VCCP					AB15				
		VCCP					U16				
		VCCP					V13				
		VCCP					V22				
		VCCP					V25				
		VCCP					V27				
		VCCP					Y13				
		VCCP					Y27				
		VCCA_FPLL					AC30				
		VCCA_FPLL					AC9				
		VCCA_FPLL					Y30				
		VCCA_FPLL					AA9				
		VCCBAT					R33				
		VCC_AUX					AB14				
		VCC_AUX					AB26				
		VCC_AUX					U14				
		VCC_AUX					U28				
		VCCD_FPLL					AD31				
		VCCD_FPLL					AE9				
		VCCD_FPLL					W30				
		VCCD_FPLL					W9				
		VCCA_GXBL0					AF33				
		VCCA_GXBR0					AE7				
		VCCA_GXBL1					AB33				
		VCCA_GXBR1					AA7				
		VCC_H_GXBL0					AD33				
		VCC_H_GXBR0					AC7				
		VCC_H_GXBL1					Y33				
		VCC_H_GXBR1					W7				
		VCCL_GXBL0					AD34				
		VCCL_GXBL0					AD35				
		VCCL_GXBR0					AC5				
		VCCL_GXBR0					AC6				
		VCCL_GXBL1					Y34				
		VCCL_GXBL1					Y35				
		VCCL_GXBR1					W5				
		VCCL_GXBR1					W6				
		VCCR_GXBL					AC34				
		VCCR_GXBL					AC35				
		VCCR_GXBL					AG34				
		VCCR_GXBL					AG35				
		VCCR_GXBL					R35				
		VCCR_GXBR					AB5				
		VCCR_GXBR					AB6				
		VCCR_GXBR					AF5				
		VCCR_GXBR					AF6				
		VCCR_GXBR					PE				
		VCCT_GXBL0					AE34				
		VCCT_GXBL0					AF35				
		VCCT_GXBR0					AD6				
		VCCT_GXBR0					AE5				
		VCCT_GXBL1					AA34				
		VCCT_GXBL1					AB35				
		VCCT_GXBR1					AA5				
		VCCT_GXBR1					Y6				
		VCC					AA10				
		VCC					AA12				
		VCC					AA14				
		VCC					AA16				
		VCC					AA18				
		VCC					AA20				
		VCC					AA22				
		VCC					AA24				
		VCC					AA26				
		VCC					AB11				
		VCC					AB17				
		VCC					U10				



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1517	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
		VCC					U12				
		VCC					Y11				
		VCC					V15				
		VCC					V17				
		VCC					V23				
		VCC					V29				
		VCC					W10				
		VCC					W12				
		VCC					W14				
		VCC					W16				
		VCC					W18				
		VCC					W20				
		VCC					W22				
		VCC					W24				
		VCC					W26				
		VCC					W28				
		VCC					Y11				
		VCC					Y15				
		VCC					Y17				
		VCC					Y19				
		VCC					Y23				
		VCC					Y25				
		VCC					Y29				
		VCC					Y21				
		VCCI03A					AH29				
		VCCI03A					AJ30				
		VCCI03A					AK35				
		VCCI03A					AM30				
		VCCI03A					AP35				
		VCCI03A					AT35				
		VCCI03B					AK28				
		VCCI03B					AL27				
		VCCI03B					AN28				
		VCCI03B					AT28				
		VCCI03C					AJ24				
		VCCI03C					AL25				
		VCCI03C					AM24				
		VCCI03C					AP25				
		VCCI03C					AR24				
		VCCI03C					AU25				
		VCCI03D					AJ22				
		VCCI03D					AL21				
		VCCI03D					AM22				
		VCCI03D					AP21				
		VCCI03D					AR22				
		VCCI03D					AU21				
		VCCI04A					AG10				
		VCCI04A					AJ5				
		VCCI04A					AL5				
		VCCI04A					AN5				
		VCCI04A					AR5				
		VCCI04A					AU5				
		VCCI04B					AK13				
		VCCI04B					AM12				
		VCCI04B					AN10				
		VCCI04B					AN13				
		VCCI04B					AR12				
		VCCI04B					AT10				
		VCCI04C					AJ15				
		VCCI04C					AM15				
		VCCI04C					AR15				
		VCCI04C					AV15				
		VCCI04D					AJ19				
		VCCI04D					AK18				
		VCCI04D					AM19				
		VCCI04D					AN18				
		VCCI04D					AR19				
		VCCI04D					AT18				
		VCCI07A					E5				
		VCCI07A					G5				
		VCCI07A					H7				
		VCCI07A					J5				
		VCCI07A					L5				
		VCCI07A					M9				
		VCCI07B					C13				
		VCCI07B					D10				
		VCCI07B					F13				
		VCCI07B					G10				
		VCCI07B					K10				
		VCCI07B					L13				
		VCCI07C					F16				
		VCCI07C					G15				
		VCCI07C					K15				
		VCCI07C					L16				
		VCCI07D					B19				
		VCCI07D					D18				
		VCCI07D					E19				
		VCCI07D					G18				
		VCCI07D					H19				
		VCCI07D					M18				
		VCCI08A					B35				
		VCCI08A					G31				
		VCCI08A					G33				
		VCCI08A					K31				
		VCCI08A					K33				
		VCCI08A					P33				



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1517	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
		VCCIO8B					E28				
		VCCIO8B					E30				
		VCCIO8B					H30				
		VCCIO8B					K28				
		VCCIO8C					C25				
		VCCIO8C					D27				
		VCCIO8C					F25				
		VCCIO8C					G27				
		VCCIO8C					J25				
		VCCIO8C					M24				
		VCCIO8D					C21				
		VCCIO8D					D22				
		VCCIO8D					F21				
		VCCIO8D					G22				
		VCCIO8D					K22				
		VCCIO8D					L21				
		VCCPD3					AA27				
		VCCPD3					AA28				
		VCCPD3					AA29				
		VCCPD3					AB22				
		VCCPD3					AB23				
		VCCPD3					AB24				
		VCCPD3					AB30				
		VCCPD4A					AC10				
		VCCPD4A					AE10				
		VCCPD4BCD					AB12				
		VCCPD4BCD					AB13				
		VCCPD4BCD					AB16				
		VCCPD4BCD					AB18				
		VCCPD4BCD					AB19				
		VCCPD7A					P8				
		VCCPD7A					R10				
		VCCPD7BCD					T12				
		VCCPD7BCD					T13				
		VCCPD7BCD					T16				
		VCCPD7BCD					U18				
		VCCPD7BCD					U19				
		VCCPD8					R32				
		VCCPD8					T30				
		VCCPD8					U21				
		VCCPD8					U22				
		VCCPD8					U24				
		VCCPD8					U26				
		VCCPD8					U29				
		VCCPGM					N11				
		VCCPGM					AG29				
		GND					AA11				
		GND					AA13				
		GND					AA15				
		GND					AA17				
		GND					AA19				
		GND					AA23				
		GND					AA30				
		GND					AB10				
		GND					AC11				
		GND					AC14				
		GND					AC17				
		GND					AC20				
		GND					AC23				
		GND					AC26				
		GND					AC28				
		GND					AE30				
		GND					AF11				
		GND					AF14				
		GND					AF17				
		GND					AF20				
		GND					AF23				
		GND					AF26				
		GND					AF29				
		GND					AF30				
		GND					AG31				
		GND					AG9				
		GND					AJ11				
		GND					AJ14				
		GND					AJ17				
		GND					AJ20				
		GND					AJ23				
		GND					AJ26				
		GND					AJ29				
		GND					AJ32				
		GND					AJ8				
		GND					AM11				
		GND					AM14				
		GND					AM17				
		GND					AM20				
		GND					AM23				
		GND					AM26				
		GND					AM29				
		GND					AM32				
		GND					AM8				
		GND					AR11				
		GND					AR14				
		GND					AR17				
		GND					AR20				
		GND					AR23				
		GND					AR26				



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1517	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
		GND					AR29				
		GND					AR32				
		GND					AR8				
		GND					AV11				
		GND					AV14				
		GND					AV17				
		GND					AV20				
		GND					AV23				
		GND					AV26				
		GND					AV29				
		GND					AV32				
		GND					AV5				
		GND					AV8				
		GND					B11				
		GND					B14				
		GND					B17				
		GND					B20				
		GND					B23				
		GND					B26				
		GND					B29				
		GND					B32				
		GND					B8				
		GND					E11				
		GND					E14				
		GND					E17				
		GND					E20				
		GND					E23				
		GND					E26				
		GND					E29				
		GND					E32				
		GND					E8				
		GND					H11				
		GND					H14				
		GND					H17				
		GND					H20				
		GND					H23				
		GND					H26				
		GND					H29				
		GND					H32				
		GND					H8				
		GND					L11				
		GND					L14				
		GND					L17				
		GND					L20				
		GND					L23				
		GND					L26				
		GND					L29				
		GND					L32				
		GND					L8				
		GND					N8				
		GND					P11				
		GND					P14				
		GND					P17				
		GND					P20				
		GND					P23				
		GND					P26				
		GND					P29				
		GND					P32				
		GND					U11				
		GND					U13				
		GND					U15				
		GND					U17				
		GND					U20				
		GND					U23				
		GND					U25				
		GND					U27				
		GND					U30				
		GND					V10				
		GND					V12				
		GND					V14				
		GND					V16				
		GND					V18				
		GND					V21				
		GND					V24				
		GND					V26				
		GND					V28				
		GND					V30				
		GND					W11				
		GND					W13				
		GND					W15				
		GND					W17				
		GND					W19				
		GND					W23				
		GND					W25				
		GND					W27				
		GND					W29				
		GND					Y10				
		GND					Y12				
		GND					Y14				
		GND					Y16				
		GND					Y18				
		GND					Y20				
		GND					Y22				
		GND					Y24				
		GND					Y26				
		GND					Y28				



Bank Number	VREF	PinName/Function (2)	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1517	DQS for X8/X9	DQS for X16/ X18	DQS for X32/ X36	DDR3/DDR2 hard memory PHY (3)
		GND					W21				
		VCCR_GXBR					V6				
		VCCR_GXBR					V5				
		VCCR_GXBL					W35				
		VCCR_GXBL					W34				
		VCCD_FPLL					R9				
		VCCD_FPLL					T31				
		VCCA_FPLL					U9				
		VCCA_FPLL					V31				
		VCCL_GXBR2					R6				
		VCCL_GXBR2					R5				
		VCCL_GXBL2					T35				
		VCCL_GXBL2					T34				
		VCCH_GXBR2					R7				
		VCCH_GXBL2					T33				
		VCCA_GXBR2					U7				
		VCCA_GXBL2					V33				
		GND					H88				
		GND					T8				
		GND					H39				
		GND					T9				
		DNU					G37				
		DNU					B4				
		DNU					G36				
		DNU					B3				
		GND					F38				
		GND					C1				
		GND					F39				
		GND					C2				
		DNU					E37				
		DNU					D4				
		DNU					E36				
		DNU					D3				
		GND					D38				
		GND					E1				
		GND					D39				
		GND					E2				
		DNU					C37				
		DNU					F4				
		DNU					C36				
		DNU					F3				
		GND					U31				
		GND					G1				
		GND					U32				
		GND					G2				
		GND					W31				
		DNU					H4				
		GND					W32				
		DNU					H3				
		GND					P38				
		GND					J1				
		GND					P39				
		GND					J2				
		DNU					N37				
		DNU					K4				
		DNU					N36				
		DNU					K3				
		GND					M38				
		GND					L1				
		GND					M39				
		GND					L2				
		DNU					L37				
		DNU					M4				
		DNU					L36				
		DNU					M3				
		GND					K38				
		GND					N1				
		GND					K39				
		GND					N2				
		DNU					J37				
		GND					V9				
		DNU					J36				
		GND					V9				
		VCCT_GXBR2					U5				
		VCCT_GXBR2					T6				
		VCCT_GXBL2					V35				
		VCCT_GXBL2					U34				

Notes:

- (1) For more information about pin definitions and pin connection guidelines, refer to the [Arria V Device Family Pin Connection Guidelines](#).
- (2) GXB_REFCLK pin is not supported in current Quartus II version, but will be supported in future Quartus II release version.
- (3) RESET pin is only applicable for DDR3 device.



Pin Information for the Arria® V 5AGXMB3 Device
Version 1.7

Version Number	Date	Changes Made
1.0	9/2/2011	Initial release.
1.1	11/8/2011	Updated F1517 package - R9 and T31 changed from NC to VCCD_FPLL - U9 and V31 changed from NC to VCCA_FPLL
1.2	11/30/2011	Updated pin name nPERSTL1 to nPERSTR0
1.3	1/3/2012	Split VCC to VCC and VCCP
1.4	5/11/2012	Rename the CQ pins in DQS and hard memory PHY columns
1.5	7/6/2012	- Some of the NC pins changed to power, DNU, or GND pins. - Updated for production device support. Added two HMC address pins (A_4D_15 and A_7D_15) for 5AGXB3 production devices, these two pins are not applicable for 5AGXB3 ES devices.
1.6	9/3/2012	Removed unsupported nPERSTR0 pin
1.7	7/31/2015	Removed LPDDR2 hard memory PHY, RLDRAMII hard memory PHY, and QDRII hard memory PHY columns.